

1.10 แบบฟอร์มตัวอย่างเอกสารแสดง Table of Compliance

หมายเหตุ

1. ข้อมูลของ Table of Compliance อ้างอิงกับเอกสารดังต่อไปนี้
 - (1) SPECIFICATION NO.: RSUB-010/2560 (Rev. 1.0) SUBSTATION CONTROL AND PROTECTION SYSTEM (SCPS)
 - (2) ADDENDUM SPECIFICATION NO. RSUB-010/2560 (Rev. 1.0): SUBSTATION CONTROL AND PROTECTION SYSTEM (SCPS)
 - (3) SPECIFICATION NO.: RPRO - 011/2556 - Arc detection system
 - (4) เอกสารแนบท้ายเอกสารประกวดราคาอิเล็กทรอนิกส์ ข้อ 1.1 รายละเอียดและขอบเขตของงาน
2. เนื่องจากอุปกรณ์ Protective Relay ทั้งหมดของทุกสถานีไฟฟ้า และอุปกรณ์ระบบป้องกัน Arc Protection สำหรับ 22 kV Indoor Switchgear สำหรับสถานีไฟฟ้านวนคร 3 และสถานีไฟฟ้าบางปลา สำหรับการประกวดราคาครั้งนี้ กำหนดให้เสนอผลิตภัณฑ์ รุ่น และประเทศผู้ผลิต ตามที่ปรากฏอยู่ในเอกสารแนบท้ายเอกสารประกวดราคาอิเล็กทรอนิกส์ ข้อ 1.8 รายชื่อผลิตภัณฑ์อุปกรณ์ป้องกันสำหรับงานบำรุงรักษาสถานีไฟฟ้า (Acceptance Lists) ดังนั้น Table of Compliance ในการประกวดราคาครั้งนี้จะไม่มีรายละเอียดของข้อกำหนดในส่วนที่เป็นเนื้อหาเดียวกันกับที่ได้พิจารณาไปแล้วในการขึ้นทะเบียนอุปกรณ์

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
1	<p>Scope</p> <p>The detailed design submissions include:</p> <p>1) Schematic or Circuit Drawings (Station & Bay Level) – AC and DC distribution, instrument transformer & power circuit, measuring & instrumentation circuit, communication network, switching device tripping & closing circuits, protection circuits, manual synchronizing, alarm monitoring, system drawing, terminal function diagram, etc.</p>				
	<p>The Integrated SCPS shall be designed:</p> <p>1) To accommodate future substation upgrades, modifications, extension and expansion</p> <p>2) To achieve the objectives of IEC 61850 standard, i.e. interoperability, simple configuration & allocation of functions, and be future proof</p> <p>3) To ensure high reliability, performance and availability to minimize the interruption of service and functions</p> <p>4) To ensure that single failure at station level or one bay will not affect the operation and functions of other bays</p> <p>5) To maximize the utilization of substation information for supporting decision processes, engineering, operation & maintenance, fault investigation & diagnostics, and asset management</p> <p>6) To optimize the application of devices, panels, cabling and substation space</p> <p>7) To provide safe, secure and reliable operation of the substation throughout its total life cycle</p> <p>8) To withstand harsh operational substation environment such as the impact of electromagnetic interference and adverse environmental conditions.</p>				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
	<p>The Contractor shall design and implement the Integrated SCPS to facilitate:</p> <ol style="list-style-type: none"> 1) A distributed architecture using distributed station and bay intelligent devices, functions and applications 2) full system integration via substation communication network 3) fully automated functions 4) the separation of substation operator interface and engineering interface 5) the station level operator interface and SCADA gateway to perform station/supervisory monitoring and control operation of the substation 6) to support engineering workstations to manage the SCPS, communication network and substation information, and to provide applications utilizing the substation information 7) to support the application of Ethernet Technology and Information Communication Technology (ICT) such as Client-Server communication, Peer-to-Peer communication, web-based application, SCL, MMS (Manufacturer Message Specification), TCP/IP and Ethernet 8) IEC 61850 enabled technology including IEC 61850 conformant multifunction intelligent devices 9) self-monitoring, condition-based monitoring (optional) and management of intelligent devices, communication network and substation equipment. The Contractor shall propose condition-based monitoring as an option, together with a separate quotation, for PEA approval. 10) the integration of intelligent devices in single panel 11) the interoperability of IEDs from several different manufacturers to exchange information and use the information for their own functions. 12) the maximum utilization of information from IEDs. 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page																																										
1.2	<p>OBJECT MODELLING</p> <p>The Contractor shall perform the following typical tasks as part of the scope to abstractly model the substation data before mapping to mainstream communication protocols:</p> <ol style="list-style-type: none"> 1) Analyse PEA requirements, substation single line diagram, constraints and functions as specified in the specifications 2) Define the abstract model data and communication services model (i.e., Abstract Communication Service Interface, ACSI) based on the functions, SCADA points and requirements 3) Determine the functions allocation and the Logical Nodes (Refer to IEC 61850-7-4, 61850-7-410, and 61850-7-420 for the complete list of all IEC 61850 Logical Nodes as a reference) 4) Map the required functions to the Logical Node and their data 5) Determine the object modelling including the Logical Device modelling 6) Determine the information flows, and data exchanges within the substation 7) Create PEA SCL files (.icd., and .scd files) for the specific substation configuration based on .ssd file provided by PEA 8) Generate .cid file from .scd file and configured all the IEDs used for the substation 9) Determine the data sets and control blocks of the IEDs based on the above modelling 																																														
1.3 1.3.1 1.3.1.1	<p>ENVIRONMENTAL CONSTRAINTS AND ELECTROMAGNETIC</p> <p>Environmental Data</p> <p>All the equipment supplied in the scope of this project shall be compliant with the environment constraints listed in paragraph.</p> <p>Temperature requirements:</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Category</th> <th colspan="2" style="text-align: center;">I</th> <th colspan="2" style="text-align: center;">II</th> <th colspan="2" style="text-align: center;">III</th> </tr> </thead> <tbody> <tr> <td>Rated operation range ⁽¹⁾</td> <td style="text-align: center;">T1: +5°C</td> <td style="text-align: center;">T2: +40°C</td> <td style="text-align: center;">T1: -10°C</td> <td style="text-align: center;">T2: +55°C</td> <td style="text-align: center;">T1: -25°C</td> <td style="text-align: center;">T2: +70°C</td> </tr> <tr> <td>Maximum operation limits ⁽²⁾</td> <td style="text-align: center;">T3: +5°C</td> <td style="text-align: center;">T4: +40°C</td> <td style="text-align: center;">T3: -10°C</td> <td style="text-align: center;">T4: +55°C</td> <td style="text-align: center;">T1: -25°C</td> <td style="text-align: center;">T2: +70°C</td> </tr> <tr> <td>Relative humidity At + 23°C</td> <td colspan="2" style="text-align: center;">75 %</td> <td colspan="2" style="text-align: center;">80 %</td> <td colspan="2" style="text-align: center;">90 %</td> </tr> <tr> <td>Storage and transport conditions ⁽³⁾</td> <td style="text-align: center;">-40°C</td> <td style="text-align: center;">+70°C</td> <td style="text-align: center;">-40°C</td> <td style="text-align: center;">+70°C</td> <td style="text-align: center;">-40°C</td> <td style="text-align: center;">+70°C</td> </tr> <tr> <td>Operation location example</td> <td colspan="2" style="text-align: center;">Air conditioned room</td> <td colspan="2" style="text-align: center;">Non-air conditioned room</td> <td colspan="2" style="text-align: center;">Outdoor Equipment</td> </tr> </tbody> </table> <p><small>The three above definitions are extracted from IEC 60359.</small></p>	Category	I		II		III		Rated operation range ⁽¹⁾	T1: +5°C	T2: +40°C	T1: -10°C	T2: +55°C	T1: -25°C	T2: +70°C	Maximum operation limits ⁽²⁾	T3: +5°C	T4: +40°C	T3: -10°C	T4: +55°C	T1: -25°C	T2: +70°C	Relative humidity At + 23°C	75 %		80 %		90 %		Storage and transport conditions ⁽³⁾	-40°C	+70°C	-40°C	+70°C	-40°C	+70°C	Operation location example	Air conditioned room		Non-air conditioned room		Outdoor Equipment					
Category	I		II		III																																										
Rated operation range ⁽¹⁾	T1: +5°C	T2: +40°C	T1: -10°C	T2: +55°C	T1: -25°C	T2: +70°C																																									
Maximum operation limits ⁽²⁾	T3: +5°C	T4: +40°C	T3: -10°C	T4: +55°C	T1: -25°C	T2: +70°C																																									
Relative humidity At + 23°C	75 %		80 %		90 %																																										
Storage and transport conditions ⁽³⁾	-40°C	+70°C	-40°C	+70°C	-40°C	+70°C																																									
Operation location example	Air conditioned room		Non-air conditioned room		Outdoor Equipment																																										

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page																
1.3.1.2	<p>Class of Equipment</p> <p>According to these figures, the equipment to be supplied shall be compliant with tropical constraints.</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>TEST</th> <th>METHOD</th> <th>CLASS</th> <th>SEVERITY</th> </tr> </thead> <tbody> <tr> <td>Cold</td> <td>IEC60068-2-1</td> <td style="text-align: center;">-</td> <td>-25°C / 96 h (storage) +5°C / 96 h (in operation)</td> </tr> <tr> <td>Dry heat</td> <td>IEC60068-2-2</td> <td style="text-align: center;">-</td> <td>+70°C / 96 h (storage) +70°C / 96 h (in operation)</td> </tr> <tr> <td>Damp heat</td> <td>IEC60068-2-78</td> <td style="text-align: center;">-</td> <td>+55°C / 95% / 96 h (storage) +40°C / 93% / 96 h (in operation)</td> </tr> </tbody> </table>	TEST	METHOD	CLASS	SEVERITY	Cold	IEC60068-2-1	-	-25°C / 96 h (storage) +5°C / 96 h (in operation)	Dry heat	IEC60068-2-2	-	+70°C / 96 h (storage) +70°C / 96 h (in operation)	Damp heat	IEC60068-2-78	-	+55°C / 95% / 96 h (storage) +40°C / 93% / 96 h (in operation)				
TEST	METHOD	CLASS	SEVERITY																		
Cold	IEC60068-2-1	-	-25°C / 96 h (storage) +5°C / 96 h (in operation)																		
Dry heat	IEC60068-2-2	-	+70°C / 96 h (storage) +70°C / 96 h (in operation)																		
Damp heat	IEC60068-2-78	-	+55°C / 95% / 96 h (storage) +40°C / 93% / 96 h (in operation)																		
	<p>ELECTROMAGNETIC ENVIRONMENTAL STANDARDS</p> <p>Isolation tests: voltage withstand</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>TEST</th> <th>METHOD</th> <th>CLASS</th> <th>SEVERITY</th> </tr> </thead> <tbody> <tr> <td>Rated insulation voltage</td> <td>IEC60255-27</td> <td style="text-align: center;">-</td> <td>500 VDC</td> </tr> <tr> <td>Insulation impedance</td> <td>IEC60255-27</td> <td style="text-align: center;">-</td> <td>100 MΩ</td> </tr> </tbody> </table>	TEST	METHOD	CLASS	SEVERITY	Rated insulation voltage	IEC60255-27	-	500 VDC	Insulation impedance	IEC60255-27	-	100 MΩ								
TEST	METHOD	CLASS	SEVERITY																		
Rated insulation voltage	IEC60255-27	-	500 VDC																		
Insulation impedance	IEC60255-27	-	100 MΩ																		
	<p>ISOLATION TESTS: DIELECTRIC WITHSTAND</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>TEST</th> <th>METHOD</th> <th>CLASS</th> <th>SEVERITY</th> </tr> </thead> <tbody> <tr> <td>Rated insulation voltage</td> <td>IEC60255-27</td> <td style="text-align: center;">-</td> <td>2 kV/50 Hz/1 mm</td> </tr> </tbody> </table>	TEST	METHOD	CLASS	SEVERITY	Rated insulation voltage	IEC60255-27	-	2 kV/50 Hz/1 mm												
TEST	METHOD	CLASS	SEVERITY																		
Rated insulation voltage	IEC60255-27	-	2 kV/50 Hz/1 mm																		
	<p>Isolation tests: impulse voltage withstand</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>TEST</th> <th>METHOD</th> <th>CLASS</th> <th>SEVERITY</th> </tr> </thead> <tbody> <tr> <td>Unidirectional surge</td> <td>IEC61000-4-5</td> <td style="text-align: center;">-</td> <td>5 kV (supply)</td> </tr> <tr> <td>1.2 / 50 μs (voltage)</td> <td>IEC60255-27</td> <td style="text-align: center;">-</td> <td>5 kV (I/O)</td> </tr> <tr> <td>8 / 20 μs (current)</td> <td></td> <td style="text-align: center;">-</td> <td>1 kV (communication)</td> </tr> </tbody> </table>	TEST	METHOD	CLASS	SEVERITY	Unidirectional surge	IEC61000-4-5	-	5 kV (supply)	1.2 / 50 μs (voltage)	IEC60255-27	-	5 kV (I/O)	8 / 20 μs (current)		-	1 kV (communication)				
TEST	METHOD	CLASS	SEVERITY																		
Unidirectional surge	IEC61000-4-5	-	5 kV (supply)																		
1.2 / 50 μs (voltage)	IEC60255-27	-	5 kV (I/O)																		
8 / 20 μs (current)		-	1 kV (communication)																		
	<p>Immunity tests against radiated electromagnetic field disturbances</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>TEST</th> <th>METHOD</th> <th>CLASS</th> <th>SEVERITY</th> </tr> </thead> <tbody> <tr> <td>Radiated electromagnetic field disturbance</td> <td>IEC61000-4-3 IEC60255-26</td> <td style="text-align: center;">3</td> <td>30 V/m (15 V/m for talky-walky frequencies)</td> </tr> </tbody> </table>	TEST	METHOD	CLASS	SEVERITY	Radiated electromagnetic field disturbance	IEC61000-4-3 IEC60255-26	3	30 V/m (15 V/m for talky-walky frequencies)												
TEST	METHOD	CLASS	SEVERITY																		
Radiated electromagnetic field disturbance	IEC61000-4-3 IEC60255-26	3	30 V/m (15 V/m for talky-walky frequencies)																		
	<p>Immunity tests against recurrent fast transient</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>TEST</th> <th>METHOD</th> <th>CLASS</th> <th>SEVERITY</th> </tr> </thead> <tbody> <tr> <td>Electrical fast transient burst</td> <td>IEC61000-4-4</td> <td style="text-align: center;">4</td> <td>4 kV (supply) 4 kV (input/output) 4 kV (communication)</td> </tr> </tbody> </table>	TEST	METHOD	CLASS	SEVERITY	Electrical fast transient burst	IEC61000-4-4	4	4 kV (supply) 4 kV (input/output) 4 kV (communication)												
TEST	METHOD	CLASS	SEVERITY																		
Electrical fast transient burst	IEC61000-4-4	4	4 kV (supply) 4 kV (input/output) 4 kV (communication)																		

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page								
	<p>1 MHz damped oscillatory wave tests</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">TEST</th> <th style="text-align: center;">METHOD</th> <th style="text-align: center;">CLASS</th> <th style="text-align: center;">SEVERITY</th> </tr> </thead> <tbody> <tr> <td>1 MHz damped oscillatory wave</td> <td>IEC60255-26</td> <td style="text-align: center;">3</td> <td>2.5 kV CM (supply) 2.5 kV (input/output) 2.5 kV (communication)</td> </tr> </tbody> </table>	TEST	METHOD	CLASS	SEVERITY	1 MHz damped oscillatory wave	IEC60255-26	3	2.5 kV CM (supply) 2.5 kV (input/output) 2.5 kV (communication)				
TEST	METHOD	CLASS	SEVERITY										
1 MHz damped oscillatory wave	IEC60255-26	3	2.5 kV CM (supply) 2.5 kV (input/output) 2.5 kV (communication)										
	<p>Electrostatic discharge</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">TEST</th> <th style="text-align: center;">METHOD</th> <th style="text-align: center;">CLASS</th> <th style="text-align: center;">SEVERITY</th> </tr> </thead> <tbody> <tr> <td>Electrostatic discharge</td> <td>IEC61000-4-2 IEC60255-26</td> <td style="text-align: center;">4</td> <td>15 kV contact</td> </tr> </tbody> </table>	TEST	METHOD	CLASS	SEVERITY	Electrostatic discharge	IEC61000-4-2 IEC60255-26	4	15 kV contact				
TEST	METHOD	CLASS	SEVERITY										
Electrostatic discharge	IEC61000-4-2 IEC60255-26	4	15 kV contact										
	<p>Mechanical shock</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">TEST</th> <th style="text-align: center;">METHOD</th> <th style="text-align: center;">CLASS</th> <th style="text-align: center;">SEVERITY</th> </tr> </thead> <tbody> <tr> <td>Semi-sinusoidal shock in operation</td> <td>IEC60068-2-27</td> <td style="text-align: center;">-</td> <td>15 g / 11 ms 1 shock per sense and per axe</td> </tr> </tbody> </table>	TEST	METHOD	CLASS	SEVERITY	Semi-sinusoidal shock in operation	IEC60068-2-27	-	15 g / 11 ms 1 shock per sense and per axe				
TEST	METHOD	CLASS	SEVERITY										
Semi-sinusoidal shock in operation	IEC60068-2-27	-	15 g / 11 ms 1 shock per sense and per axe										
	<p>Fast transient tests for measuring relays with single input</p> <p>TEST METHOD CLASS SEVERITY</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">TEST</th> <th style="text-align: center;">METHOD</th> <th style="text-align: center;">CLASS</th> <th style="text-align: center;">SEVERITY</th> </tr> </thead> <tbody> <tr> <td>Fast transient disturbance test</td> <td>IEC60255-3</td> <td style="text-align: center;">3</td> <td>2.5 kV CM (supply) 2.5 kV (input/output) 2.5 kV (communication)</td> </tr> </tbody> </table>	TEST	METHOD	CLASS	SEVERITY	Fast transient disturbance test	IEC60255-3	3	2.5 kV CM (supply) 2.5 kV (input/output) 2.5 kV (communication)				
TEST	METHOD	CLASS	SEVERITY										
Fast transient disturbance test	IEC60255-3	3	2.5 kV CM (supply) 2.5 kV (input/output) 2.5 kV (communication)										
	<p>Vibrations</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">TEST</th> <th style="text-align: center;">METHOD</th> <th style="text-align: center;">CLASS</th> <th style="text-align: center;">SEVERITY</th> </tr> </thead> <tbody> <tr> <td>Sinusoidal vibrations (in operation)</td> <td>IEC60068-2-6</td> <td></td> <td>10 to 55 Hz / 0,15 mm or 2 gn 2 hours per axe</td> </tr> </tbody> </table>	TEST	METHOD	CLASS	SEVERITY	Sinusoidal vibrations (in operation)	IEC60068-2-6		10 to 55 Hz / 0,15 mm or 2 gn 2 hours per axe				
TEST	METHOD	CLASS	SEVERITY										
Sinusoidal vibrations (in operation)	IEC60068-2-6		10 to 55 Hz / 0,15 mm or 2 gn 2 hours per axe										
1.3.1.3	<p>Ventilation</p> <p>The specified equipment shall be able to operate in normal continuous service without forced ventilation under the following environmental conditions. In order to increase the reliability a forced ventilation shall be included. In case of a failure of the forced ventilation equipment, an alarm shall be sent to the substation control unit.</p>												
	<p>The formation of condensed water on the circuit boards, modules, covering and in general in the apparatus shall be avoided.</p>												
	<p>All equipment covered by this specification shall be selected and especially treated, as required, for used in a tropical climate and for protection against fungus growth and corrosion during shipment and storage.</p>												

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
1.3.2	<p>Physical Environment and Service Conditions</p> <p>All SCPS equipment shall be housed in dust proof and water proof housing cabinet to IEC 60529, protection class IP50 or better for indoor, and protection class IP65 for outdoor, but shall be adequately ventilated to prevent damage to any component when exposed to high ambient temperatures.</p>				
1.3.2.1	<p>Outdoor Devices</p> <p>All MUs & Smart I/Os (Merging Units and Smart I/Os) plus their power supply modules and supporting LAN plus all necessary connectors, extenders, terminators and LAN assembly devices shall be classed as SCPS outdoor devices.</p> <p>The proposed SCPS outdoor devices shall be suitable for continuous operation in Thailand's tropical monsoon climate and shall also be subject to severe thunderstorms, heavy industrial pollution and high levels of airborne dust.</p> <p>The proposed SCPS outdoor devices shall be conformally coated to meet the specified climatic conditions (Class C2 in accordance with IEC 60870-2-2 and class 3K7 in accordance with IEC 60721), and shall have been type tested for continuous operation over the following environmental conditions:</p>				
	<ul style="list-style-type: none"> • Temperature : -10°C to +70°C (test with IEC 60068-2-1, 60068-2-2, 60068-2-3 and 60068-2-14) • Temperature Gradient : Up to 30°C (test with IEC 60068-2-1, 60068-2-2, 60068-2-3 and 60068-2-14) • Relative Humidity : Up to 95% at 40°C (test with IEC 60068-2-30 and 60068-2-38) • Cyclic Damp Heat : +40°C to +25°C at 95% Relative Humidity (test with IEC 60068-2-30 and 60068-2-38) • Absolute Humidity : Up to 29 g/m³ (test with IEC 60068-2-30 and 60068-2-38) • Vibration (sinusoidal) : 2 g acceleration 9 to 350 Hz (test with IEC 60068-2-6) • Shock : 15 g 11 ms (test with IEC 60068-2-27) <p>The above referenced type tests shall be carried out by suitably accredited test laboratories, which are independent of the bidder and SCPS manufacturer. The certified copies of test certificates and test results shall be included as part of the bidder's proposal. Failure to conform to this requirement shall be constitute for rejection of the bidder's proposal</p>				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
1.3.2.2	<p>Indoor Devices</p> <p>The SCPS Systems, IED relay, BCU, IED device and Local User Interface (HMI) plus their power supplies and all supporting equipment shall be classed as SCPS indoor devices.</p> <p>Indoor devices, in air-conditioned rooms, shall be suitable for continuous operation over the following environmental conditions:</p> <ul style="list-style-type: none"> • Operating Temperature : between 20 °C and 27 °C. • Relative humidity : between 40% and 60%. <p>Malfunctioning of air conditioning equipment may cause the temperature to increase to 40 °C with humidity up to 95%.</p> <p>Therefore, indoor devices shall be suitable for operation under these conditions for a continuous period of up to 24 hours. So, the same IEC standards as mentioned in the previous chapter (outdoor devices), shall be also the standards for indoor devices.</p>				
1.3.3	<p>Electromagnetic Environmental Precautions</p> <p>The correct operation of the substation control system and protection equipment shall not be limited or restricted by environmental influences. Therefore the substation control system and protection equipment shall be designed to withstand the influence of:</p> <ol style="list-style-type: none"> 1) Switching operations in primary circuits 2) Lightning stroke in HV line 3) Lightning stroke in grounded component 4) Switching operations in secondary circuits 5) Faults occurring within or near the substation producing ground currents and ground potential rise 6) Radio interferences produced by hand-held walkie-talkie type radio communication equipment (P = 2 Watt) in the frequency range 80/160/460 MHz at 30 cm distance <p>The measures to be taken to reduce EMI (electromagnetic interferences) are listed below:</p>				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
1.3.3.1	<p>Primary circuits</p> <p>Most of the measures listed below are necessary to protect HV equipment but they have also a beneficial effect on interference to secondary circuits.</p> <ol style="list-style-type: none"> 1) Protection against lightning strokes 2) Protection by lightning arrests 3) Configuration of earthing systems 4) Use of VT and CT with acceptable transient response 				
1.3.3.2	<p>Secondary circuits</p> <p>In secondary circuits the following measures shall be at least adopted to reduce EMI.</p> <ol style="list-style-type: none"> 1) Separation of the various circuits connected with devices having different degrees of interference level (power supplies, input and output network circuits, earth connections). 2) Galvanic separation of the I/O signal circuits and of the auxiliary supply circuit lines with isolating relays, optodiodes, transformers, coupling condensers. 3) Screens of the cables from switch bays shall not be laid to adjacent unshielded circuits. 				
	<p>Further following measures are to be taken in the installation:</p> <ol style="list-style-type: none"> 1) Separation (spacing out or different routes) of power circuits (e.g. AC power supply cables) from control cables. 2) Separate cabling of the low frequency and high frequency circuits 3) Earthing connection of equipment shall be kept as short as possible and generally separated from the cables. For HV equipment at least two connections are necessary. 4) Increasing density of the earthing mat meshes where the occurrence of high transient current is more likely (lightning arresters, spark gaps, VT and CT). 5) Impedance between equipment (VT and CT etc.) and the earth network shall be as low as possible. 6) Cable route shall run as far as possible from and not parallel to busbars or power cables. 7) The forward and return conductor of the same circuit shall run in the same cable. 8) Twisted pairs or quad cables shall be adopted whenever possible (i.e. low current circuits and data lines). 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
	9) Screened cables shall run as close together as possible. 10) DC auxiliary supply cables shall be laid in a radial configuration better than a ring. 11) Screen of perfectly homogeneous with low resistance, protected of the external high frequency electric and magnetic field for the cables shall be provided. 12) Screen of the cables shall have low coupling impedance within the interference frequency range. 13) Earthing of the screen shall have very low impedance with adequate section minimum length and optimum contact arrangements.				
1.3.4	Immunity to Electrical Stress and Disturbance The electrical and electronic components of the proposed SCPS shall satisfy the requirements for insulation, isolation, and immunity from electromagnetic interference, radiated disturbance and electrostatic discharge stated in the following sub-clauses 1.3.4.1 and 1.3.4.2. The ability to meet these requirements shall be verified by type tests.				
1.3.4.1	Minimum Insulation of Equipment Exposed Equipment: "Exposed" equipment terminals may be interconnected without special protection of the insulation. Equipment terminals shall be considered "Exposed" when they directly connected to: 1) Current or voltage transformer secondary circuits. 2) Substation 125 V DC battery supplies. 3) Conductor longer than 100 meters within the substation. 4) Substation 125 V DC supplies.				
	Controlled Exposure Equipment: "Controlled Exposure" equipment terminals may be interconnected when special conditions are met. Equipment terminals shall be considered "Controlled Exposure" terminals when all of the following criteria are met: 1) The rated voltage of the associated circuit does not exceed 32 V AC or 48 V DC. 2) Direct galvanic connections to exposed equipment terminals are made using a suitable barrier device which has the isolation ratings required for exposed equipment. 3) Terminals are galvanically connected to circuits which less than 100 meters in length and are themselves isolated from other components in a way that meets the requirements of exposed equipment.				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page																																																																																
	<p>The SCPS equipment shall meet or exceed the insulation requirements shown in Table 1.1:</p> <p>Table 1.1 – MINIMUM INSULATION REQUIREMENTS</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th rowspan="2" style="text-align: center;">Requirements</th> <th rowspan="2" style="text-align: center;">Test Standard</th> <th colspan="2" style="text-align: center;">Specified Details</th> </tr> <tr> <th style="text-align: center;">Exposed Equipment</th> <th style="text-align: center;">Controlled Exposure Equipment</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;">Rated Insulation Voltage</td> <td style="text-align: center;">IEC 60255-5 Table I</td> <td style="text-align: center;">500 V</td> <td style="text-align: center;">60 V</td> </tr> <tr> <td style="text-align: center;">Dielectric Test Voltage</td> <td style="text-align: center;">IEC 60255-5 Table I Series B (Clause 6)</td> <td style="text-align: center;">2.0 kV r.m.s.</td> <td style="text-align: center;">1.0 kV r.m.s.</td> </tr> <tr> <td style="text-align: center;">Insulation Resistance Test</td> <td style="text-align: center;">IEC 60255-5 (Clause 7)</td> <td style="text-align: center;">Required</td> <td style="text-align: center;">Required</td> </tr> <tr> <td style="text-align: center;">Impulse Voltage Test</td> <td style="text-align: center;">IEC 60255-5 (Clause 8)</td> <td style="text-align: center;">5 kV, 1.2/50 μs 0.5 J</td> <td style="text-align: center;">5 kV, 1.2/50 μs 0.5 J</td> </tr> </tbody> </table>	Requirements	Test Standard	Specified Details		Exposed Equipment	Controlled Exposure Equipment	Rated Insulation Voltage	IEC 60255-5 Table I	500 V	60 V	Dielectric Test Voltage	IEC 60255-5 Table I Series B (Clause 6)	2.0 kV r.m.s.	1.0 kV r.m.s.	Insulation Resistance Test	IEC 60255-5 (Clause 7)	Required	Required	Impulse Voltage Test	IEC 60255-5 (Clause 8)	5 kV, 1.2/50 μ s 0.5 J	5 kV, 1.2/50 μ s 0.5 J																																																														
Requirements	Test Standard			Specified Details																																																																																	
		Exposed Equipment	Controlled Exposure Equipment																																																																																		
Rated Insulation Voltage	IEC 60255-5 Table I	500 V	60 V																																																																																		
Dielectric Test Voltage	IEC 60255-5 Table I Series B (Clause 6)	2.0 kV r.m.s.	1.0 kV r.m.s.																																																																																		
Insulation Resistance Test	IEC 60255-5 (Clause 7)	Required	Required																																																																																		
Impulse Voltage Test	IEC 60255-5 (Clause 8)	5 kV, 1.2/50 μ s 0.5 J	5 kV, 1.2/50 μ s 0.5 J																																																																																		
1.3.4.2	<p>Immunity from Electromagnetic Interference, Radiated Disturbance and Electrostatic Discharge</p> <p>The SCPS shall be designed for safe operation in the harsh environment of a high voltage substation and shall conform to the immunity, susceptibility and interference requirements shown in Table 1.2:</p> <p>Data communication ports shall be demonstrated to withstand disturbance test without permanent corruption of data, and subsequent delay of data transfer.</p> <p>Table 1.2 – IMMUNITY, SUSCEPTIBILITY AND INTERFERENCE REQUIREMENTS</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th style="text-align: center;">Requirements</th> <th style="text-align: center;">Test Standard</th> <th style="text-align: center;">Class or Level</th> <th style="text-align: center;">Specified Details</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;">High Voltage Impulse</td> <td style="text-align: center;">IEC 60060-1</td> <td></td> <td style="text-align: center;">5 kV, 0.5 J</td> </tr> <tr> <td style="text-align: center;">Electrical Disturbances (1 MHz Burst)</td> <td style="text-align: center;">IEC 60255-22-1</td> <td style="text-align: center;">Class 3</td> <td style="text-align: center;">2.5 kV CM 1.0 kV DM</td> </tr> <tr> <td style="text-align: center;">Electrostatic Discharge Immunity</td> <td style="text-align: center;">IEC 61000-4-2</td> <td style="text-align: center;">Level 3 Level 4</td> <td style="text-align: center;">8 kV air 8 kV direct</td> </tr> <tr> <td style="text-align: center;">Radiated Immunity</td> <td style="text-align: center;">IEC 61000-4-3</td> <td style="text-align: center;">Level 3</td> <td style="text-align: center;">80 MHz-1 GHz</td> </tr> <tr> <td></td> <td style="text-align: center;">IEC 60255-22-3</td> <td style="text-align: center;">Class 3</td> <td style="text-align: center;">27-500 MHz</td> </tr> <tr> <td></td> <td style="text-align: center;">IEC 61000-4-3</td> <td style="text-align: center;">Class 3</td> <td style="text-align: center;">50 KHz-1 GHz</td> </tr> <tr> <td></td> <td style="text-align: center;">ENV 50204 (GSM)</td> <td style="text-align: center;">Level 3</td> <td style="text-align: center;">10V/m 2W at 0.6m</td> </tr> <tr> <td style="text-align: center;">Fast Transient/Burst Immunity</td> <td style="text-align: center;">IEC 61000-4-4</td> <td style="text-align: center;">Level 4</td> <td style="text-align: center;">4 kV</td> </tr> <tr> <td></td> <td style="text-align: center;">IEC 60255-22-4</td> <td style="text-align: center;">Class 4</td> <td style="text-align: center;">4 kV</td> </tr> <tr> <td></td> <td style="text-align: center;">ANSI/IEEE C37.90.1</td> <td style="text-align: center;">-</td> <td style="text-align: center;">4-5 kV</td> </tr> <tr> <td style="text-align: center;">Surge Immunity</td> <td style="text-align: center;">IEC 61000-4-5</td> <td style="text-align: center;">Level 4</td> <td style="text-align: center;">2 kV/4 kV</td> </tr> <tr> <td style="text-align: center;">Conducted Immunity</td> <td style="text-align: center;">IEC 61000-4-6</td> <td style="text-align: center;">Level 3</td> <td style="text-align: center;">10 V</td> </tr> <tr> <td style="text-align: center;">Harmonics Emissions</td> <td style="text-align: center;">IEC 61000-4-7</td> <td style="text-align: center;">-</td> <td style="text-align: center;">Required for ac powered systems</td> </tr> <tr> <td style="text-align: center;">Power Frequency Magnetic Field Immunity</td> <td style="text-align: center;">IEC 61000-4-8</td> <td style="text-align: center;">Level 4</td> <td style="text-align: center;">30 A/m</td> </tr> <tr> <td style="text-align: center;">Pulse Magnetic Field Immunity</td> <td style="text-align: center;">IEC 61000-4-9</td> <td style="text-align: center;">Level 5</td> <td style="text-align: center;">1000 A/m</td> </tr> <tr> <td style="text-align: center;">Damped Oscillatory Magnetic Field Immunity</td> <td style="text-align: center;">IEC 61000-4-10</td> <td style="text-align: center;">Level 4</td> <td style="text-align: center;">30 A/m</td> </tr> <tr> <td style="text-align: center;">Oscillatory Transient Immunity</td> <td style="text-align: center;">IEC 61000-4-12</td> <td style="text-align: center;">Level 4</td> <td style="text-align: center;">Ring Wave</td> </tr> <tr> <td></td> <td style="text-align: center;">IEC 61000-4-12</td> <td style="text-align: center;">Level 3</td> <td style="text-align: center;">Damped Oscillatory</td> </tr> <tr> <td></td> <td style="text-align: center;">ANSI/IEEE C37.90.1</td> <td style="text-align: center;">-</td> <td style="text-align: center;">2.5 kV</td> </tr> </tbody> </table>	Requirements	Test Standard	Class or Level	Specified Details	High Voltage Impulse	IEC 60060-1		5 kV, 0.5 J	Electrical Disturbances (1 MHz Burst)	IEC 60255-22-1	Class 3	2.5 kV CM 1.0 kV DM	Electrostatic Discharge Immunity	IEC 61000-4-2	Level 3 Level 4	8 kV air 8 kV direct	Radiated Immunity	IEC 61000-4-3	Level 3	80 MHz-1 GHz		IEC 60255-22-3	Class 3	27-500 MHz		IEC 61000-4-3	Class 3	50 KHz-1 GHz		ENV 50204 (GSM)	Level 3	10V/m 2W at 0.6m	Fast Transient/Burst Immunity	IEC 61000-4-4	Level 4	4 kV		IEC 60255-22-4	Class 4	4 kV		ANSI/IEEE C37.90.1	-	4-5 kV	Surge Immunity	IEC 61000-4-5	Level 4	2 kV/4 kV	Conducted Immunity	IEC 61000-4-6	Level 3	10 V	Harmonics Emissions	IEC 61000-4-7	-	Required for ac powered systems	Power Frequency Magnetic Field Immunity	IEC 61000-4-8	Level 4	30 A/m	Pulse Magnetic Field Immunity	IEC 61000-4-9	Level 5	1000 A/m	Damped Oscillatory Magnetic Field Immunity	IEC 61000-4-10	Level 4	30 A/m	Oscillatory Transient Immunity	IEC 61000-4-12	Level 4	Ring Wave		IEC 61000-4-12	Level 3	Damped Oscillatory		ANSI/IEEE C37.90.1	-	2.5 kV				
Requirements	Test Standard	Class or Level	Specified Details																																																																																		
High Voltage Impulse	IEC 60060-1		5 kV, 0.5 J																																																																																		
Electrical Disturbances (1 MHz Burst)	IEC 60255-22-1	Class 3	2.5 kV CM 1.0 kV DM																																																																																		
Electrostatic Discharge Immunity	IEC 61000-4-2	Level 3 Level 4	8 kV air 8 kV direct																																																																																		
Radiated Immunity	IEC 61000-4-3	Level 3	80 MHz-1 GHz																																																																																		
	IEC 60255-22-3	Class 3	27-500 MHz																																																																																		
	IEC 61000-4-3	Class 3	50 KHz-1 GHz																																																																																		
	ENV 50204 (GSM)	Level 3	10V/m 2W at 0.6m																																																																																		
Fast Transient/Burst Immunity	IEC 61000-4-4	Level 4	4 kV																																																																																		
	IEC 60255-22-4	Class 4	4 kV																																																																																		
	ANSI/IEEE C37.90.1	-	4-5 kV																																																																																		
Surge Immunity	IEC 61000-4-5	Level 4	2 kV/4 kV																																																																																		
Conducted Immunity	IEC 61000-4-6	Level 3	10 V																																																																																		
Harmonics Emissions	IEC 61000-4-7	-	Required for ac powered systems																																																																																		
Power Frequency Magnetic Field Immunity	IEC 61000-4-8	Level 4	30 A/m																																																																																		
Pulse Magnetic Field Immunity	IEC 61000-4-9	Level 5	1000 A/m																																																																																		
Damped Oscillatory Magnetic Field Immunity	IEC 61000-4-10	Level 4	30 A/m																																																																																		
Oscillatory Transient Immunity	IEC 61000-4-12	Level 4	Ring Wave																																																																																		
	IEC 61000-4-12	Level 3	Damped Oscillatory																																																																																		
	ANSI/IEEE C37.90.1	-	2.5 kV																																																																																		

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page																			
4	CONTROL AND PROTECTION SYSTEM FUNCTIONAL REQUIREMENTS																							
4.1	GENERAL REQUIREMENTS																							
4.1.1	System Average Life Time and Life Cycle 3) The Contractor shall state the expectancy support for spare parts. Availability of these parts shall be guaranteed for a period of no less than ten (10) years from the date of the latest delivery of equipment containing these parts or assemblies. The Contractor shall commit to notifying PEA at least six (6) months in advance of any part or assembly becoming unavailable for purchase, in order to enable PEA to stock up on that item.																							
4.1.2	Substation Environment The SCPS shall be designed to withstand harsh operational HV substation environment. All IEDs shall be certified by an independent competent entity and type tested as protection grade devices. Unless specified otherwise, all station clients shall be certified and type tested as industrial grade equipment.																							
	The following is the summary of the required electrical technological conformance and mechanical requirements for substation environment considerations: <table border="1" style="margin-left: 40px;"> <thead> <tr> <th>System Requirements</th> <th>Type of Test</th> </tr> </thead> <tbody> <tr> <td rowspan="3">Mechanical Stress (Vibration and shock)</td> <td>Vibration Test</td> </tr> <tr> <td>Shock and bump test</td> </tr> <tr> <td>Seismic Test</td> </tr> <tr> <td>Insulation</td> <td>High Voltage Test and Impulse Voltage Tests</td> </tr> <tr> <td rowspan="7">Electromagnetic Compatibility - Immunity</td> <td>Damped oscillatory wave test</td> </tr> <tr> <td>Fast transient test</td> </tr> <tr> <td>Surge Test</td> </tr> <tr> <td>Conducted radio interference test</td> </tr> <tr> <td>Electrostatic discharge test</td> </tr> <tr> <td>Variations and interruptions in AC and DC auxiliary voltage</td> </tr> <tr> <td>Electromagnetic fields</td> </tr> <tr> <td>50Hz power frequency magnetic fields</td> </tr> <tr> <td rowspan="2">Electromagnetic Compatibility - Noise Emission</td> <td>Conducted RF interference on power supply terminals and radiated interference. Harmonics for AC supply</td> </tr> <tr> <td>Flicker</td> </tr> </tbody> </table>	System Requirements	Type of Test	Mechanical Stress (Vibration and shock)	Vibration Test	Shock and bump test	Seismic Test	Insulation	High Voltage Test and Impulse Voltage Tests	Electromagnetic Compatibility - Immunity	Damped oscillatory wave test	Fast transient test	Surge Test	Conducted radio interference test	Electrostatic discharge test	Variations and interruptions in AC and DC auxiliary voltage	Electromagnetic fields	50Hz power frequency magnetic fields	Electromagnetic Compatibility - Noise Emission	Conducted RF interference on power supply terminals and radiated interference. Harmonics for AC supply	Flicker			
System Requirements	Type of Test																							
Mechanical Stress (Vibration and shock)	Vibration Test																							
	Shock and bump test																							
	Seismic Test																							
Insulation	High Voltage Test and Impulse Voltage Tests																							
Electromagnetic Compatibility - Immunity	Damped oscillatory wave test																							
	Fast transient test																							
	Surge Test																							
	Conducted radio interference test																							
	Electrostatic discharge test																							
	Variations and interruptions in AC and DC auxiliary voltage																							
	Electromagnetic fields																							
50Hz power frequency magnetic fields																								
Electromagnetic Compatibility - Noise Emission	Conducted RF interference on power supply terminals and radiated interference. Harmonics for AC supply																							
	Flicker																							
4.1.3	System Performance The SCPS shall be designed such that system performance, including system availability and system reliability set forth in Clause 4.3 is satisfied.																							
4.1.4	Operation and Maintenance (Maintainability) The SCPS shall be designed such that system maintainability, including future extension and upgrade, system flexibility, system scalability, and substation access control and cyber security measure, which are described further in Chapter 11, is satisfied.																							
4.1.5	Operational and System Safety The SCPS shall be designed so that it is compliant with PEA safety rules and other safety standards, such as IEC 61010-1. Hence, safety of personnel, plants and equipment is fully and highly aware of																							
4.1.6	System Configurations The SCPS shall be designed by taking into account the following important implementation issues which are described further in details in Annex 1 Control and Protection System Configurations.																							

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
4.2	SYSTEM HIERARCHICAL STRUCTURE The system architecture shall be configured based on multi-tier hierarchical structure. The multi-tier hierarchical structure levels as a minimum for the SCPS are: 1) Level 1 – Station Level 2) Level 2 – Bay Level				
	Bidders shall be able to propose a solution, e.g., using a redundant box (Redbox), so that the systems are connected and functioning as required. When a Redbox is used with a relay, due to hardware or speed issues with massive SV traffic, a relay shall be connected to a station-level side, not to a process-level side				
	Redundant equipment should be on different source of power supply from main				
	Relay of 115 kV systems will be separated into Main 1 and Main 2 Relays. The mechanism control and protection of selecting either Main 1/BCU and or Main 2/BCU to perform the functions of control and protection, in case of commanding/controlling from SCADA center, shall be configured within the IEDs.				
(ADDENDUM)	Network redundancy protocol for each topology shall be Parallel Redundancy Protocol (PRP) and/or High Availability Seamless Redundancy (HSR) protocol for zero-time recovery.				
(ADDENDUM)	Time synchronization shall be accomplished via IEEE 1588 or IRIG-B.				
	An Engineering Workstation might have 1 connection port, but can interchangeably connect to main or redundant connection.				
	The Contractor shall provide IED servers, i.e. Bay Controller, at bay level to perform all allocated distributed functions of bay level functionality.				
	Engineering workstation shall be provided to ensure secure information flow with the SCADA/DMS located at ADDC engineering offices. The station bus shall provide the communication network (IEC 61850), integration, data exchange and data flow between station-to-bay level and bay-to-bay level.				
4.2.1	Station Level The main characteristics of the station devices shall be; 1) multifunction IED 2) use of IED technology 3) IEDs conform with IEC 61850 standard 4) interface to user through device HMI and remote client such as Engineering Workstation integrated as part of SCPS through networked communication. 5) flexible applications and functions 6) capability to interoperate with other IEDs from several different manufacturers to exchange information and use the information for own functions 7) IEC 61850 server which provide rich source of IED information such as settings, configuration information, events, alarms, power system information, fault records, COMTRADE fault waveform files, etc. a. Station-level data management, data storage, and data retrieval mechanisms: include support for IEC 61850 information models, historical data, configuration data, diagnostic and maintenance data, and files (e.g. non-operational, configuration, application programs, software updates). b. Station-wide collection of maintenance data, diagnostic data, and statistical data for (1) primary system components, (2) secondary system components, and (3) application functions				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
	<p>8) self-monitoring and supervision</p> <p>9) certified and type tested as protection grade device</p> <p>10) enact programmable logic: any IED or other devices which can act as a programmable logical controller should be able to be programmed using methods stipulated in IEC 61131</p> <p>11) powered from substation auxiliary DC system</p> <p>12) interfaced to the station bus via hardened managed Ethernet Switch</p> <p>13) failure not affecting other functions or bay level</p> <p>14) Hardwired parallel connections to the primary equipment or apparatus (switchgears and instrument transformers). ("This part belongs to the Bay Level").</p>				
	<p>Local Repository and System Logs: The following data structures form the core of the SCPS system. They include six system logs that chronologically capture the stations operational history.</p>				
	<p>1) Local Repository</p> <p>The Repository represents the present state of the station. It shall hold the IEC 61850-based information models for the primary system and secondary system components, including off-the-shelf and programmable logic applications.</p>				
	<p>IEC 61850 provides information models for most of the available system data, and those models can be extended to include new components. Although it is not desirable for the Repository to store all data available in the station, it must at least include all data subscribed by station or enterprise clients.</p>				
	<p>The SCPS Systems shall implement all of IEC 61850's ASCII service models, with the following exceptions: GSSE Control Block and the Sampled Value Class Model. Clients and servers using the Repository shall find all of the other services available. The Repository must be maintained in a replaceable flash memory module. Battery power is an unacceptable approach to maintaining non-volatile data memory.</p>				
	<p>2) StatusLog</p> <p>The StatusLog is a chronological record of recent changes in either primary or secondary system status, either commanded or uncommanded.</p> <ul style="list-style-type: none"> - The StatusLog shall hold events for the most recent 100 records. It shall be backed up in archives, each archive containing events for a particular month. - All StatusLog entries shall include a time-stamp, identify the system item that changed, identify the new status, and identify the cause (or agent) of the change. 				
	<p>3) CommandLog</p> <ul style="list-style-type: none"> - The CommandLog is a chronological record of recent control commands to station equipment (e.g. Trip, Close, Open, Close, Raise, Lower, Enable, Disable, and set-points) issued by System Clients. -The CommandLog shall hold commands issued during the most recent 100 days. It shall be backed up in archives, each archive containing control commands for a particular month. - All CommandLog entries shall include a time-stamp, identify the system item being controlled, identify the state being commanded, and identify the source of the control command. 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
	4) ChangeLog - The ChangeLog is a chronological record of recent changes made by an HMI unit to system and device configuration parameters. The ChangeLog shall hold changes issued during the most recent 100 days. It is backed up in archives, each archive containing changes for a particular month. All ChangeLog entries shall include a time-stamp, identify the system or IED parameter being changed, identify the new state, and identify the source (i.e. agent) of the change.				
	5) SubLog The SubLog is a chronological record of changes made by clients using the IEC 61850 substitution services. The SubLog shall include all substitution events, including a return to process values, that have occurred during the most recent 100 days.				
	6) FileLog The FileLog is a chronological record of recent file transfers and file deletions involving any intelligent station device (e.g. BCU, SCPS Systems, HMI). The FileLog shall include all such file events that have occurred during the most recent 100 days. It shall be backed up in archives, each archive containing file events for a particular month. All FileLog entries shall include a time-stamp, identify the file reference, identify the action taken, and identify the source (i.e. agent) of the action.				
	The station functions and the Logical Nodes (LN) shall be distributed and allocated to station level devices. 1) Engineering Workstation (EWS) with HMI 2) SCADA gateway to PEA SCADA/DMS: Protocol for communications between the SCADA/DMS and substations is DNP3.0 over IP. Communications between the SCADA gateway and IED servers are via SCPS Systems 3) SCPS Systems 4) Station optical fibre ring bus, providing the means by which devices and applications exchange data within the station 5) Station-operator HMI or station level operator interface (SLOI) 6) Time synchronization server with GPS receiver				
	Operating Systems (OS) of HMI and Engineering Workstation shall be Windows. OS of Gateway and SCPS Systems shall be a stable one, such as Linux.				
4.2.2	Bay Level The main characteristics of the bay devices shall be; 1) multifunction IED 2) use of IED technology 3) IED conform with IEC 61850 standard 4) performing distributed bay level functionalities 5) interface to user through device HMI and remote client such as Engineering Workstation 6) compact with integrated functionalities in one device. Integrated as part of SCPS through networked communication. 7) flexible applications and functions 8) ability to activate or deactivate the main functions 9) capability to interoperate with other IEDs from several different manufacturers to exchange information and use the information for own functions 10) IEDs which provide rich source of IED information such as settings, configuration information, events, alarms, power system information, fault records, COMTRADE fault waveform files, etc.				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
	<p>11) self-monitoring and supervision</p> <p>12) certified and type tested as protection grade device</p> <p>13) enact programmable logic.interfaced to the station bus via hardened managed Ethernet Switch</p> <p>14) possibility to minimise the use of external electromechanical auxiliary relays and lockout relay. powered from substation 125V auxiliary DC system interfaced to the station bus via hardened managed Ethernet Switch</p> <p>15) proxy to legacy devices or non-IEDs (as an alternative, a dedicated protocol converter with generic logical nodes shall be provided)</p> <p>16) failure not affecting other functions within or external to the particular bay or level</p> <p>17) hardwired parallel connections to the primary equipment or apparatus (switchgears and instrument transformers). The IEC 61850 process bus shall also be implemented.</p>				
	The bay functions and the Logical Nodes shall be distributed and allocated to bay level devices, i.e. protection devices and single control device.				
	Data flow of operational real time data and control, through client-servers communication, shall be ensured between IEDs and station level clients. Each IED shall be able to support multiple clients (at least 5 clients). The IEDs shall be able to provide configuration information and IED specific information including COMTRADE files, IED native individual parameters, etc. to the Engineering Workstation at station level.				
(ADDENDUM)	<p>Typical of Protective relay functions can be categorized as:</p> <p>1) 115 kV Bus Protection (Main 1 and Main 2) 87B, 95B</p> <p>2) 115 kV Line Protection (Main 1 and Main 2) 21/21N, 67/67N, 25, 27/59, 79, 50BF</p> <p>3) 115 kV Transformer Protection (Main 1 and Main 2) 87T,87REF, 50/51, 50N/51N, 51GB, 50BF</p> <p>4) Others 115 kV Protections</p> <p>5) 22 or 33 kV Feeder Protection 50/51, 50N/51N, 67/67N, 25, 79, 50BF, 81, 27/59, 60</p> <p>6) Others MV Protections</p> <p>All protection functions of the protective relay shall be completely programmed from manufacturer's factory</p>				
4.2.3	System Logical Architecture				
	The main features of the SCPS architecture are:				
	1) distributed architecture using Ethernet Local Area Network (LAN) station bus with 1 Gbits/s optical fibre ring topology				
	2) All IEDs and clients are connected to the station bus via hardened managed Ethernet Switch certified to IEC 61850-3 and IEEE 1613				
	3) Distributed multifunction bay IEDs or relays integrated in single panel per bay				
	4) Transformer Automatic Voltage Control/Regulator device shall be located in a separate panel				
	5) For AIS (Air Insulated Switchgear?) substations, the bay panels may be located in Prefabricated relay house(s) at the substation switchyard				
	6) Local displays (mimic screen) in independent panel at each Prefabricated relay house to provide safe operational awareness for operation and maintenance purposes, unless PEA states otherwise				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
	7) SCPS Systems to perform station level functions including control and automation functions				
	8) Station Level Operator Interface (SLOI) to perform Station-operator HMI				
	9) Gateway for communication interface with PEA SCADA/DMS. The gateway shall be supplied by the Contractor				
	10) Engineering Workstation to manage the SCPS, communication network and substation information, and to provide applications utilizing the substation information				
	11) Time synchronization server (NTP, and IEEE 1588 or IRIG-B, with the latest version, if IEEE 1588 is not available, Server) synchronizing with GPS master clock receiver to provide time source for time synchronization of all SCPS components. Depending on synchronization standard used, a dedicated communication interface and network might be provided for time synchronization, such as for IRIG-B.				
4.2.4	Supporting SCADA/DMS Operations The Dispatchers shall be able to control station equipment and gather system data via DNP3.0 over IP command and polling messages transmitted from the SCADA/DMS control centre. Implementation of DNP 3.0 over IP protocol shall meet at least ALL DNP 3.0 over IP standard requirements.				
	The DNP communications shall be supported by the Gateway via a process that links and converts IEC 61850 data from the Local Repository to the desired DNP values and formats. These resulting DNP data shall be stored and maintained in a separate DNP database that can be accessed by DNP data communication services. This approach provides two significant advantages: (1) the continual DNP data conversion process is independent of (i.e. not interrupted by) DNP message processing, and (2) the DNP database allows the HMI to quickly respond to message requests. DNP commands shall likewise be translated to use IEC 61850 control blocks and procedures for controlling system equipment.				
4.6	SYSTEM SECURITY The software system shall be the latest version, and free of viruses when the Contractor delivers. During the guarantee period, the Contractor shall keep the software up-to-date. After the guarantee period, the Contractor shall propose an option to update the software to PEA; the update shall not be via the internet.				
	The Contractor shall recommend security capabilities that conform with standard IEC 62351 for SCPS security, and IEC 27032 for other relevant Information Technology (IT) operations. The recommendations shall provide reasonable protection for a reasonable cost, so as to significantly reduce the risk of damage, loss of information, unauthorized use, or impairment of use or control of the station facility.				
4.9	AUTOMATIC CONTROL FUNCTIONS Automatic function is like programmable inside the memory of Relay or BCU, and shall be included in Relay or BCU, for example, Sequential Switching, Load Shedding, Automatic Transfer Switch etc.				
	The automation function shall be programmed and performed at station level in the station intelligent electronic device IED. However, the automated sequence may be initiated by operator at the Station-operator HMI or Station Level Operator Interface (SLOI).				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page						
4.10	MEASUREMENT FUNCTIONS Measurement of electrical quantities such as voltage, current, active power, reactive power, etc. shall be taken directly, without separate interposing or transducers, by the IED from substation current and/or voltage transformer(s). Measurement from DC and 400V AC voltages may be derived from substation auxiliary AC and DC systems.										
	The measurement functions are modelled and grouped according to the IEC 61850 Logical Node Group which begins with the character M.										
4.11	MONITORING FUNCTIONS The monitoring function provides substation device or equipment indications and information										
4.12	CONTROL INTERLOCKING FUNCTIONS All station and bay interlocking schemes shall be provided and controlled by intelligent electronic control devices using GOOSE messages.										
4.13 (ADDENDUM)	INTERFACING, ADVANCE ANALYTICS AND ARCHIVING FUNCTIONS The interfacing and archiving functions are performed at the following locations: 1)Station-operator HMI or station level operator interface (SLOI) 2)SCADA gateway for remote interface to PEA SCADA/DMS 3)Prefabricated relay housing screen mimic (If applicable) 4)Engineering workstation 5)Emergency control interface (Backup Mimic)										
(ADDENDUM)	<p>Table 4.5 – Interfacing Issues</p> <table border="1"> <thead> <tr> <th>System Component</th> <th>Comment:</th> </tr> </thead> <tbody> <tr> <td>Station-operator HMI or Station Level Operator Interface (SLOI)</td> <td>Station Level Operator Interface (SLOI) shall provide station-operator HMI functions such as: substation local control, monitoring, and handling of local alarms and events. The detail requirement shall be referred to the relevant Section of the Specification, see Table 11 (“should be made sure that this Table is put in this Specification”)</td> </tr> <tr> <td>SCADA Gateway(SGW)</td> <td>The SCADA Gateway forms the interface between the substation and Network Control Centre(-), and between the substation and other substations using standard SCADA protocol. This is interconnection device that supports the full stack of relevant protocol and security to interface or communicate with the SCADA/DMS and other future systems that access to station for operation and maintenance.</td> </tr> </tbody> </table>	System Component	Comment:	Station-operator HMI or Station Level Operator Interface (SLOI)	Station Level Operator Interface (SLOI) shall provide station-operator HMI functions such as: substation local control, monitoring, and handling of local alarms and events. The detail requirement shall be referred to the relevant Section of the Specification, see Table 11 (“should be made sure that this Table is put in this Specification”)	SCADA Gateway(SGW)	The SCADA Gateway forms the interface between the substation and Network Control Centre(-), and between the substation and other substations using standard SCADA protocol. This is interconnection device that supports the full stack of relevant protocol and security to interface or communicate with the SCADA/DMS and other future systems that access to station for operation and maintenance.				
System Component	Comment:										
Station-operator HMI or Station Level Operator Interface (SLOI)	Station Level Operator Interface (SLOI) shall provide station-operator HMI functions such as: substation local control, monitoring, and handling of local alarms and events. The detail requirement shall be referred to the relevant Section of the Specification, see Table 11 (“should be made sure that this Table is put in this Specification”)										
SCADA Gateway(SGW)	The SCADA Gateway forms the interface between the substation and Network Control Centre(-), and between the substation and other substations using standard SCADA protocol. This is interconnection device that supports the full stack of relevant protocol and security to interface or communicate with the SCADA/DMS and other future systems that access to station for operation and maintenance.										

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page														
	<table border="1"> <thead> <tr> <th>System Component</th> <th>Comment:</th> </tr> </thead> <tbody> <tr> <td>Engineering Workstation – Engineering Unit Interface (EUI) (See more detail: in Clause 8.4.)</td> <td> <p>Engineer Interface Unit. It is the IEC 61850 client that gathers information from various IED devices and enables the operator to supervise and have local or remote control. Include OPC-Server.</p> <p>Engineering Workstation manages the SCPS, communication network and substation information, and to provide applications utilizing the substation information. The Engineering Workstation functions are:</p> <ol style="list-style-type: none"> 1) Real time data historian & analysis 2) Communication network management 3) System access control and cyber security management 4) SCPS monitoring, diagnostic and maintenance 5) Substation IED interrogation and monitoring 6) Substation Protection, Automation and Control system and IED configuration management 7) GOOSE messaging management (configurable via the workstation) 8) Disturbance and fault information handling, analysis and evaluation (via Program Fault Record) 9) Engineering HMI 10) Web browser and interface (for equipment setting) 11) Substation status display 12) Sequence of event and alarm analysis 13) Data archiving, trending and historical analysis 14) Automatic fault report generation and notification 15) Substation equipment monitoring 16) Substation documentation management <p>The HMI software shall be capable of IED devices management function such as setting and resetting of all Protective relays and other by remote via Router.</p> </td> </tr> </tbody> </table>	System Component	Comment:	Engineering Workstation – Engineering Unit Interface (EUI) (See more detail: in Clause 8.4.)	<p>Engineer Interface Unit. It is the IEC 61850 client that gathers information from various IED devices and enables the operator to supervise and have local or remote control. Include OPC-Server.</p> <p>Engineering Workstation manages the SCPS, communication network and substation information, and to provide applications utilizing the substation information. The Engineering Workstation functions are:</p> <ol style="list-style-type: none"> 1) Real time data historian & analysis 2) Communication network management 3) System access control and cyber security management 4) SCPS monitoring, diagnostic and maintenance 5) Substation IED interrogation and monitoring 6) Substation Protection, Automation and Control system and IED configuration management 7) GOOSE messaging management (configurable via the workstation) 8) Disturbance and fault information handling, analysis and evaluation (via Program Fault Record) 9) Engineering HMI 10) Web browser and interface (for equipment setting) 11) Substation status display 12) Sequence of event and alarm analysis 13) Data archiving, trending and historical analysis 14) Automatic fault report generation and notification 15) Substation equipment monitoring 16) Substation documentation management <p>The HMI software shall be capable of IED devices management function such as setting and resetting of all Protective relays and other by remote via Router.</p>														
System Component	Comment:																		
Engineering Workstation – Engineering Unit Interface (EUI) (See more detail: in Clause 8.4.)	<p>Engineer Interface Unit. It is the IEC 61850 client that gathers information from various IED devices and enables the operator to supervise and have local or remote control. Include OPC-Server.</p> <p>Engineering Workstation manages the SCPS, communication network and substation information, and to provide applications utilizing the substation information. The Engineering Workstation functions are:</p> <ol style="list-style-type: none"> 1) Real time data historian & analysis 2) Communication network management 3) System access control and cyber security management 4) SCPS monitoring, diagnostic and maintenance 5) Substation IED interrogation and monitoring 6) Substation Protection, Automation and Control system and IED configuration management 7) GOOSE messaging management (configurable via the workstation) 8) Disturbance and fault information handling, analysis and evaluation (via Program Fault Record) 9) Engineering HMI 10) Web browser and interface (for equipment setting) 11) Substation status display 12) Sequence of event and alarm analysis 13) Data archiving, trending and historical analysis 14) Automatic fault report generation and notification 15) Substation equipment monitoring 16) Substation documentation management <p>The HMI software shall be capable of IED devices management function such as setting and resetting of all Protective relays and other by remote via Router.</p>																		
	<table border="1"> <thead> <tr> <th>System Component</th> <th>Comment:</th> </tr> </thead> <tbody> <tr> <td>Merging Unit (MU)</td> <td> <p>The Merging Unit is a physical unit used for time-dependent combination of current and/or voltage data from secondary converter. A merging unit can be a component part of the instrument transformer or a separate unit.</p> <p>Typical locations for MU shall be as follows:</p> <ol style="list-style-type: none"> 1) MV switchgear: low-voltage compartment of each cubicle (mounted on MV switchgear). 2) HV switchgear: marshalling cubicles/function boxes, local control cabinet. 3) HV/MV power transformer: local control cabinet. 4) Automatic switching capacitor bank: local control cabinet. </td> </tr> <tr> <td>Protocol Converter (i.e., IEC 61850 Gateway)</td> <td>Element that allows the integration of devices that have not yet implemented the IEC 61850 architecture. The IEC 61850 Gateway collects the information through the communication protocol of the devices and it adapts this information by integrating it in the new IEC 61850 format.</td> </tr> <tr> <td>Communication Network</td> <td>The communication network is constituted by an Ethernet network (ISO/IEC 8802-3), as it is shown in Part 8-1, 9-1, 9-2 of the IEC 61850 standard.</td> </tr> <tr> <td>Ethernet Switch</td> <td>They are the local network connection elements. Enable network access to the different units of the system avoiding collisions.</td> </tr> <tr> <td>Time Reference Unit (GPS clock)</td> <td>Time server with GPS synchronization. It is the main synchronization source of the system. NTP, and IEEE 1588 (PTP-the latest version) or IRIG-B protocol enable the synchronization through a local communication network of the different devices. The Contractor shall provide time accuracy corresponding to the proposed synchronization protocol for PEA approval.</td> </tr> <tr> <td>Intelligent Electronic Device (IED)</td> <td>IEC 61850 client: which receives the information from the bay level IEDs, and support the communication with the SCADA system, thus executing the logic at station level. The RTU functions and the logic may be separated into independent IEDs.</td> </tr> </tbody> </table>	System Component	Comment:	Merging Unit (MU)	<p>The Merging Unit is a physical unit used for time-dependent combination of current and/or voltage data from secondary converter. A merging unit can be a component part of the instrument transformer or a separate unit.</p> <p>Typical locations for MU shall be as follows:</p> <ol style="list-style-type: none"> 1) MV switchgear: low-voltage compartment of each cubicle (mounted on MV switchgear). 2) HV switchgear: marshalling cubicles/function boxes, local control cabinet. 3) HV/MV power transformer: local control cabinet. 4) Automatic switching capacitor bank: local control cabinet. 	Protocol Converter (i.e., IEC 61850 Gateway)	Element that allows the integration of devices that have not yet implemented the IEC 61850 architecture. The IEC 61850 Gateway collects the information through the communication protocol of the devices and it adapts this information by integrating it in the new IEC 61850 format.	Communication Network	The communication network is constituted by an Ethernet network (ISO/IEC 8802-3), as it is shown in Part 8-1, 9-1, 9-2 of the IEC 61850 standard.	Ethernet Switch	They are the local network connection elements. Enable network access to the different units of the system avoiding collisions.	Time Reference Unit (GPS clock)	Time server with GPS synchronization. It is the main synchronization source of the system. NTP, and IEEE 1588 (PTP-the latest version) or IRIG-B protocol enable the synchronization through a local communication network of the different devices. The Contractor shall provide time accuracy corresponding to the proposed synchronization protocol for PEA approval.	Intelligent Electronic Device (IED)	IEC 61850 client: which receives the information from the bay level IEDs, and support the communication with the SCADA system, thus executing the logic at station level. The RTU functions and the logic may be separated into independent IEDs.				
System Component	Comment:																		
Merging Unit (MU)	<p>The Merging Unit is a physical unit used for time-dependent combination of current and/or voltage data from secondary converter. A merging unit can be a component part of the instrument transformer or a separate unit.</p> <p>Typical locations for MU shall be as follows:</p> <ol style="list-style-type: none"> 1) MV switchgear: low-voltage compartment of each cubicle (mounted on MV switchgear). 2) HV switchgear: marshalling cubicles/function boxes, local control cabinet. 3) HV/MV power transformer: local control cabinet. 4) Automatic switching capacitor bank: local control cabinet. 																		
Protocol Converter (i.e., IEC 61850 Gateway)	Element that allows the integration of devices that have not yet implemented the IEC 61850 architecture. The IEC 61850 Gateway collects the information through the communication protocol of the devices and it adapts this information by integrating it in the new IEC 61850 format.																		
Communication Network	The communication network is constituted by an Ethernet network (ISO/IEC 8802-3), as it is shown in Part 8-1, 9-1, 9-2 of the IEC 61850 standard.																		
Ethernet Switch	They are the local network connection elements. Enable network access to the different units of the system avoiding collisions.																		
Time Reference Unit (GPS clock)	Time server with GPS synchronization. It is the main synchronization source of the system. NTP, and IEEE 1588 (PTP-the latest version) or IRIG-B protocol enable the synchronization through a local communication network of the different devices. The Contractor shall provide time accuracy corresponding to the proposed synchronization protocol for PEA approval.																		
Intelligent Electronic Device (IED)	IEC 61850 client: which receives the information from the bay level IEDs, and support the communication with the SCADA system, thus executing the logic at station level. The RTU functions and the logic may be separated into independent IEDs.																		
(ADDENDUM)	<table border="1"> <thead> <tr> <th>System Component</th> <th>Comments</th> </tr> </thead> <tbody> <tr> <td>Emergency Control Interface, if requested by PEA</td> <td> <p>Emergency Control for each bay (for CB operation only) in the event of Control Bay Control IED failure.</p> <ol style="list-style-type: none"> 1) The Emergency Control interface includes: Pushbutton to trip or open the circuit breaker 2) Pushbutton to close the circuit breaker with hardwire interlocking command supervision and synchronizing bypass switch 3) Hardwire connection </td> </tr> </tbody> </table>	System Component	Comments	Emergency Control Interface, if requested by PEA	<p>Emergency Control for each bay (for CB operation only) in the event of Control Bay Control IED failure.</p> <ol style="list-style-type: none"> 1) The Emergency Control interface includes: Pushbutton to trip or open the circuit breaker 2) Pushbutton to close the circuit breaker with hardwire interlocking command supervision and synchronizing bypass switch 3) Hardwire connection 														
System Component	Comments																		
Emergency Control Interface, if requested by PEA	<p>Emergency Control for each bay (for CB operation only) in the event of Control Bay Control IED failure.</p> <ol style="list-style-type: none"> 1) The Emergency Control interface includes: Pushbutton to trip or open the circuit breaker 2) Pushbutton to close the circuit breaker with hardwire interlocking command supervision and synchronizing bypass switch 3) Hardwire connection 																		

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
4.14.4	<p>Technical IEC 61850 Functions</p> <p>1) All devices shall conform with IEC 61850 standard and the following requirements:</p> <ul style="list-style-type: none"> a. Interoperability, i.e. ability to communicate and to exchange information with other IEDs from several different manufacturers and use the information for own functions b. Free configuration and allocation of functions Future proof, independent of communication technology and evolving system requirements c. Successfully pass IED conformance test based on IEC 61850 part10 as necessary d. Information management by standardizing the Data Models and Abstract Communication Services e. Engineering and configuration management using XML based Substation Configuration Language (SCL) and IEC 61850 conformant Engineering Tools. f. Client-Server communication including relevant services such as reporting, data sets, control blocks and self-description via MMS protocol g. Peer-to-peer communication using IEC61850-9-2 SV and IEC61850 GOOSE tripping channels. h. IED native Ethernet port that support all relevant IEC 61850 protocols i. Engineering access, event report collection, and non-IEC 61850 setting transfer via TCP/IP mechanisms <p>2) The following device information shall be provided:</p> <ul style="list-style-type: none"> a. IED Capability Description (ICD) b. Configured IED capability Description (CID) c. Model Implementation Conformance Statement (MICS) d. Protocol Implementation Conformance Statement (PICS) e. Protocol Implementation Extra Information for Testing (PIXIT) <p>4) The IED shall support IEC 61850 standard in terms of the following:</p> <ul style="list-style-type: none"> a. Buffered reports supported b. Unbuffered reports supported c. Customization of the reports and data sets d. Ability to freely rename data sets, and logical devices e. Ability to add prefix and suffix to logical nodes f. Use specific logical node name for commonly used information rather than generic data references (such as GGIO) g. Ability to change data sets and reporting configuration via Configuration Tool h. Ability to download CID file directly into IED via Configuration Tool i. Ability to download CID file directly into IED via Ethernet using standard TCP/IP mechanism from remote such as from HMI. j. Flexible configuration of data sets k. Ability to setting logical devices, logical nodes, and their contents l. Ability for user to query IED directly and to verify which IEC 61850 configuration file (.CID file) is active within the IED 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
	<p>5) The IED shall also support the IEC 61850 GOOSE implementation in terms of the followings:</p> <ul style="list-style-type: none"> a. At least 8 of unique GOOSE messages capable to be published b. At least 24 GOOSE messages to be subscribed c. Capability of monitoring GOOSE message quality d. Capability of processing incoming data elements and their associated quality e. Capability of monitoring message and data quality as permissive prior to use of the incoming data. At the time of configuration, the end user can choose to ignore the possibly corrupted data if the data or message quality fails to prevent an unwanted operation. f. Capability of creating GOOSE data set that include Boolean values and non-Boolean data type, such as Analog values g. Capability of accepting and processing data sets from other IEDs that contain Boolean and non-Boolean data types h. Ability to support priority tagging of GOOSE messages for optimizing latency through Ethernet Switch. i. Ability to support VLAN identifiers to facilitate segregation of GOOSE traffic on Ethernet network. j. Ability to support custom editing of data sets published in the GOOSE messages. k. Ability to change data sets, GOOSE parameters, GOOSE publication, and GOOSE subscription via Configuration Tool. l. Ability to support Recovery delay demands acc. to IEC 61850-5 Ed. 2 on Ethernet network. <p>6) The Network shall also support the Recovery Time implementation in terms of the followings:</p> <ul style="list-style-type: none"> a. IEC 61850-8-1 Station Bus. <ul style="list-style-type: none"> • GOOSE traffic not delayed beyond a critical threshold due to failover. • Unless stated otherwise, PRP and/or HSR provide seamless recovery, i.e. zero recovery time, on Station Bus for demanding applications. If a RedBox (Redundant Box) is needed in the proposed topology, the Bidder shall provide specification and quotation of the RedBox for PEA approval. 				
	<p>7) The IEDs specified in the specifications are for the followings:</p> <ul style="list-style-type: none"> a. Control devices, i.e. station and bay control devices b. IED Protective relay or devices c. IED for Protection for each bay level shall be physically independent. d. The IEDs are devices incorporating one or more processors with the capability to receive or send data/control from or to an external source. The IEDs shall also be capable for peer-to-peer communication (IEC61850 GOOSE) and Client/Server communication. (Such as Reporting by Exception) e. All IEDs supplied shall pass the IEC 61850 Conformance Test based on IEC61850-10. The IEC 61850 Conformance Test Certificate from an independent laboratory shall be provided as evidence and part of the tender submission. The laboratory shall be accredited by UCA International Users Group with ISO/IEC17025 certification with certification. f. The IEDs shall not show any non-conformance to IEC 61850-3, 6, 7-1, 7-2, 7-3, 7-4&8-1, and 9-2 (2011). g. Markings and Labelling Data. Clearly inscribed labels or markings shall be provided on the devices to describe the manufacturer name, model number, application and ratings. 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
	<p>8) Device Electrical Parameter Values.</p> <p>The standard device electrical parameter values are:</p> <ul style="list-style-type: none"> a. The device shall be suitable for operation using substation auxiliary DC system. b. The device shall not mal-operate on DC auxiliary supply interruption or application/restoration or when energized from inverted polarities. c. The device shall also be stable and not affected by slow decay, surges, dips, ripples, spikes, capacitive coupling, DC earth fault, transient and switching disturbances. Indication shall be made available in the event of DC failure. 				
4.14.5	<p>Station Level Devices Functions</p> <p>The main characteristics of the station devices shall be:</p> <ul style="list-style-type: none"> 1) Multifunction IED 2) Use of IED technology. 3) IED conform with IEC 61850 standard 4) Interface to user through device HMI and remote client such as Engineering Workstation 5) Integrated as part of SCPS through networked communication flexible applications and functions. 6) Capability to interoperate with other IEDs from several different manufacturers to exchange information and use the information for own functions. 7) IEC 61850 server which provide rich source of IED information such as settings, configuration information, events, alarms, power system information, fault records, COMTRADE fault waveform files and can be send COMTRADE files to HMI by automatically, etc. 8) Self-monitoring and supervision. 9) Certified and type tested as protection grade device. 10) Interfaced to the station bus via hardened managed Ethernet Switch. 11) Failure not affecting other functions or bay level. 12) The station functions and the Logical Nodes shall be distributed and allocated to station level devices. 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
4.14.6 (ADDENDUM)	Bay Level Devices Functions 1)Switchgear Manual Close and Open Control Operation a.Control of Circuit Breaker b.Control of Isolator Switch c.Control Mode Selection (Local/Remote/OFF) d.Select-Before-Execute Control Command Procedure- Manual Close Synchronism & Voltage Check e.Synchronism check - Voltage difference, Phase angle difference, Slip frequency/difference f.Voltage check				
	2)Dead line-live bus (DLLB), Live line-dead bus (LLDB), Dead line-dead bus (DLDB)				
	3)Interlocking (Command Supervision) 27UV a.Bay Interlocking b.Station-Wide Interlocking (Peer-to-peer) c.Under voltage Interlocking				
	4)Event and Alarm Handling				
	5)Monitoring a.Switchgear Status Indication and Mimic b.Bay Alarm Annunciator				
	6)Bay IED Operations and Status, CB Alarm a.Auto and Manual Trip Counter b.IED Self Supervision and Monitoring				
	8)Measurements a.Current (Amps) b.Voltage (V) c.Power (MW and MVAR) d.Frequency (Hz) e.Power Factor				
4.14.6.1	IED Bay Control Unit (BCU) without Protective Relay This specification refers to smart bay implementations as BCU. As such, they are assumed to have sufficient local processing, memory, programmable logic, and communication resources to support expanded responsibilities and capabilities. In case of an IED BCU (without Protective Relay), the programmable logic should be included in the IED. When these resources are combined with support for the IEC 61850 communications standard, BCU gain flexibility and power that can significantly elevate their system roles and provide enormous flexibility.				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
4.14.8	<p>Enhanced Automation Functions</p> <p>The SCPS systems shall perform enhanced automation functions, including the following:</p> <ol style="list-style-type: none"> 1) Heartbeat function for IED health and on-line status monitoring 2) Maintenance of TRIP Counters for breakers 3) Rate of Change (ROC) Limit Checking 4) Breaker operating time checks (should perform at HMI) 5) Substation-wide, automated control sequences: Automatic Transfer Switch(ATS), Bus Coupler Throw-over Scheme (CTO), Line Throw-over (LTO) & Bus Throw-over (BTO), Load Shedding / Load Restoration, and Voltage Selection (VT connection is Hardwire, Logic at Software at Bay Level). 6) Station-wide interlocking (GOOSE interlocking at Bay level) 7) Protection applications (Breaker Failure Protection) (at Bay level, both Main & Back up protection) 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
5	SCPS: CONTROL REQUIREMENTS				
5.1	5.1 SCOPE OF WORK The scope of work shall include 1) the preparation of a SCPS Detailed Design Documents for approval by PEA prior to commencement of system production. The initial list of required data points and typical screen displays are provided in Annexes 4 and 5, respectively. A printout report shall be kept electronically as a raw log file, and can be printed out according to the format guideline given in Annex 5.				
	2) the development of the control software to perform all substation manual and automatic functions.				
	3) all necessary hardware/software required for integrating the SCPS to the Distribution Management System (DMS) Mater Station located at each Area Distribution Dispatching Center (ADDC).				
	4) the preparation and maintenance to as built stage of a database, which documents all data points within the substation.				
	The Contractor shall submit performance test report and interoperability test report from independent testing laboratories for PEA approval.				
5.2	SOFTWARE/FIRMWARE The major system functions to be implemented in the SCPS software area shall be as follows: 1) Substation equipment control 2) Substation equipment indications 3) Substation equipment alarm and event handling facilities 4) Graphical information display 5) System configuration and database maintenance 6) Manual and automatic control function maintenance 7) Interlocking maintenance 8) Serial ports protocol assignment 9) DMS Interface software maintenance 10) IED devices management 11) System Disturbance Analysis 12) Measurement values including Load reports and Load curves creation and display 13) Printing 14) Automatic self-diagnostic 15) Help information 16) Archiving				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
5.3	FUNCTIONAL REQUIREMENTS				
5.3.1	<p>General</p> <p>The SCPS shall perform the following functions:</p> <ol style="list-style-type: none"> 1) Control electric power substation equipment 2) Monitor the status of electric power substation equipment 3) Acquire operating data from electric power substations 4) Operate autonomously and on command from the DMS and a local user interface (HMI). 				
5.3.2	<p>Input/Output Point Types</p> <p>The SCPS shall include facilities for handling all analog input, status input, and control output points. Requirements for each type of I/O point are described in the following sub-clauses.</p> <p>Where the SCPS is used to acquire any of the specified data I/O via an interface to the IED devices such as substation Protective relays or power meters, the overall system performance and responses as called for in these specifications shall not be compromised.</p>				
5.3.2.1	<p>Analog Input</p> <p>Analog measurement from CT/VT shall be processed in IED relay and/or BCU.</p>				
5.3.2.2	<p>Status Input</p> <p>Status Inputs shall be processed in IED relay and/or BCU.</p>				
5.3.2.3	<p>Control Output</p> <p>The SCPS shall include the following types of control points to support control actions initiated by the DMS master stations or, where applicable, the integral programmable logic facilities of the SCPS:</p> <ol style="list-style-type: none"> 1) On/Off Device Control 2) Raise/Lower Control 3) Setpoint Control 				
5.4	SYSTEM PERFORMANCE REQUIREMENTS				
5.4.1	<p>Response to a Control</p> <p>The delay between the completion of an operator's keying sequence and the response of the substation equipment as observed on the HMI display shall not exceed 2.0 second. This time does not include the operating time of the primary equipment.</p>				
5.4.2	<p>Status Change</p> <p>The delay between the occurrence of a spontaneous status change at the substation and the appearance of the corresponding indication on the HMI display shall not exceed 1.0 second.</p>				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
	Where the SCPS is used to acquire any of the specified data I/O via an interface to the IED devices such as substation Protective relays. The response time requirement shall also be applied for the information acquired from such Protective relays when they operated.				
5.4.3	<p>Measured Values</p> <p>Measured values, which are rapidly varying quantities, shall be updated on the HMI display at least every 2 seconds</p>				
5.4.4	<p>Alarms/Events</p> <p>The delay between the occurrence of an alarm/event at the substation and the appearance of the corresponding logged message on the HMI display shall not exceed 1.0 second.</p>				
	Where the SCPS is used to acquire any of the specified data I/O via an interface to the IED devices such as substation Protective relays. The response time requirement shall also be applied for the information acquired from such Protective relays when they operated				
5.4.5	<p>Alarm Generation</p> <p>The alarms shall be stored in buffer in chronological order with 10 ms or better resolution time and shall be possible to be displayed on HMI display or printed on a printer. The following conditions listed below shall be considered as alarms and shall give both audible and visual indications.</p> <ol style="list-style-type: none"> 1) Failure of equipment or predefined change in the condition of equipment into the alarm state. These include both substation equipment and SCPS equipment. 2) Surpassing of predefined upper/lower limits by the Analog values including fault current, harmonics, voltage sag, and voltage swells. 3) Executed command not successful. 4) Uncommanded status change. 5) Disagreement of normally open or normally closed contacts input for the substation equipment status. 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
5.4.6	<p>Sequential Events Recording</p> <p>The sequential events recording shall include all events, which can be of interest, occurring in the substation. The normal events shall be stored in database in chronological order with 10 ms or better resolution time and shall be displayed on HMI display or printed out on a printer. The system shall automatically log the following events:</p> <ol style="list-style-type: none"> 1) All alarm conditions as defined in Clause 5.4.5 2) All alarmed failure of substation and SCPS equipment returning to normal 3) All alarmed Analog value points returning to normal. 4) All status changes. 5) All operator intervention. 6) Placement and removal of all tags. 7) Changing of the measured value limits and scaling: the Contractor shall describe in detail how the two repositories are kept in sync 8) Any other important events input by PEA. 				
5.4.7	<p>High-resolution Sequence-of-Events (SOE)</p> <p>The SCPS shall include a high-resolution Sequence-of-Events (SOE) reporting capability. As a minimum, the status input points shall be assigned to SOE reporting in addition to normal status reporting.</p>				
	<p>The SCPS shall detect changes in the state of SOE points, record the date and time of change with a resolution of ± 1 ms relative to the SCPS internal clock, inform the DMS that SOE data has been recorded, and report SOE data to the DMS upon request.</p>				
	<p>The time tagging of all SOE inputs within a substation shall be made in the BCU and shall be synchronized to ensure that SOE inputs connected to different control cabinets satisfy the time resolution requirement. Time delays introduced by Contractor-supplied auxiliary relays used to acquire SOE status inputs from substation control circuits shall be consistent between devices to prevent time tag "skewing".</p>				
	<p>Where the SCPS is used to acquire any of the specified data I/O via an interface to the IED devices such as substation Protective relays, the resolution time requirement shall also be applied for the information acquired from such Protective relays when they operated.</p>				
	<p>To ensure that SOE data is not lost or overwritten until the DMS acknowledges receipt of the data, a SCPS buffer capable of storing a minimum of 512 events shall be provided. The SCPS shall be able to retransmit stored SOE data if requested by the DMS.</p>				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
5.4.8	Storage of System Disturbance and Power Quality Data				
5.4.8.1	System Disturbance Data The SCPS shall include a function for storing AC voltage and current waveform data prior to, during, and following power system disturbances detected as user-defined events. The stored data shall be made available to the DMS master station for post-disturbance analysis and shall be in an IEEE COMTRADE format.				
	At least 12 user-defined data track shall be provided for each measuring point of each switchgear bay. Each track shall be capable of storing data up to 1 second in one time window with a user-defined trigger. The capabilities for storing data of multiple disturbances such as auto-reclose on fault shall be provided.				
	Typical triggers include those that shall occur when events such as overvoltage and undervoltage are detected. In general, however, the ability to define event triggers based on calculated as well as actual data points shall be provided.				
	When an event occurs, the SCPS shall save the contents of the associated time window together with a time-stamped event flag. This flag shall identify the event type and shall be made available to the DMS master station for use by its Disturbance Data Collection function. The user shall be able to specify whether the contents of the saved buffer should remain frozen until collected or released by the DMS.				
	Where the SCPS is used to acquire any data of the specified functions via an interface to the IED devices such as substation Protective relays or power meters, the overall system performance and responses as called for in these specifications shall not be compromised.				
5.4.9	Fault Current Detection				
	The SCPS shall provide the facilities for detecting and reporting a fault current level for each of its AC current inputs. The function shall provide for the recording, time tagged to 10 millisecond, of an excursion outside user definable limits, together with the peak deviation and the time that the measured value returned to a point below the user defined trigger level. The limits of the fault current amplitude resolution shall be 20 times normal full load, and the trigger point for saving the record shall be user definable.				
	The SCPS shall save the fault current detection event as a database record for reporting to the HMI and the DMS master as required. The SCPS shall be capable of saving at least 256 such events in its database.				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
	Where the SCPS is used to acquire any data of the specified functions via an interface to the IED devices such as substation Protective relays or power meters, the overall system performance and responses as called for in these specifications shall not be compromised.				
5.4.10	Tagging and Labelling				
	The proposed SCPS shall provide labelling and tagging facilities which allow the substation operator to indicate the presence of control suppression, live line working, advise of the control status of a device and allow limited control of the system's scanning and alarm processing functions. The OFF NORMAL and EVENTS list entries shall record the application of these tags and labels. The minimum requirement for labels and tags shall be but not limited the following:				
5.4.10.1	Out of Scan Tag				
	A visual tag indicating that scanning of a device has been suppressed by the operator. All other system functions shall also be suppressed for such a point. It shall be possible to place screen comments regarding the status of tagged points.				
5.4.10.2	Alarm Suppression Tag A visual tag indicating that alarm processing on a system point (a device or measured value) has been suppressed by the operator. Status/Value information shall continue to be scanned and displayed. Provision shall be made for single point and functional group alarm suppression.				
5.4.10.3	Live Line Working Tags A visual tag indicating that some of PEA workers are doing some maintenance task on the line outside substation territory while the line is being energized. When this tag is applied to any line protection circuit breaker, selection of an auto-reclosing device of such circuit breaker shall result in a message to the operator e.g. CB_ AUTO-RECLOSE CONTROL BLOCKED.				
5.4.10.4	Control Suppression Tag A visual tag indicating that primary system equipment appearing on the HMI operator display has been suppressed. Selection of a device with control suppressed shall result in a message to the operator e.g. CB_ CONTROL BLOCKED.				
5.4.10.5	Method of Application of Tags and Labels The tags and labels shall be quickly and easily applied by the operator. The preferred method shall be by using cursor positioning and a simple keystroke sequence to apply any of the tag to any point/device on operating diagrams.				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
5.4.11	Interlocking The closing or opening operation of primary equipment such as circuit breakers, disconnectors, earth switches, etc. shall be supervised by the appropriate predefined interlocking. The facilities for interlocking maintenance shall also be provided.				
5.4.12	Load Reports and Load Curves Analog measured and calculated values shall be recorded in historical data file at the end of each half hour (snapshot) for subsequence reports creation.				
	As a minimum, daily load report, monthly load report, peak & light load report and yearly load report of each incoming and outgoing shall be provided and shall be in accordance with typical printout report format provide in Annex 5.				
	These reports shall be able to be shown on the HMI display, with the required format at any time by the operator.				
	Screen menus shall be provided for operator to select the required period of information by entering date(s), month and year. Daily and monthly load curve creation shall also be provided by using such stored data.				
	The delay between the completion of an operator's keying sequence and the response of any report or curve display as observed on the HMI display shall not exceed 5 second.				
5.4.13	IED Device Management The HMI software shall be capable of IED device management via the router and firewall for remote the IED devices management function such as setting and resetting of all Protective relays and BCU.				
5.4.14	Archiving The SCPS system shall be able to take care of archiving data on measurements, events, alarms, and fault records to hard disk. The hard disk shall be capable of storing all of above data for at least 1 year. The data stored on a hard disk shall be in the form of standard databases and shall be processed by means of the system itself as well as by means of the other standard packages such as Ms-Access, etc.				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
5.4.15	<p>Operation Screen Displays</p> <p>The operation screen displays for the monitoring and control of the substation shall include but not be limited to the following:</p> <ol style="list-style-type: none"> 1) Detailed equipment status, and network configuration information. 2) Visual indication of device setting, selection, operation and interlocking 3) Service and measurement values, including analog measurements and their limit setting. 4) Alarm annunciation. 5) Visual record of system alarms, including fault information, events and SOE. 6) A means of displaying the status of devices that are not monitored automatically but are under the substation operator's control such as application of tags or labels. 7) If keyboard inputs have not been received for 1 hour then the screen shall revert to screen saver mode. 8) IED internal events. 				
5.4.16	<p>System Management Displays</p> <p>These are displays for monitoring and controlling the SCPS system. They shall include:</p> <ol style="list-style-type: none"> 1) System Configuration Control Display 2) HMI Assignments Display, for the management of HMI modes 3) Display for monitoring and controlling the SubLAN 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page or Clarification Letters
6	SCPS: Protection requirements Access to relay display and setting parameters will be keyed by different authorization levels (password).				
6.1	GENERAL REQUIREMENTS				
6.1.1	Digital Fault Recorder (DFR) for a switching substation is an optional, which PEA shall specify its requirements case by case. At the minimum, the DFR shall conform with the specification given in Annex 10 of Spec RSUB-010-2560.				
6.1.2	Reference Standards All equipment, materials, fabrication and testing under this Specification shall conform to the latest applicable standard specifications and codes contained in the following list, or to equivalent applicable standard specifications and codes established and approved in the country of manufacturer of the equipment. Where standards are mentioned by name, equivalent applicable standards may be used. IEC 60068-2-1, IEC 60068-2-2, IEC 60068-2-6, IEC 60068-2-27, IEC 60068-2-78, IEC 60255-3, IEC 60255-27, IEC 60255-26, IEC 60870-5-1012, IEC 60947-1, IEC 60947-7-1, IEC 61000-4-2, IEC 61000-4-3, IEC 61000-4-4, IEC 61000-4-5; see more details in Clause 2.2 Specific Relevant Standards. Any details not specifically covered by these standards shall be subject to the approval of PEA. In the event of contradictory requirements between such standards and this Specification, the terms of the Specification shall govern.				
6.1.3.1	Details of Switchboard Construction. Each control switchboard, each control and protective relay switchboard, each protective relay switchboard and each interposing relay cabinet, shall consist of an assembly made from not less than No. 3.0 mm levelled sheet steel and formed steel members as required to form a rigid self-supporting structure. No butt surface joints shall be made on the outside surfaces of switchboards and cabinets. No holes or fasteners shall be visible as viewed from the front of the panels. Switchboards and cabinets shall be designed to have bottom sheets and each bottom sheet shall be provided with gland plate which shall be made of a non-magnetic metal. Each gland plate shall be provided with adequate quantity of holes for control cable entrance from underneath the switchboard and cabinet. They shall be furnished with channel bases. The front and rear panels of the switchboards and the cabinets shall have bent angle or flange edges with an outside radius not exceeding 10 mm. The construction details of the switchboards shall be as shown on Drawing No. OOT10N. Finished panel surfaces shall be free from waves, bellies, or other imperfections. Exterior and interior surfaces shall be cleaned by sanding and steam cleaning, ground smooth, filled, primed, sanded and shall be finish-painted inside and outside with RAL 7032.				
6.1.3.2	Equipment shall be protected against electrical and electro-magnetic disturbance and shall particularly comply with IEC 60255-27 and IEC 60255-26 standards.				
6.2	DETAILED REQUIREMENTS				
6.2.2.2	Bay Control Unit (BCU) Refer to Sub-Clause Bay Control Unit 8.3.8 for Hardware Requirement.				
6.2.2.3	I/O Interface All signals shall be processed by the SCPS from the SCPS Systems.				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page or Clarification Letters
6.2.2.4	<p>Trip circuit</p> <p>All the relays used for tripping shall still operate if the DC supply voltage is equal to 80% of the rated voltage.</p> <p>All tripping control circuits for the CB shall be interrupted for the qualitative and quantitative tests. These circuits shall be located at the same test block provided to test the relay with currents and/or voltages.</p>				
6.2.2.7	<p>DC-Supply</p> <p>The power supply shall be based on 125 V or 48 V lead-acid station battery depend on each PEA Substation.</p>				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
7	COMMUNICATION SYSTEM REQUIREMENTS				
7.1	<p>GENERAL REQUIREMENTS</p> <p>The communication requirements shall be based on IEC 61850 standards, in particular IEC 61850-3: General Requirements, 61850-5: Communication Requirements For Functions and Device Models, IEEE 1615: Recommended Practice for Network Communication in Electric Power Substations and IEEE 1613: Standard Environmental and Testing Requirements for Communications Networking Devices in Electric Power Substations.</p>				
7.2	<p>FUNCTION HIERARCHY, INTERFACE, AND TOPOLOGY</p> <p>the optical SCPS or CGW ports shall meet the following requirements:</p> <ol style="list-style-type: none"> 1) 2.5 kV optical isolation 2) Electrical EIA RS-232 DB-25 or DB-9 male connector (DTE-DCE selectable) 3) Optical connector supporting ST or LC multimode 4) Power budget of 12 db (optical fibre cable 62.5/125 micron) 5) Data rate from 300 to 19,200 bps 6) Auto-powered from RS-232 interface 7) Environmental capability of 0 to 50 °C, 5 to 95% relative humidity 				
7.3	<p>COMMUNICATION NETWORK</p> <p>The communication network infrastructure shall satisfy the following requirements:</p> <ol style="list-style-type: none"> 1) Access control and cyber security especially for remote access 2) Configuration, system and network management 3) Deterministic predictable network (collision-free environment) with the utilization of a dedicated managed Ethernet Switch 4) Deterministic real time network capability 5) Environmentally hardened network devices and components, rated for operation in HV substation environment 6) Flexibility and scalability for system change or expansion 7) Fully duplex communication backbone using high speed 1Gbit/s optical fibre ring Ethernet local area network (LAN) topology 8) Fully duplex Ethernet communication connection to IEDs using either 100Base Fx (Preferred) or 100BaseT 9) Integration of intelligent devices 10) Priority queuing support 11) Simultaneously support multiple applications including virtual LAN (VLAN) support 12) Time synchronization over Ethernet. 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
	<p>Internet protocol suite (IPS) shall be used for the transfer of operational and non-operational data as well as configuration management. The followings shall be considered:</p> <p>1) Development plan for IP address allocations. PEA will manage the IP addressing. Details on PEA IP addressing management is in Annex 6.</p> <p>2) Private and fixed IP addressing shall be employed on the substation network.</p> <p>3) SCPS connected to an enterprise or WAN must pass through a properly configured router with firewall and cyber security measures as described in Clauses 8.4.3 System Access Control and Cyber Security Management and 11.5 Substation Access Control and Cyber Security measures. However, the provision of the router with firewall is not under the scope of this specification, and shall be supplied by PEA ICT Division.</p>				
7.3.1	<p>Communication Network Device – Ethernet Switch</p> <p>All Ethernet switches shall be certified and type tested as protection grade devices.</p>				
(ADDENDUM)	<p>The main characteristics of the Ethernet Switch shall be designed for continuous operation in a high voltage substation and shall conform to the industrial environment performance, according to IEEE 1613 – class 1 for the Ethernet Switch used in station bus level and IEEE 1613 - class 2 “ error free” for Ethernet Switch used in process bus level, for real-time control and EMI immunity and shall pass a type test according to IEC 61850-3. And the requirements stated in Clause 4.6 System Security. Ethernet Switch at a station bus level shall be L3 type, and those at a process bus level shall be L2 type.</p>				
	<p>Network Redundancy using IEC 62439</p> <p>1) IEC SC65C WG15 published IEC 62439 “Highly Available Automation Networks”</p> <p>2) IEC 62439-3 Clause 4 Parallel Redundancy Protocol PRP</p> <p>3) IEC 62439-3 Clause 5 High Availability Seamless Ring HSR</p>				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page																																
(ADDENDUM)	<p>The basic requirements of the managed Ethernet switch are:</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Requirement</th> <th style="text-align: center;">Comments</th> </tr> </thead> <tbody> <tr> <td>Network Device Type</td> <td> 1) Fully Managed Ethernet switch 2) Fanless 3) Modular Design </td> </tr> <tr> <td>Auxiliary Supply</td> <td> 1) 125 VDC nominal voltage (substation DC system) with minimum range 80-120% of nominal voltage, or 2) 230 VAC nominal voltage with $\pm 10\%$ of nominal voltage </td> </tr> <tr> <td>Temperature Range</td> <td> 1) Extended temperature range operation 2) -40 to +85 °C (IEC 61850-3) </td> </tr> </tbody> </table>	Requirement	Comments	Network Device Type	1) Fully Managed Ethernet switch 2) Fanless 3) Modular Design	Auxiliary Supply	1) 125 VDC nominal voltage (substation DC system) with minimum range 80-120% of nominal voltage, or 2) 230 VAC nominal voltage with $\pm 10\%$ of nominal voltage	Temperature Range	1) Extended temperature range operation 2) -40 to +85 °C (IEC 61850-3)																												
	Requirement	Comments																																			
	Network Device Type	1) Fully Managed Ethernet switch 2) Fanless 3) Modular Design																																			
Auxiliary Supply	1) 125 VDC nominal voltage (substation DC system) with minimum range 80-120% of nominal voltage, or 2) 230 VAC nominal voltage with $\pm 10\%$ of nominal voltage																																				
Temperature Range	1) Extended temperature range operation 2) -40 to +85 °C (IEC 61850-3)																																				
(ADDENDUM)	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Requirement</th> <th style="text-align: center;">Comments</th> </tr> </thead> <tbody> <tr> <td>EMC and Environmental Type Tests</td> <td> 1) EMI-hardening 2) Protection Grading 3) IEC 61850-3 and IEEE 1613 4) Type test certificate to be provided as evidence </td> </tr> <tr> <td>Mounting</td> <td> 1) Panel 2) DIN rail 3) Rack-Mount </td> </tr> <tr> <td>Port Speed</td> <td>1) 1 Gbps (Station Bus Backbone), 100 Mbps (IED connection)</td> </tr> <tr> <td>Port Type</td> <td> 1) 1000Base FX (For Backbone) 2) 1000BaseTX (For Segment or IED) </td> </tr> <tr> <td>Switching Method</td> <td>1) Store and forward</td> </tr> <tr> <td>Switching Delay</td> <td>1) < 10 μsec (100 Mbps)</td> </tr> <tr> <td>Priority Queues Number</td> <td>1) Minimum 2</td> </tr> <tr> <td>Backbone Media</td> <td> 1) Optical fibre (at the process level) 2) RJ45 Copper (at the station level) </td> </tr> <tr> <td>Backbone Interface (Station bus communication)</td> <td>1) SFP LC type optical fibre connector</td> </tr> <tr> <td>Segment or IED Interface (within panel)</td> <td> 1) RJ45 port 2) Option for ST optical fibre connector (multi-mode optical fibre) </td> </tr> <tr> <td>SCADA monitoring and management</td> <td>1) Switch should compliant with IEC 61850-90-4 MMS bridge modelling</td> </tr> <tr> <td>Network Management Tools</td> <td> 1) SNMP or MMS with the latest version 2) Web-based 3) Remote Monitoring </td> </tr> <tr> <td>Cyber Security</td> <td> 1) User passwords 2) SSH/SSL encryption 3) Encrypted authentication and access security 4) MAC based port security 5) VLAN (IEEE Std 802.1Q) </td> </tr> <tr> <td>Others</td> <td>The switch shall support transmissions of GOOSE messaging.</td> </tr> <tr> <td>Quality Assurance</td> <td>1) ISO 9001:2000</td> </tr> </tbody> </table>	Requirement	Comments	EMC and Environmental Type Tests	1) EMI-hardening 2) Protection Grading 3) IEC 61850-3 and IEEE 1613 4) Type test certificate to be provided as evidence	Mounting	1) Panel 2) DIN rail 3) Rack-Mount	Port Speed	1) 1 Gbps (Station Bus Backbone), 100 Mbps (IED connection)	Port Type	1) 1000Base FX (For Backbone) 2) 1000BaseTX (For Segment or IED)	Switching Method	1) Store and forward	Switching Delay	1) < 10 μ sec (100 Mbps)	Priority Queues Number	1) Minimum 2	Backbone Media	1) Optical fibre (at the process level) 2) RJ45 Copper (at the station level)	Backbone Interface (Station bus communication)	1) SFP LC type optical fibre connector	Segment or IED Interface (within panel)	1) RJ45 port 2) Option for ST optical fibre connector (multi-mode optical fibre)	SCADA monitoring and management	1) Switch should compliant with IEC 61850-90-4 MMS bridge modelling	Network Management Tools	1) SNMP or MMS with the latest version 2) Web-based 3) Remote Monitoring	Cyber Security	1) User passwords 2) SSH/SSL encryption 3) Encrypted authentication and access security 4) MAC based port security 5) VLAN (IEEE Std 802.1Q)	Others	The switch shall support transmissions of GOOSE messaging.	Quality Assurance	1) ISO 9001:2000				
	Requirement	Comments																																			
	EMC and Environmental Type Tests	1) EMI-hardening 2) Protection Grading 3) IEC 61850-3 and IEEE 1613 4) Type test certificate to be provided as evidence																																			
	Mounting	1) Panel 2) DIN rail 3) Rack-Mount																																			
	Port Speed	1) 1 Gbps (Station Bus Backbone), 100 Mbps (IED connection)																																			
	Port Type	1) 1000Base FX (For Backbone) 2) 1000BaseTX (For Segment or IED)																																			
	Switching Method	1) Store and forward																																			
	Switching Delay	1) < 10 μ sec (100 Mbps)																																			
	Priority Queues Number	1) Minimum 2																																			
	Backbone Media	1) Optical fibre (at the process level) 2) RJ45 Copper (at the station level)																																			
	Backbone Interface (Station bus communication)	1) SFP LC type optical fibre connector																																			
	Segment or IED Interface (within panel)	1) RJ45 port 2) Option for ST optical fibre connector (multi-mode optical fibre)																																			
	SCADA monitoring and management	1) Switch should compliant with IEC 61850-90-4 MMS bridge modelling																																			
	Network Management Tools	1) SNMP or MMS with the latest version 2) Web-based 3) Remote Monitoring																																			
	Cyber Security	1) User passwords 2) SSH/SSL encryption 3) Encrypted authentication and access security 4) MAC based port security 5) VLAN (IEEE Std 802.1Q)																																			
Others	The switch shall support transmissions of GOOSE messaging.																																				
Quality Assurance	1) ISO 9001:2000																																				
(ADDENDUM)	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Requirement</th> <th style="text-align: center;">Comments</th> </tr> </thead> <tbody> <tr> <td>Operating Temperature</td> <td>-40 to +85 °C</td> </tr> <tr> <td>Power Supply</td> <td>Dual redundant, load sharing, hot-swappable</td> </tr> <tr> <td>Ethernet Module</td> <td>Field replaceable</td> </tr> <tr> <td>Ports</td> <td>High density: 28 ports, all gigabit capable RJ45 with a secure copper connector, or <u>fiber</u> for future expansion</td> </tr> <tr> <td>Fiber Type Connector</td> <td>ST, or LC</td> </tr> <tr> <td>Network Switch and Time Synchronization</td> <td>Transparent Clock</td> </tr> <tr> <td>Coating</td> <td>Conformal coating to prevent mould / corrosion</td> </tr> </tbody> </table>	Requirement	Comments	Operating Temperature	-40 to +85 °C	Power Supply	Dual redundant, load sharing, hot-swappable	Ethernet Module	Field replaceable	Ports	High density: 28 ports, all gigabit capable RJ45 with a secure copper connector, or <u>fiber</u> for future expansion	Fiber Type Connector	ST, or LC	Network Switch and Time Synchronization	Transparent Clock	Coating	Conformal coating to prevent mould / corrosion																				
	Requirement	Comments																																			
	Operating Temperature	-40 to +85 °C																																			
	Power Supply	Dual redundant, load sharing, hot-swappable																																			
	Ethernet Module	Field replaceable																																			
	Ports	High density: 28 ports, all gigabit capable RJ45 with a secure copper connector, or <u>fiber</u> for future expansion																																			
	Fiber Type Connector	ST, or LC																																			
	Network Switch and Time Synchronization	Transparent Clock																																			
Coating	Conformal coating to prevent mould / corrosion																																				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page																				
7.3.2	<p>Communication Network Device – Media</p> <p>The selection of the network media in the substation shall consider the followings:</p> <ol style="list-style-type: none"> 1) Required data speed/throughput 2) Linear distance 3) Physical routing 4) Electromagnetic interference (EMI) and ground potential rise (GPR) susceptibility 5) Number of network-connected devices 6) Substation wiring practices/procedures 7) Fibre Monitoring: All fibre media should support DDM (Digital Diagnostics Monitoring) and follow industry-standard SFF-8472. 																								
	<p>The communication media to be used in the substation shall be copper and/or optical fibre as depicted in Figure 7.2.</p> <div style="text-align: center;"> <p>Figure 7.2 – Substation Network Media</p> </div>																								
	<p>The type of the optical fibre to be used in the substation as the network backbone interface (station bus communication) shall be as the following:</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Optical Fibre Type</th> <th style="text-align: center;">Wavelength</th> <th style="text-align: center;">Speed</th> <th style="text-align: center;">Connector</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;">1000Base-X, Single mode glass</td> <td style="text-align: center;">1310nm</td> <td style="text-align: center;">1 Gbps</td> <td style="text-align: center;">ST or LC (SFP)</td> </tr> </tbody> </table> <p>Other requirements of the optical fibre cabling are:</p> <ol style="list-style-type: none"> 1) Vermin proof with mechanical protection 2) Redundant spare optical fibre cable shall be provided as per project specific requirements 3) 100% spare optical fibre cores in each cable shall be provided, i.e., full redundant fibre cores should be provided in each cable 4) Optical fibre cables lay in PVC conduit if mechanical protection is not provided. 5) Power budget calculation shall be approved by PEA 	Optical Fibre Type	Wavelength	Speed	Connector	1000Base-X, Single mode glass	1310nm	1 Gbps	ST or LC (SFP)																
Optical Fibre Type	Wavelength	Speed	Connector																						
1000Base-X, Single mode glass	1310nm	1 Gbps	ST or LC (SFP)																						
	<p>The copper cable used in the network segment inside a panel shall be UTP or STP Ethernet cable (depend on the induced and radiated noise within the panel) as the following:</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Rating</th> <th style="text-align: center;">Name</th> <th style="text-align: center;">Connector</th> <th style="text-align: center;">Speed</th> <th style="text-align: center;">Standard</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;">CAT 5</td> <td style="text-align: center;">100 BASE TX</td> <td style="text-align: center;">RJ45</td> <td style="text-align: center;">100Mbps</td> <td style="text-align: center;">IEEE Std 802.3-2005 and EIA/TIA 568A/B</td> </tr> <tr> <td style="text-align: center;">CAT 5E (Preferred)</td> <td style="text-align: center;">100 BASE TX</td> <td style="text-align: center;">RJ45</td> <td style="text-align: center;">100Mbps</td> <td style="text-align: center;">IEEE Std 802.3-2005 and EIA/TIA 568A/B</td> </tr> <tr> <td style="text-align: center;">CAT 6</td> <td style="text-align: center;">100 BASE TX</td> <td style="text-align: center;">RJ45</td> <td style="text-align: center;">100Mbps</td> <td style="text-align: center;">IEEE Std 802.3-2005 and EIA/TIA 568A/B</td> </tr> </tbody> </table>	Rating	Name	Connector	Speed	Standard	CAT 5	100 BASE TX	RJ45	100Mbps	IEEE Std 802.3-2005 and EIA/TIA 568A/B	CAT 5E (Preferred)	100 BASE TX	RJ45	100Mbps	IEEE Std 802.3-2005 and EIA/TIA 568A/B	CAT 6	100 BASE TX	RJ45	100Mbps	IEEE Std 802.3-2005 and EIA/TIA 568A/B				
Rating	Name	Connector	Speed	Standard																					
CAT 5	100 BASE TX	RJ45	100Mbps	IEEE Std 802.3-2005 and EIA/TIA 568A/B																					
CAT 5E (Preferred)	100 BASE TX	RJ45	100Mbps	IEEE Std 802.3-2005 and EIA/TIA 568A/B																					
CAT 6	100 BASE TX	RJ45	100Mbps	IEEE Std 802.3-2005 and EIA/TIA 568A/B																					

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page																											
	<p>Alternatively, multi-mode optical fibre may be used in the network X, subject to Ethernet switch port availability and PEA approval, as the following:</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Optical Fibre Type</th> <th style="text-align: center;">Wavelength</th> <th style="text-align: center;">Speed</th> <th style="text-align: center;">Connector</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;">Multi-mode glass</td> <td style="text-align: center;">850nm, 1310nm</td> <td style="text-align: center;">100Mbps</td> <td style="text-align: center;">ST</td> </tr> </tbody> </table>	Optical Fibre Type	Wavelength	Speed	Connector	Multi-mode glass	850nm, 1310nm	100Mbps	ST																							
Optical Fibre Type	Wavelength	Speed	Connector																													
Multi-mode glass	850nm, 1310nm	100Mbps	ST																													
7.4	<p>COMMUNICATION SERVICES TO BE SUPPORTED</p> <p>Communication services to be supported are summarized in Table</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Service Model</th> <th style="text-align: center;">Description</th> <th style="text-align: center;">Services</th> <th style="text-align: center;">Requirement</th> </tr> </thead> <tbody> <tr> <td>Server</td> <td>Represents the external visible behaviour of a device. All other ACSI models are part of the server</td> <td>ServerDirectory</td> <td></td> </tr> <tr> <td>Application Association</td> <td>Provision of how two or more devices can be connected. Provides different views to a device: restricted access to the server's information and functions</td> <td>Associate Abort Release</td> <td></td> </tr> <tr> <td>Logical Device</td> <td>Represents a group of functions; each function is defined as a logical node</td> <td>LogicalDeviceDirectory</td> <td></td> </tr> <tr> <td>Logical Node</td> <td>Represents a specific function of the substation system, for example, over voltage protection</td> <td>LogicalNodeDirectory GetAllDataValues</td> <td></td> </tr> <tr> <td>Data</td> <td>Provides a means to specify typed information, for example, position of a switch with quality information, and timestamp</td> <td>GetDataValues SetDataValues GetDataDefinition GetDataDirectory</td> <td></td> </tr> <tr> <td>Data Set</td> <td>Allow to group various Refer to Data set data together</td> <td>GetDataSetValue SetDataSetValue CreateDataSet DeleteDataSet GetDataSetDirectory</td> <td></td> </tr> </tbody> </table>	Service Model	Description	Services	Requirement	Server	Represents the external visible behaviour of a device. All other ACSI models are part of the server	ServerDirectory		Application Association	Provision of how two or more devices can be connected. Provides different views to a device: restricted access to the server's information and functions	Associate Abort Release		Logical Device	Represents a group of functions; each function is defined as a logical node	LogicalDeviceDirectory		Logical Node	Represents a specific function of the substation system, for example, over voltage protection	LogicalNodeDirectory GetAllDataValues		Data	Provides a means to specify typed information, for example, position of a switch with quality information, and timestamp	GetDataValues SetDataValues GetDataDefinition GetDataDirectory		Data Set	Allow to group various Refer to Data set data together	GetDataSetValue SetDataSetValue CreateDataSet DeleteDataSet GetDataSetDirectory				
Service Model	Description	Services	Requirement																													
Server	Represents the external visible behaviour of a device. All other ACSI models are part of the server	ServerDirectory																														
Application Association	Provision of how two or more devices can be connected. Provides different views to a device: restricted access to the server's information and functions	Associate Abort Release																														
Logical Device	Represents a group of functions; each function is defined as a logical node	LogicalDeviceDirectory																														
Logical Node	Represents a specific function of the substation system, for example, over voltage protection	LogicalNodeDirectory GetAllDataValues																														
Data	Provides a means to specify typed information, for example, position of a switch with quality information, and timestamp	GetDataValues SetDataValues GetDataDefinition GetDataDirectory																														
Data Set	Allow to group various Refer to Data set data together	GetDataSetValue SetDataSetValue CreateDataSet DeleteDataSet GetDataSetDirectory																														
	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Service Model</th> <th style="text-align: center;">Description</th> <th style="text-align: center;">Services</th> <th style="text-align: center;">Requirement</th> </tr> </thead> <tbody> <tr> <td>Substitution</td> <td>The client can request the server to replace a process value by a value set by the client, for example, in the case of an invalid measurement value</td> <td>SetDataValues</td> <td></td> </tr> <tr> <td>Setting Group Control</td> <td>Defines how to switch from one set of setting values to another one control and how to edit setting groups</td> <td>SelectActiveGG SelectEditGg SetGGValues ConformEditGGValues GetGGValues GetGCBValues</td> <td></td> </tr> <tr> <td rowspan="4">Reporting and Logging</td> <td rowspan="4">Describes the conditions for generating reports and logs based on parameters set by the client. Reports may be triggered by changes of process data values (for example, state change or dead band) or by quality changes. Logs Logging can be queried for later retrieval. Reports may be sent immediately or deferred (buffered). Reports provide change of state and sequence-of-events information exchange</td> <td>Buffered RCB: Report GetBRCBValues SetBRCBValues</td> <td></td> </tr> <tr> <td>Log CB: GetLCBValues SetLCBValues</td> <td>For Measurement Only</td> </tr> <tr> <td>Unbuffered RCB: Report GetURCBValues SetURCBValues</td> <td>Option</td> </tr> <tr> <td>Log: QueryLogByTime QueryLogAfter GetLogStatusValues</td> <td>Option</td> </tr> </tbody> </table>	Service Model	Description	Services	Requirement	Substitution	The client can request the server to replace a process value by a value set by the client, for example, in the case of an invalid measurement value	SetDataValues		Setting Group Control	Defines how to switch from one set of setting values to another one control and how to edit setting groups	SelectActiveGG SelectEditGg SetGGValues ConformEditGGValues GetGGValues GetGCBValues		Reporting and Logging	Describes the conditions for generating reports and logs based on parameters set by the client. Reports may be triggered by changes of process data values (for example, state change or dead band) or by quality changes. Logs Logging can be queried for later retrieval. Reports may be sent immediately or deferred (buffered). Reports provide change of state and sequence-of-events information exchange	Buffered RCB: Report GetBRCBValues SetBRCBValues		Log CB: GetLCBValues SetLCBValues	For Measurement Only	Unbuffered RCB: Report GetURCBValues SetURCBValues	Option	Log: QueryLogByTime QueryLogAfter GetLogStatusValues	Option									
Service Model	Description	Services	Requirement																													
Substitution	The client can request the server to replace a process value by a value set by the client, for example, in the case of an invalid measurement value	SetDataValues																														
Setting Group Control	Defines how to switch from one set of setting values to another one control and how to edit setting groups	SelectActiveGG SelectEditGg SetGGValues ConformEditGGValues GetGGValues GetGCBValues																														
Reporting and Logging	Describes the conditions for generating reports and logs based on parameters set by the client. Reports may be triggered by changes of process data values (for example, state change or dead band) or by quality changes. Logs Logging can be queried for later retrieval. Reports may be sent immediately or deferred (buffered). Reports provide change of state and sequence-of-events information exchange	Buffered RCB: Report GetBRCBValues SetBRCBValues																														
		Log CB: GetLCBValues SetLCBValues	For Measurement Only																													
		Unbuffered RCB: Report GetURCBValues SetURCBValues	Option																													
		Log: QueryLogByTime QueryLogAfter GetLogStatusValues	Option																													

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page																								
	<table border="1" style="width: 100%; border-collapse: collapse; font-size: small;"> <thead> <tr> <th>Service Model</th> <th>Description</th> <th>Services</th> <th>Requirement</th> </tr> </thead> <tbody> <tr> <td>Generic substation event: (GSE)</td> <td>Provides fast and reliable system-wide distribution of data; peer-to-peer exchange of IED binary status information GOOSE means: Generic Object Oriented Substation Event and supports the exchange of a wide range of possible common data organized by a DATA SET GSE means: Generic Substation State Event and provides the capability to convey state change information</td> <td>GOOSE CB: SendGOOSEMessage GetGoReference GetGOOSEElementNumber GetGoCBValues SetGoCBValues GSE CB: SendGSEMessage GetGReference GetGSEElementNumber GetGCBValues SetGCBValues</td> <td>Not Implemented</td> </tr> <tr> <td>Transmission of Sampled Values</td> <td>Fast and cyclic transfer of sample, for example of instrument transformer</td> <td>Multicast SVC: SendMSVMessage GetMSVCBValues SetMSVCBValues Unicast SVC: SendUSVMessage GetUSVCBValues SetUSVCBValues</td> <td>Future Not Implemented Future Not Implemented</td> </tr> <tr> <td>Control</td> <td>Describes the services to control, for example, devices or parameter setting groups</td> <td>Select SelectWithValue Cancel Operate CommandTermination TimeActivatedOperate</td> <td></td> </tr> <tr> <td>Time and Time Synchronization</td> <td>Provides the time base for the device and system</td> <td>Services in SC5M</td> <td></td> </tr> <tr> <td>File transfer</td> <td>Defines the exchange of large data blocks: such as programs</td> <td>GetFile SetFile DeleteFile GetFileAttributeValues</td> <td></td> </tr> </tbody> </table>	Service Model	Description	Services	Requirement	Generic substation event: (GSE)	Provides fast and reliable system-wide distribution of data; peer-to-peer exchange of IED binary status information GOOSE means: Generic Object Oriented Substation Event and supports the exchange of a wide range of possible common data organized by a DATA SET GSE means: Generic Substation State Event and provides the capability to convey state change information	GOOSE CB: SendGOOSEMessage GetGoReference GetGOOSEElementNumber GetGoCBValues SetGoCBValues GSE CB: SendGSEMessage GetGReference GetGSEElementNumber GetGCBValues SetGCBValues	Not Implemented	Transmission of Sampled Values	Fast and cyclic transfer of sample, for example of instrument transformer	Multicast SVC: SendMSVMessage GetMSVCBValues SetMSVCBValues Unicast SVC: SendUSVMessage GetUSVCBValues SetUSVCBValues	Future Not Implemented Future Not Implemented	Control	Describes the services to control, for example, devices or parameter setting groups	Select SelectWithValue Cancel Operate CommandTermination TimeActivatedOperate		Time and Time Synchronization	Provides the time base for the device and system	Services in SC5M		File transfer	Defines the exchange of large data blocks: such as programs	GetFile SetFile DeleteFile GetFileAttributeValues					
Service Model	Description	Services	Requirement																										
Generic substation event: (GSE)	Provides fast and reliable system-wide distribution of data; peer-to-peer exchange of IED binary status information GOOSE means: Generic Object Oriented Substation Event and supports the exchange of a wide range of possible common data organized by a DATA SET GSE means: Generic Substation State Event and provides the capability to convey state change information	GOOSE CB: SendGOOSEMessage GetGoReference GetGOOSEElementNumber GetGoCBValues SetGoCBValues GSE CB: SendGSEMessage GetGReference GetGSEElementNumber GetGCBValues SetGCBValues	Not Implemented																										
Transmission of Sampled Values	Fast and cyclic transfer of sample, for example of instrument transformer	Multicast SVC: SendMSVMessage GetMSVCBValues SetMSVCBValues Unicast SVC: SendUSVMessage GetUSVCBValues SetUSVCBValues	Future Not Implemented Future Not Implemented																										
Control	Describes the services to control, for example, devices or parameter setting groups	Select SelectWithValue Cancel Operate CommandTermination TimeActivatedOperate																											
Time and Time Synchronization	Provides the time base for the device and system	Services in SC5M																											
File transfer	Defines the exchange of large data blocks: such as programs	GetFile SetFile DeleteFile GetFileAttributeValues																											
7.5	<p>COMMUNICATION PROFILE</p> <p>Communication profiles the Contractor must comply with are Application (A) Profile, and Transport (T) Profile, which can be found in the following services:</p> <ol style="list-style-type: none"> 1) Client/Server services (Core ACSI Services) 2) GOOSE/GSE Management Services 3) Time Synchronization <div style="text-align: center;"> <p>Figure 7.3 -- Communication Profile for the Substation</p> </div>																												

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
7.5.1	<p>Communication Profile – Client/Server Services</p> <p>The client/server communication profile shall be used when declaring support for the services shown in the following tables of IEC 61850-8-1.</p> <p>1) Table 2 Service Requiring Client/Server Communication Profile 2) Table 3 Service and Protocols for Client/Server Communication A-Profile 3) Table 4 Service and Protocols for Client/Server Communication T-Profile</p>				
7.5.2	<p>Communication Profile – GOOSE/GSE Management Services</p> <p>For the GSE Management and GOOSE communication profile when declaring support for the services, refer to Table 6 Service Requiring GSE Management and GOOSE Communication Profile of IEC 61850-8-1.</p> <p>For service and protocols for GSE Management and GOOSE communication A and T profiles, refer to Tables 7 and 8 of IEC 61850-8-1, respectively.</p>				
7.5.3	<p>Communication Profile – Time Synchronization Time synchronisation for the SCPS shall be accomplished using NTP protocol with direct interface to the Ethernet network through connectionless user datagram protocol (UDP) at transport layer.</p>				
	<p>This communication profile shall be used for any implementation claiming conformance to this standard and declaring support for objects containing an attribute of type TIMESTAMP.</p>				
7.6	<p>INTRA-SUBSTATION AND REMOTE CONTROL CENTER COMMUNICATIONS</p> <p>Communications between substations, and between a substation and a remote control center shall be via a secured router/CGW. Engineer WAN shall be installed at all substation to facilitate fault investigation and event record view via remote access to IED including the disturbance recorder.</p>				
	<p>The communications should comply with IEC 61850, Part 90-1 for communications between substations, and Part 90-2 for communications between substation and a control center.</p>				
	<p>In case that IEC 61850, Part 90-2 has not been released yet, the Contractor shall propose communications between a substation and a control centre for PEA approval.</p>				
7.7	<p>STATION TIME SYNCHRONIZATION</p> <p>Time synchronisation of all IEDs and IEC 61850 based SCPS components in the substation shall be accomplished via NTP Server and modulated IEEE 1588 or IRIG-B with GPS master clock receiver(s).</p>				
	<p>The Contractor shall make sure that synchronization across a given SCPS system, via NTP together with IEEE 1588 or IRIG-B, shall work properly.</p>				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page																				
	Time synchronisation server shall provide the time source for time synchronisation of all SCPS components. The time shall be distributed to all substation IEDs via the station bus. The expected time stamp resolution of devices shall be 1ms (IEC 61850 Time Performance Class T1) and the expected accuracy (\pm) between network devices shall be 0.1ms.																								
	The expected time stamp resolution of devices shall be 1ms (IEC 61850 Time Performance Class T1) and the expected accuracy (\pm) between network devices shall be 0.1ms.																								
	One (1) GPS satellite disk and receiver shall be provided for time synchronization purposes at each SCPS system station site. The physical connection and installation of the GPS hardware components shall simple, not requiring any RF or GPS expertise. Any software for configuring or operating the unit shall be provided with the system.																								
	<p>The basic requirements of the Time Server are:</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Requirement</th> <th style="text-align: center;">Comments</th> </tr> </thead> <tbody> <tr> <td>Device output protocol type</td> <td>1) NTP Server (for network connection, with RJ45 Ethernet Interface) 2) IEEE 1588 or IRIG-B (for direct-wired connection)</td> </tr> <tr> <td>Auxiliary supply</td> <td>1) 125VDC nominal voltage (substation DC system) 2) Minimum range 80-120% of nominal voltage</td> </tr> <tr> <td>EMC and environmental type tests</td> <td>1) Withstand substation EMI 2) EMI-hardening</td> </tr> <tr> <td>Protocol for NTP server</td> <td>1) NTP 2) Internet protocol suite standard for time synchronization 3) Network Time Protocol v4.0 or higher 4) Should be compatible with IEEE 1588/IEC 61588 standard</td> </tr> <tr> <td>Time source</td> <td>Redundant Global Positioning Satellite (GPS) system receivers with antennae and wiring</td> </tr> <tr> <td>Expected accuracy (\pm) between Network devices</td> <td>1) 0.1ms (Expected Time Synchronizing of IED Clocks – one order of magnitude better than IED time stamp resolution) 2) Note: Typical Accuracy 3) 1-2 ms (NTP) 4) 1 microsec (IEEE 1588 or IRIG-B)</td> </tr> <tr> <td>Interface</td> <td>1) Ethernet (NTP, and IEEE 1588) 2) Direct-Wired Co-axial (IRIG-B)</td> </tr> <tr> <td>Maintainability requirement</td> <td>1) Maintenance port to perform the management, configuration, test and maintenance functions 2) Possibility to verify the time server accuracy and precision 3) Possibility to diagnose and troubleshoot problems</td> </tr> <tr> <td>Other requirements</td> <td>High precision clock discipline algorithms to counter inaccuracies caused by jitter and wander</td> </tr> </tbody> </table>	Requirement	Comments	Device output protocol type	1) NTP Server (for network connection, with RJ45 Ethernet Interface) 2) IEEE 1588 or IRIG-B (for direct-wired connection)	Auxiliary supply	1) 125VDC nominal voltage (substation DC system) 2) Minimum range 80-120% of nominal voltage	EMC and environmental type tests	1) Withstand substation EMI 2) EMI-hardening	Protocol for NTP server	1) NTP 2) Internet protocol suite standard for time synchronization 3) Network Time Protocol v4.0 or higher 4) Should be compatible with IEEE 1588/IEC 61588 standard	Time source	Redundant Global Positioning Satellite (GPS) system receivers with antennae and wiring	Expected accuracy (\pm) between Network devices	1) 0.1ms (Expected Time Synchronizing of IED Clocks – one order of magnitude better than IED time stamp resolution) 2) Note: Typical Accuracy 3) 1-2 ms (NTP) 4) 1 microsec (IEEE 1588 or IRIG-B)	Interface	1) Ethernet (NTP, and IEEE 1588) 2) Direct-Wired Co-axial (IRIG-B)	Maintainability requirement	1) Maintenance port to perform the management, configuration, test and maintenance functions 2) Possibility to verify the time server accuracy and precision 3) Possibility to diagnose and troubleshoot problems	Other requirements	High precision clock discipline algorithms to counter inaccuracies caused by jitter and wander				
Requirement	Comments																								
Device output protocol type	1) NTP Server (for network connection, with RJ45 Ethernet Interface) 2) IEEE 1588 or IRIG-B (for direct-wired connection)																								
Auxiliary supply	1) 125VDC nominal voltage (substation DC system) 2) Minimum range 80-120% of nominal voltage																								
EMC and environmental type tests	1) Withstand substation EMI 2) EMI-hardening																								
Protocol for NTP server	1) NTP 2) Internet protocol suite standard for time synchronization 3) Network Time Protocol v4.0 or higher 4) Should be compatible with IEEE 1588/IEC 61588 standard																								
Time source	Redundant Global Positioning Satellite (GPS) system receivers with antennae and wiring																								
Expected accuracy (\pm) between Network devices	1) 0.1ms (Expected Time Synchronizing of IED Clocks – one order of magnitude better than IED time stamp resolution) 2) Note: Typical Accuracy 3) 1-2 ms (NTP) 4) 1 microsec (IEEE 1588 or IRIG-B)																								
Interface	1) Ethernet (NTP, and IEEE 1588) 2) Direct-Wired Co-axial (IRIG-B)																								
Maintainability requirement	1) Maintenance port to perform the management, configuration, test and maintenance functions 2) Possibility to verify the time server accuracy and precision 3) Possibility to diagnose and troubleshoot problems																								
Other requirements	High precision clock discipline algorithms to counter inaccuracies caused by jitter and wander																								
	Time synchronisation between devices which require high accuracy equal or less than 0.1 msec. shall be accomplished via IEEE 1588 or IRIG-B, direct-wired synchronization network.																								
	BCU and TRU units must support both NTP, and IEEE1588 (PTP) or IRIG-B protocols.																								

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
7.8	<p>SUBSTATION CONFIGURATION LANGUAGE (SCL)</p> <p>A standard configuration language SCL, (Substation Configuration Language), based on the XML (Extensible Markup Language) shall be used to define the characteristics of each IED with regards to communication configuration, data model and parameters. SCL is a file format for describing communication related IED (Intelligent Electronic Device) configurations and IED parameters, communication system configurations, switchyard (function) structures, and the relations between them. The main purpose of this format is to exchange IED capability descriptions, and SA system descriptions between IED engineering tools and the system engineering tool(s) of different manufacturers in a compatible way; see Fig. 7.4.</p>				
	<p>SCL types are classified with different suffixes including ICD, CID, SSD, and SCD as described, previously, in Clause 4.14.1: IEC 61850 Configuration functions for Tools and Process.</p> <p style="text-align: center;">Figure 7.4 – IED and System Configuration Tools and SCL</p>				
	<p>The SCL shall describe a model of:</p> <ol style="list-style-type: none"> 1) The primary (power) system structure: which primary apparatus functions are used, and how the apparatus are connected. This results in a designation of all covered switchgear as substation automation functions, structured according to IEC 81346. 2) The communication system: how IEDs are connected to subnetworks and networks, and at which of their communication access points (communication ports). 3) The application level communication: how data is grouped into data sets for sending, how IEDs trigger the sending and which service they choose, which input data from other IEDs is needed. 4) Each IED: the logical devices configured on the IED, the logical nodes with class and type belonging to each logical device, the reports and their data contents, the (pre-configured) associations available; and which data shall be logged. 5) Instantiable logical node (LN) type definitions. The logical nodes as defined in IEC 61850-7x have mandatory, optional and user defined DATA (here abbreviated DO) as well as optional services, and are therefore not instantiable. In this document, instantiable. LNTypes and DOTypes are defined as templates, which contain the really implemented Dos and services. 6) The relations between instantiated logical nodes and their hosting IEDs on one side and the switchyard (function) parts on the other side. 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page																																													
7.8.1	<p>IED Configuration</p> <p>Any IED supporting the IEC 61850 standard will be accompanied by a configuration file with ICD (IED Capability Description) which defines capacities of the IED. This file will start each project with the installation values, such as addresses, initial parameter values, etc. generating a new CID (Configured IED Description) file.</p>																																																	
7.8.2	<p>System Configuration and Specification</p> <p>The Contractor shall provide all relevant SCL files including System Specification Description (SSD), Substation Configuration Description (SCD), and make sure for IED can be automatically configured from the power system design.</p>																																																	
	<p>The SCPS configuration shall be done via a management application, as described in Clause 8.4.6 SCPS System and IED Configuration Management. All IEDs shall be configured using SCL-compliant tools, files, and procedures as described in IEC 61850, Part 6.</p>																																																	
7.9	<p>COMMUNICATION PERFORMANCE</p>																																																	
7.9.1	<p>Communication Message Performance</p> <p>The seven message types specified must meet the following performance requirements:</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Message Type</th> <th style="text-align: center;">Description</th> <th style="text-align: center;">Typical use</th> <th style="text-align: center;">Performance</th> </tr> </thead> <tbody> <tr> <td rowspan="3" style="text-align: center;">1</td> <td rowspan="3">Fast messages - Simple binary code containing data, command or simple message. Triggers the receiving IED to respond immediately.</td> <td rowspan="3">Trip command to XCBR, intertrip and scheme discriminations</td> <td>P1 - 10ms</td> </tr> <tr> <td>P2 - 3ms</td> </tr> <tr> <td>P3 - 3ms</td> </tr> <tr> <td style="text-align: center;">1B</td> <td>Fast messages for Others</td> <td>Fast response function other than trip command such as interlocking, blocking, etc.</td> <td>P1 - 100ms P2 - 20ms P3 - 20ms</td> </tr> <tr> <td style="text-align: center;">2</td> <td>Medium speed messages</td> <td>Calculated r.m.s. values</td> <td><100ms</td> </tr> <tr> <td style="text-align: center;">3</td> <td>Low speed messages containing complex messages that may require time tagging</td> <td>Slow speed auto-control functions, transmission of event records, set point, etc.</td> <td><300ms</td> </tr> <tr> <td style="text-align: center;">4</td> <td>Future Raw data messages</td> <td>Voltage & current phasor from instrument transformer with sampling rate of 480 Hz. These values are for protection & control usage</td> <td>P1 - 10ms P2 - 3ms P3 - 3ms</td> </tr> <tr> <td style="text-align: center;">5</td> <td>File transfer functions Time synchronization messages</td> <td>Lowest priority. Transfer large file of recording, information, setting etc.</td> <td>>1000ms</td> </tr> <tr> <td rowspan="3" style="text-align: center;">6</td> <td rowspan="3">Control and Protection Events</td> <td rowspan="3">Used to synchronize internal clock of IED in SCPS. Include all station, bay and process level IE</td> <td>T1 -Time tagging of events ±1ms</td> </tr> <tr> <td>T2 -Time tagging of zero crossings and data for distributed ±0.1ms</td> </tr> <tr> <td>T3 Time tagging for sampled values ±25µs</td> </tr> <tr> <td rowspan="2" style="text-align: center;">7</td> <td rowspan="2">Instrument transformer</td> <td rowspan="2">Used to transfer control for security</td> <td>T4 ±4µs</td> </tr> <tr> <td>T5 ±1µs</td> </tr> <tr> <td></td> <td>Command messages with access control</td> <td></td> <td>>1000ms</td> </tr> </tbody> </table>	Message Type	Description	Typical use	Performance	1	Fast messages - Simple binary code containing data, command or simple message. Triggers the receiving IED to respond immediately.	Trip command to XCBR, intertrip and scheme discriminations	P1 - 10ms	P2 - 3ms	P3 - 3ms	1B	Fast messages for Others	Fast response function other than trip command such as interlocking, blocking, etc.	P1 - 100ms P2 - 20ms P3 - 20ms	2	Medium speed messages	Calculated r.m.s. values	<100ms	3	Low speed messages containing complex messages that may require time tagging	Slow speed auto-control functions, transmission of event records, set point, etc.	<300ms	4	Future Raw data messages	Voltage & current phasor from instrument transformer with sampling rate of 480 Hz. These values are for protection & control usage	P1 - 10ms P2 - 3ms P3 - 3ms	5	File transfer functions Time synchronization messages	Lowest priority. Transfer large file of recording, information, setting etc.	>1000ms	6	Control and Protection Events	Used to synchronize internal clock of IED in SCPS. Include all station, bay and process level IE	T1 -Time tagging of events ±1ms	T2 -Time tagging of zero crossings and data for distributed ±0.1ms	T3 Time tagging for sampled values ±25µs	7	Instrument transformer	Used to transfer control for security	T4 ±4µs	T5 ±1µs		Command messages with access control		>1000ms				
Message Type	Description	Typical use	Performance																																															
1	Fast messages - Simple binary code containing data, command or simple message. Triggers the receiving IED to respond immediately.	Trip command to XCBR, intertrip and scheme discriminations	P1 - 10ms																																															
			P2 - 3ms																																															
			P3 - 3ms																																															
1B	Fast messages for Others	Fast response function other than trip command such as interlocking, blocking, etc.	P1 - 100ms P2 - 20ms P3 - 20ms																																															
2	Medium speed messages	Calculated r.m.s. values	<100ms																																															
3	Low speed messages containing complex messages that may require time tagging	Slow speed auto-control functions, transmission of event records, set point, etc.	<300ms																																															
4	Future Raw data messages	Voltage & current phasor from instrument transformer with sampling rate of 480 Hz. These values are for protection & control usage	P1 - 10ms P2 - 3ms P3 - 3ms																																															
5	File transfer functions Time synchronization messages	Lowest priority. Transfer large file of recording, information, setting etc.	>1000ms																																															
6	Control and Protection Events	Used to synchronize internal clock of IED in SCPS. Include all station, bay and process level IE	T1 -Time tagging of events ±1ms																																															
			T2 -Time tagging of zero crossings and data for distributed ±0.1ms																																															
			T3 Time tagging for sampled values ±25µs																																															
7	Instrument transformer	Used to transfer control for security	T4 ±4µs																																															
			T5 ±1µs																																															
	Command messages with access control		>1000ms																																															

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page												
	<p style="text-align: center;">Table 7.8 – Message Performance</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th colspan="3" style="background-color: #e1e5e9;">Performance Class</th> </tr> </thead> <tbody> <tr> <td style="width: 10%;">P1</td> <td style="width: 40%;">Distribution with low requirements</td> <td style="width: 50%;">M1 Quality metering up to the 5th harmonic</td> </tr> <tr> <td>P2</td> <td>Transmission bay</td> <td>M2 Quality metering up to the 13th harmonic</td> </tr> <tr> <td>P3</td> <td>Transmission bay with top performance requirements</td> <td>M3 Quality metering up to the 40th harmonic</td> </tr> </tbody> </table>	Performance Class			P1	Distribution with low requirements	M1 Quality metering up to the 5th harmonic	P2	Transmission bay	M2 Quality metering up to the 13th harmonic	P3	Transmission bay with top performance requirements	M3 Quality metering up to the 40th harmonic				
Performance Class																	
P1	Distribution with low requirements	M1 Quality metering up to the 5th harmonic															
P2	Transmission bay	M2 Quality metering up to the 13th harmonic															
P3	Transmission bay with top performance requirements	M3 Quality metering up to the 40th harmonic															
	<p>The definition of the transfer time for the communication message performances is explained in the Figure below. The given performance times are referring to the total transfer time “t” that includes the IEDs internal processing time as well as the transmission time used over the communication network.</p> <div style="text-align: center;"> <p>Figure 7.4 – Transfer Time Definition</p> </div>																
7.9.2	<p>Communication System Performance</p> <p>The following parameters shall be measured at station-operator HMI level to evaluate system performance for worst case scenario which includes normal, abnormal, emergency, and post-fault state of operations.</p>																
	<p>Typical values measured at the station-operator HMI or the Station Level Operator Interface (SLO) is listed in the following table:</p> <p style="text-align: center;">Table 7.9 – HMI Performance</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="background-color: #e1e5e9;">Parameters</th> <th style="background-color: #e1e5e9;">Performance</th> </tr> </thead> <tbody> <tr> <td>Exchange of display (first reaction)</td> <td><1.5 s</td> </tr> <tr> <td>Presentation of a binary change in the process display</td> <td><1 s</td> </tr> <tr> <td>Presentation of Analog change in the process display</td> <td><1.5 s</td> </tr> <tr> <td>From order to process output</td> <td><1 s</td> </tr> <tr> <td>From order to updating the display</td> <td><2 s</td> </tr> </tbody> </table>	Parameters	Performance	Exchange of display (first reaction)	<1.5 s	Presentation of a binary change in the process display	<1 s	Presentation of Analog change in the process display	<1.5 s	From order to process output	<1 s	From order to updating the display	<2 s				
Parameters	Performance																
Exchange of display (first reaction)	<1.5 s																
Presentation of a binary change in the process display	<1 s																
Presentation of Analog change in the process display	<1.5 s																
From order to process output	<1 s																
From order to updating the display	<2 s																
7.10	<p>COMMUNICATION SYSTEM AVAILABILITY</p> <p>The Contractor shall refer to Clause 4.3 System Performance of this specification, and IEC 61850-7, for details on communication system availability.</p>																
7.11	<p>COMMUNICATION SYSTEM MAINTAINABILITY</p> <p>The SCPS designs that do not required periodic preventive maintenance and inspection are preferred by PEA. If periodic maintenance is required, it shall be possible to perform all such work in the field without requiring the associated media, and/or the communication system to be off.</p> <p>The Contractor shall refer to IEC 61850-7, for details on the maintainability.</p>																

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page										
7.12	IEC 61850 ACSI CONFORMANCE STATEMENTS Refer to Tables A.1-A.4 of IEC 61850-7-2 for the IEC 61850 ACSI Conformance Statement for PEA requirements, i.e. 1) ACSI Basic Conformance Statement 2) ACSI Models Conformance Statement, and 3) ACSI Service Conformance Statement.														
7.13	INFORMATION MANAGEMENT SYSTEM The structure of information management system for the SCPS is depicted in Figure 7.5. <div style="text-align: center;"> <p>Figure 7.5 – Information Management System</p> </div>														
	The Information Management System shall consist of: <table border="1" style="width: 100%; border-collapse: collapse;"> <caption>Table 7.10 – Substation Data and Information</caption> <thead> <tr> <th style="text-align: center;">Topic</th> <th style="text-align: center;">Comment</th> </tr> </thead> <tbody> <tr> <td style="vertical-align: top;">Substation Data and Information</td> <td> The substation data types are: Operational Data: Typical instantaneous measurement values (current, voltage, frequency), indications & status change/event that are conveyed to SCADA master station and Station-operator HMI/GLOI Non-Operational Data: All other non-instantaneous substation information, such as: oscillography waveform records, fault data, configuration files; and all information from IED Control Commands: Control command messages sent by operators and control processes to optimise and restore the state of power system IT Infrastructure Data: All communication & network-related data such as: network & device status, activities, etc. Data priority and time requirements shall be determined with operational data and control command at the highest priority. </td> </tr> <tr> <td style="vertical-align: top;">Communication Infrastructure</td> <td> 1) Networked communication architecture using Ethernet and Web technology 2) Network devices and time synchronisation 3) Substation clients such as: Engineering Workstation 4) High speed database server - Data Historian (Real-time database) and Relational Database 5) Network and system management system </td> </tr> <tr> <td style="vertical-align: top;">Applications Utilising the Information</td> <td> 1) SCPS functions and applications 2) SCADA 3) Condition-based (optional) and self-monitoring of primary and secondary equipment 4) Network and system management 5) Configuration and setting management 6) Fault handling, analysis, evaluation & diagnostics 7) Alarm and event handling and analysis 8) Trending 9) Asset maintenance and management </td> </tr> <tr> <td style="vertical-align: top;">Users/Clients (both local and remote users) of the Information and Applications:</td> <td> 1) SCADA gateway and control centre 2) Substation Operator through Station-operator HMI/GLOI 3) Engineering Workstation 4) Protection System Engineering 5) Operation & Maintenance 6) Asset management </td> </tr> </tbody> </table>	Topic	Comment	Substation Data and Information	The substation data types are: Operational Data: Typical instantaneous measurement values (current, voltage, frequency), indications & status change/event that are conveyed to SCADA master station and Station-operator HMI/GLOI Non-Operational Data: All other non-instantaneous substation information, such as: oscillography waveform records, fault data, configuration files; and all information from IED Control Commands: Control command messages sent by operators and control processes to optimise and restore the state of power system IT Infrastructure Data: All communication & network-related data such as: network & device status, activities, etc. Data priority and time requirements shall be determined with operational data and control command at the highest priority.	Communication Infrastructure	1) Networked communication architecture using Ethernet and Web technology 2) Network devices and time synchronisation 3) Substation clients such as: Engineering Workstation 4) High speed database server - Data Historian (Real-time database) and Relational Database 5) Network and system management system	Applications Utilising the Information	1) SCPS functions and applications 2) SCADA 3) Condition-based (optional) and self-monitoring of primary and secondary equipment 4) Network and system management 5) Configuration and setting management 6) Fault handling, analysis, evaluation & diagnostics 7) Alarm and event handling and analysis 8) Trending 9) Asset maintenance and management	Users/Clients (both local and remote users) of the Information and Applications:	1) SCADA gateway and control centre 2) Substation Operator through Station-operator HMI/GLOI 3) Engineering Workstation 4) Protection System Engineering 5) Operation & Maintenance 6) Asset management				
Topic	Comment														
Substation Data and Information	The substation data types are: Operational Data: Typical instantaneous measurement values (current, voltage, frequency), indications & status change/event that are conveyed to SCADA master station and Station-operator HMI/GLOI Non-Operational Data: All other non-instantaneous substation information, such as: oscillography waveform records, fault data, configuration files; and all information from IED Control Commands: Control command messages sent by operators and control processes to optimise and restore the state of power system IT Infrastructure Data: All communication & network-related data such as: network & device status, activities, etc. Data priority and time requirements shall be determined with operational data and control command at the highest priority.														
Communication Infrastructure	1) Networked communication architecture using Ethernet and Web technology 2) Network devices and time synchronisation 3) Substation clients such as: Engineering Workstation 4) High speed database server - Data Historian (Real-time database) and Relational Database 5) Network and system management system														
Applications Utilising the Information	1) SCPS functions and applications 2) SCADA 3) Condition-based (optional) and self-monitoring of primary and secondary equipment 4) Network and system management 5) Configuration and setting management 6) Fault handling, analysis, evaluation & diagnostics 7) Alarm and event handling and analysis 8) Trending 9) Asset maintenance and management														
Users/Clients (both local and remote users) of the Information and Applications:	1) SCADA gateway and control centre 2) Substation Operator through Station-operator HMI/GLOI 3) Engineering Workstation 4) Protection System Engineering 5) Operation & Maintenance 6) Asset management														

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page										
	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Topic</th> <th style="text-align: center;">Comment</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;">7) Planning</td> <td></td> </tr> <tr> <td style="text-align: center;">Substation Access Control and Cyber Security</td> <td> 1) Access Control such as user ID authentication, password management, access management 2) Cyber security measures </td> </tr> </tbody> </table> <p style="text-align: center; margin-top: 5px;">Table 7.11 – Sources of Substation Data</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Topic</th> <th style="text-align: center;">Comment</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;">Sources of Substation Data</td> <td> 1) IED 2) Sensor 3) Allow IED data sharing with other multiple clients connected to the communication network. </td> </tr> </tbody> </table>	Topic	Comment	7) Planning		Substation Access Control and Cyber Security	1) Access Control such as user ID authentication, password management, access management 2) Cyber security measures	Topic	Comment	Sources of Substation Data	1) IED 2) Sensor 3) Allow IED data sharing with other multiple clients connected to the communication network.				
Topic	Comment														
7) Planning															
Substation Access Control and Cyber Security	1) Access Control such as user ID authentication, password management, access management 2) Cyber security measures														
Topic	Comment														
Sources of Substation Data	1) IED 2) Sensor 3) Allow IED data sharing with other multiple clients connected to the communication network.														
7.14	<p>REDUNDANCY</p> <p>The Contractor shall comply with IEC 61850-3 Reliability Requirement. Full power redundancy with support for two power supplies shall also be provided. These power supplies can be of the same type, or of mixed voltage type to ensure reliability through diverse power sources.</p>														
7.15	<p>CABLE MANAGEMENT</p> <p>The Contractor shall provide all interconnecting wires, cables, connectors, LAN cables, and other wiring required by the SCPS.</p>														
	<p>The Contractor shall submit the results of the survey of the cable route and equipment installation location, including workshop drawings and installation procedures, to PEA for approval before installation.</p>														
	<p>All necessary cabling works with the substation building such as installation of cable trays, cable ducts, cable ladders and support or any other such work to facilitate cabling between the equipment under the scope of this specification and PEA equipment shall be considered as part of the scope of work for the Contractor. PEA will not be responsible for any future claims for minor works within the substation building to facilitate cabling.</p>														
	<p>The LAN supporting the distributed BCU, Protective relays and MU shall utilize fibre optic cables, shall provide to be glass type to satisfy the distribution distances and overall performance requirements and shall be approved by PEA.</p>														

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed of Data	Referred to Page																																															
8 8.2 8.2.3	SYSTEM COMPONENT REQUIREMENTS INTELLIGENT ELECTRONIC DEVICE (IED) Device Electrical Parameter Values The standard device electrical parameter values are: <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Electrical Parameter Requirements</th> <th style="text-align: center;">Standard Values</th> </tr> </thead> <tbody> <tr> <td>Nominal/Rated Auxiliary Operating Voltage (large range)</td> <td>125 VDC</td> </tr> <tr> <td>Operative Ranges Auxiliary Operating Voltage (80% to 110% range)</td> <td>88 to 138 VDC</td> </tr> <tr> <td>Rated DC Burden (Watts)</td> <td>To be declared by the manufacturer</td> </tr> <tr> <td>Total Device Accuracy (%) (Protective relay of Device)</td> <td>± 5%</td> </tr> <tr> <td>Total Device Accuracy (%) (Control Device)</td> <td>± 1%</td> </tr> </tbody> </table>	Electrical Parameter Requirements	Standard Values	Nominal/Rated Auxiliary Operating Voltage (large range)	125 VDC	Operative Ranges Auxiliary Operating Voltage (80% to 110% range)	88 to 138 VDC	Rated DC Burden (Watts)	To be declared by the manufacturer	Total Device Accuracy (%) (Protective relay of Device)	± 5%	Total Device Accuracy (%) (Control Device)	± 1%																																							
Electrical Parameter Requirements	Standard Values																																																			
Nominal/Rated Auxiliary Operating Voltage (large range)	125 VDC																																																			
Operative Ranges Auxiliary Operating Voltage (80% to 110% range)	88 to 138 VDC																																																			
Rated DC Burden (Watts)	To be declared by the manufacturer																																																			
Total Device Accuracy (%) (Protective relay of Device)	± 5%																																																			
Total Device Accuracy (%) (Control Device)	± 1%																																																			
	The standard nominal range of ambient temperature is -10°C to 55°C.																																																			
8.2.5	Technological Conformance and Mechanical Requirements The electrical technological and mechanical hardware tests and standards for the devices are: <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Electrical Technological Conformance and Mechanical Requirements</th> <th style="text-align: center;">Standards</th> <th style="text-align: center;">Type Test Descriptions</th> </tr> </thead> <tbody> <tr> <td>Mechanical</td> <td>IEC 60255-21-1</td> <td>Vibration test</td> </tr> <tr> <td rowspan="2">Stress – Vibration and Shock</td> <td>IEC 60255-21-2</td> <td>Shock and bump test</td> </tr> <tr> <td>IEC 60255-21-3</td> <td>Seismic Test</td> </tr> <tr> <td rowspan="2">Insulation</td> <td>IEC 60255-27</td> <td>High Voltage Test and Impulse Voltage Tests.</td> </tr> <tr> <td>IEC 60255-1</td> <td></td> </tr> <tr> <td rowspan="10">Electromagnetic Compatibility – Immunity</td> <td>IEC 60255-26</td> <td>Damped oscillatory wave test</td> </tr> <tr> <td>IEC 60255-26</td> <td>Fast transient test</td> </tr> <tr> <td>IEC 61000-4-4 Class 4</td> <td></td> </tr> <tr> <td>IEC 60255-22-5</td> <td>Surge Test</td> </tr> <tr> <td>IEC 61000-4-5 Class 3</td> <td></td> </tr> <tr> <td>IEC 60255-22-6</td> <td>Conducted radio interference test</td> </tr> <tr> <td>IEC 61000-4-6 Class 3</td> <td></td> </tr> <tr> <td>IEC 60255-26</td> <td>Electrostatic discharge test</td> </tr> <tr> <td>IEC 61000-4-2 Class 3</td> <td></td> </tr> <tr> <td>IEC 61000-4-11 for AC IEC 60255-3 and IEC 60255-26 for DC</td> <td>Variations and interruptions in AC and DC auxiliary voltages.</td> </tr> <tr> <td rowspan="3">Electromagnetic Compatibility – Noise Emission</td> <td>IEC 61000-4-3 Class 3</td> <td>Electromagnetic fields</td> </tr> <tr> <td>IEC 61000-4-8 Class 5</td> <td>50Hz power frequency magnetic fields</td> </tr> <tr> <td>CISPR 11, Class A, Group I. IEC 60555-2</td> <td>Conducted RF interference on power supply terminals and radiated interference. Harmonics for AC supply</td> </tr> <tr> <td></td> <td>CISPR 14</td> <td>Flicker</td> </tr> </tbody> </table>	Electrical Technological Conformance and Mechanical Requirements	Standards	Type Test Descriptions	Mechanical	IEC 60255-21-1	Vibration test	Stress – Vibration and Shock	IEC 60255-21-2	Shock and bump test	IEC 60255-21-3	Seismic Test	Insulation	IEC 60255-27	High Voltage Test and Impulse Voltage Tests.	IEC 60255-1		Electromagnetic Compatibility – Immunity	IEC 60255-26	Damped oscillatory wave test	IEC 60255-26	Fast transient test	IEC 61000-4-4 Class 4		IEC 60255-22-5	Surge Test	IEC 61000-4-5 Class 3		IEC 60255-22-6	Conducted radio interference test	IEC 61000-4-6 Class 3		IEC 60255-26	Electrostatic discharge test	IEC 61000-4-2 Class 3		IEC 61000-4-11 for AC IEC 60255-3 and IEC 60255-26 for DC	Variations and interruptions in AC and DC auxiliary voltages.	Electromagnetic Compatibility – Noise Emission	IEC 61000-4-3 Class 3	Electromagnetic fields	IEC 61000-4-8 Class 5	50Hz power frequency magnetic fields	CISPR 11, Class A, Group I. IEC 60555-2	Conducted RF interference on power supply terminals and radiated interference. Harmonics for AC supply		CISPR 14	Flicker				
Electrical Technological Conformance and Mechanical Requirements	Standards	Type Test Descriptions																																																		
Mechanical	IEC 60255-21-1	Vibration test																																																		
Stress – Vibration and Shock	IEC 60255-21-2	Shock and bump test																																																		
	IEC 60255-21-3	Seismic Test																																																		
Insulation	IEC 60255-27	High Voltage Test and Impulse Voltage Tests.																																																		
	IEC 60255-1																																																			
Electromagnetic Compatibility – Immunity	IEC 60255-26	Damped oscillatory wave test																																																		
	IEC 60255-26	Fast transient test																																																		
	IEC 61000-4-4 Class 4																																																			
	IEC 60255-22-5	Surge Test																																																		
	IEC 61000-4-5 Class 3																																																			
	IEC 60255-22-6	Conducted radio interference test																																																		
	IEC 61000-4-6 Class 3																																																			
	IEC 60255-26	Electrostatic discharge test																																																		
	IEC 61000-4-2 Class 3																																																			
	IEC 61000-4-11 for AC IEC 60255-3 and IEC 60255-26 for DC	Variations and interruptions in AC and DC auxiliary voltages.																																																		
Electromagnetic Compatibility – Noise Emission	IEC 61000-4-3 Class 3	Electromagnetic fields																																																		
	IEC 61000-4-8 Class 5	50Hz power frequency magnetic fields																																																		
	CISPR 11, Class A, Group I. IEC 60555-2	Conducted RF interference on power supply terminals and radiated interference. Harmonics for AC supply																																																		
	CISPR 14	Flicker																																																		
8.2.6	Operating and Reset Time The required operating and reset time of the protection device are: <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Protection</th> <th style="text-align: center;">Maximum Operating Time</th> <th style="text-align: center;">Maximum Reset Time</th> </tr> </thead> <tbody> <tr> <td>Main Line Differential Protection</td> <td style="text-align: center;">40 ms</td> <td style="text-align: center;">40 ms</td> </tr> <tr> <td>Maximum Fault Clearing Time</td> <td style="text-align: center;">150 ms</td> <td></td> </tr> </tbody> </table> <p>Note:</p> <ol style="list-style-type: none"> 1) CB operating time is assumed to be less than 40 ms for 275kV & 500kV system voltage and 50 ms for 115kV system voltage. 2) Relay operating time includes: relay fault inception detection time, microprocessor time and relay output contact time. 3) Telecommunication carrier send/receive time (from relay to relay) is assumed to be less than 20 ms. 4) Telecommunication transmission delay is assumed to be less than 10 ms. 5) Handle a delay variation or asymmetric delay of not more than 0.25ms. 	Protection	Maximum Operating Time	Maximum Reset Time	Main Line Differential Protection	40 ms	40 ms	Maximum Fault Clearing Time	150 ms																																											
Protection	Maximum Operating Time	Maximum Reset Time																																																		
Main Line Differential Protection	40 ms	40 ms																																																		
Maximum Fault Clearing Time	150 ms																																																			
8.2.7 (ADDENDUM)	The Human Machine Interface (HMI) for protection device shall be provided as a user or operator interface. The HMI provides device parameter display, device operational record/status display and device interrogation facility. The basic requirements of the HMI are:																																																			

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed of Data	Referred to Page														
	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Basic Requirements</th> <th style="text-align: center;">Details</th> </tr> </thead> <tbody> <tr> <td>Human Machine Interface (HMI)</td> <td>Alpha-numeric message display, Liquid Crystal Display (LCD) to display information.</td> </tr> </tbody> </table>	Basic Requirements	Details	Human Machine Interface (HMI)	Alpha-numeric message display, Liquid Crystal Display (LCD) to display information.														
Basic Requirements	Details																		
Human Machine Interface (HMI)	Alpha-numeric message display, Liquid Crystal Display (LCD) to display information.																		
8.2.8 (ADDENDUM)	<p style="color: red;">The HMI for control device shall be provided as a user or operator interface. The HMI provides device parameter display, device operational record/status display and device interrogation facility.</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Basic Requirements</th> <th style="text-align: center;">Details</th> </tr> </thead> <tbody> <tr> <td>Human Machine Interface (HMI)</td> <td>Alpha-numeric message display, Liquid Crystal Display (LCD) to display information.</td> </tr> <tr> <td>Information Navigation</td> <td>User friendly HMI hierarchical navigation structure</td> </tr> <tr> <td>Mounting/Location</td> <td>Front of the device</td> </tr> <tr> <td>View or Display</td> <td> <ol style="list-style-type: none"> 1) View or display device settings and configurations 2) View or monitor service and measurement/metering values 3) View or display event and relevant fault information 4) View or display IED internal events 5) View or display device information/status </td> </tr> <tr> <td>Device Control</td> <td> <ol style="list-style-type: none"> 1) Control switching devices with necessary software interlocking for bay control device 2) Select-before-execute command procedure 3) Control mode selection (Local/Remote) 4) Interrogate or access device information/status 5) Programmable logic control </td> </tr> <tr> <td>Local Information and Indication View</td> <td> <ol style="list-style-type: none"> 1) Bay Indications 2) Fault information depending on IED functions 3) IED event records and status 4) Measurements under normal load conditions </td> </tr> </tbody> </table>	Basic Requirements	Details	Human Machine Interface (HMI)	Alpha-numeric message display, Liquid Crystal Display (LCD) to display information.	Information Navigation	User friendly HMI hierarchical navigation structure	Mounting/Location	Front of the device	View or Display	<ol style="list-style-type: none"> 1) View or display device settings and configurations 2) View or monitor service and measurement/metering values 3) View or display event and relevant fault information 4) View or display IED internal events 5) View or display device information/status 	Device Control	<ol style="list-style-type: none"> 1) Control switching devices with necessary software interlocking for bay control device 2) Select-before-execute command procedure 3) Control mode selection (Local/Remote) 4) Interrogate or access device information/status 5) Programmable logic control 	Local Information and Indication View	<ol style="list-style-type: none"> 1) Bay Indications 2) Fault information depending on IED functions 3) IED event records and status 4) Measurements under normal load conditions 				
Basic Requirements	Details																		
Human Machine Interface (HMI)	Alpha-numeric message display, Liquid Crystal Display (LCD) to display information.																		
Information Navigation	User friendly HMI hierarchical navigation structure																		
Mounting/Location	Front of the device																		
View or Display	<ol style="list-style-type: none"> 1) View or display device settings and configurations 2) View or monitor service and measurement/metering values 3) View or display event and relevant fault information 4) View or display IED internal events 5) View or display device information/status 																		
Device Control	<ol style="list-style-type: none"> 1) Control switching devices with necessary software interlocking for bay control device 2) Select-before-execute command procedure 3) Control mode selection (Local/Remote) 4) Interrogate or access device information/status 5) Programmable logic control 																		
Local Information and Indication View	<ol style="list-style-type: none"> 1) Bay Indications 2) Fault information depending on IED functions 3) IED event records and status 4) Measurements under normal load conditions 																		
(ADDENDUM)	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Basic Requirements</th> <th style="text-align: center;">Details</th> </tr> </thead> <tbody> <tr> <td>Change or modify</td> <td> <ol style="list-style-type: none"> 1) Change or modify device settings and configurations 2) Change or modify device setting groups </td> </tr> <tr> <td>Testing and Monitoring</td> <td> <ol style="list-style-type: none"> 1) Monitoring of device self-supervision status 2) Testing and commissioning assistance </td> </tr> <tr> <td>Memory Type</td> <td>Non-volatile. Settings view not to be lost in the event of supply failure.</td> </tr> <tr> <td>Password</td> <td>Password restriction for change or modify the IED setting/configuration and commissioning assistance</td> </tr> </tbody> </table>	Basic Requirements	Details	Change or modify	<ol style="list-style-type: none"> 1) Change or modify device settings and configurations 2) Change or modify device setting groups 	Testing and Monitoring	<ol style="list-style-type: none"> 1) Monitoring of device self-supervision status 2) Testing and commissioning assistance 	Memory Type	Non-volatile. Settings view not to be lost in the event of supply failure.	Password	Password restriction for change or modify the IED setting/configuration and commissioning assistance								
Basic Requirements	Details																		
Change or modify	<ol style="list-style-type: none"> 1) Change or modify device settings and configurations 2) Change or modify device setting groups 																		
Testing and Monitoring	<ol style="list-style-type: none"> 1) Monitoring of device self-supervision status 2) Testing and commissioning assistance 																		
Memory Type	Non-volatile. Settings view not to be lost in the event of supply failure.																		
Password	Password restriction for change or modify the IED setting/configuration and commissioning assistance																		
8.2.9	<p>Relay Indicator</p> <p>The indications shall be visible with or without front cover mounted. The indication shall be stored and will not be lost in the event of DC supply failure.</p>																		

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed of Data	Referred to Page																						
8.2.10	Event Recording <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Basic Requirements</th> <th style="text-align: center;">Details</th> </tr> </thead> <tbody> <tr> <td>Number of Event Record</td> <td>Capacity of at least 100 event records, and at least 5 records of oscillographic recordings</td> </tr> <tr> <td>Timed & Date</td> <td>Time & date stamped by relay real time clock</td> </tr> <tr> <td>Relay real time clock</td> <td>Resolution 1 ms or less</td> </tr> <tr> <td>Memory Recording Sequence</td> <td>First in first out (FIFO)</td> </tr> <tr> <td>Display View</td> <td>LCD display Remote/PC access via the appropriate communication facility</td> </tr> <tr> <td>Chronological Event Record</td> <td> <ol style="list-style-type: none"> 1) Relay tripping 2) Binary I/O operation or change state 3) Relay internal algorithm pickup/drop-off 4) Relay internal events 5) Relay self-supervision/monitoring state 6) Setting change </td> </tr> <tr> <td>Memory Type</td> <td>Stored in non-volatile memory</td> </tr> </tbody> </table>	Basic Requirements	Details	Number of Event Record	Capacity of at least 100 event records, and at least 5 records of oscillographic recordings	Timed & Date	Time & date stamped by relay real time clock	Relay real time clock	Resolution 1 ms or less	Memory Recording Sequence	First in first out (FIFO)	Display View	LCD display Remote/PC access via the appropriate communication facility	Chronological Event Record	<ol style="list-style-type: none"> 1) Relay tripping 2) Binary I/O operation or change state 3) Relay internal algorithm pickup/drop-off 4) Relay internal events 5) Relay self-supervision/monitoring state 6) Setting change 	Memory Type	Stored in non-volatile memory										
Basic Requirements	Details																										
Number of Event Record	Capacity of at least 100 event records, and at least 5 records of oscillographic recordings																										
Timed & Date	Time & date stamped by relay real time clock																										
Relay real time clock	Resolution 1 ms or less																										
Memory Recording Sequence	First in first out (FIFO)																										
Display View	LCD display Remote/PC access via the appropriate communication facility																										
Chronological Event Record	<ol style="list-style-type: none"> 1) Relay tripping 2) Binary I/O operation or change state 3) Relay internal algorithm pickup/drop-off 4) Relay internal events 5) Relay self-supervision/monitoring state 6) Setting change 																										
Memory Type	Stored in non-volatile memory																										
8.2.11	Fault Recording The basic requirements of the relay fault recording are <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Basic Requirements</th> <th style="text-align: center;">Details</th> </tr> </thead> <tbody> <tr> <td>Number of Fault Record</td> <td>To be declared by the manufacturer. Minimum 5 fault records.</td> </tr> <tr> <td>Timed & Date</td> <td>Time & date stamped by relay real time clock</td> </tr> <tr> <td>Recording Duration</td> <td> <ol style="list-style-type: none"> 1) Dynamic fault record duration up to 5.0 second 2) Pre and post fault duration </td> </tr> <tr> <td>File Format</td> <td>COMTRADE format (IEC 60255-24)</td> </tr> <tr> <td>Sampling Frequency</td> <td> <ol style="list-style-type: none"> 1) To be declared by the manufacturer 2) Minimum 1 kHz </td> </tr> <tr> <td>Memory Recording Sequence</td> <td>First in first out (FIFO)</td> </tr> <tr> <td>Number of Analog and Binary Channels</td> <td>To be declared by the manufacturer</td> </tr> <tr> <td>Oscillographic Recording and Event Information</td> <td> <ol style="list-style-type: none"> 1) Voltage waveform 2) Current waveform 3) Zero sequence voltage & current 4) Activated element 5) Binary Input and Output Status 6) CB status </td> </tr> <tr> <td>Triggering</td> <td> <ol style="list-style-type: none"> 1) Protection start or trip 2) Binary input (manual/external triggering) </td> </tr> <tr> <td>Display View</td> <td> <ol style="list-style-type: none"> 1) Relay Interrogation and Analysis Software Tools 2) Software type to be declared by the manufacturer </td> </tr> </tbody> </table>	Basic Requirements	Details	Number of Fault Record	To be declared by the manufacturer. Minimum 5 fault records.	Timed & Date	Time & date stamped by relay real time clock	Recording Duration	<ol style="list-style-type: none"> 1) Dynamic fault record duration up to 5.0 second 2) Pre and post fault duration 	File Format	COMTRADE format (IEC 60255-24)	Sampling Frequency	<ol style="list-style-type: none"> 1) To be declared by the manufacturer 2) Minimum 1 kHz 	Memory Recording Sequence	First in first out (FIFO)	Number of Analog and Binary Channels	To be declared by the manufacturer	Oscillographic Recording and Event Information	<ol style="list-style-type: none"> 1) Voltage waveform 2) Current waveform 3) Zero sequence voltage & current 4) Activated element 5) Binary Input and Output Status 6) CB status 	Triggering	<ol style="list-style-type: none"> 1) Protection start or trip 2) Binary input (manual/external triggering) 	Display View	<ol style="list-style-type: none"> 1) Relay Interrogation and Analysis Software Tools 2) Software type to be declared by the manufacturer 				
Basic Requirements	Details																										
Number of Fault Record	To be declared by the manufacturer. Minimum 5 fault records.																										
Timed & Date	Time & date stamped by relay real time clock																										
Recording Duration	<ol style="list-style-type: none"> 1) Dynamic fault record duration up to 5.0 second 2) Pre and post fault duration 																										
File Format	COMTRADE format (IEC 60255-24)																										
Sampling Frequency	<ol style="list-style-type: none"> 1) To be declared by the manufacturer 2) Minimum 1 kHz 																										
Memory Recording Sequence	First in first out (FIFO)																										
Number of Analog and Binary Channels	To be declared by the manufacturer																										
Oscillographic Recording and Event Information	<ol style="list-style-type: none"> 1) Voltage waveform 2) Current waveform 3) Zero sequence voltage & current 4) Activated element 5) Binary Input and Output Status 6) CB status 																										
Triggering	<ol style="list-style-type: none"> 1) Protection start or trip 2) Binary input (manual/external triggering) 																										
Display View	<ol style="list-style-type: none"> 1) Relay Interrogation and Analysis Software Tools 2) Software type to be declared by the manufacturer 																										
8.2.12	Fault Locator (For Line Protection) The basic requirements of the relay fault location are: <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Basic Requirements</th> <th style="text-align: center;">Details</th> </tr> </thead> <tbody> <tr> <td>Distance to Fault Measurement</td> <td>Impedance loop</td> </tr> <tr> <td>Fault Distance display</td> <td> <ol style="list-style-type: none"> 1) kilometre line length (km), or 2) Percentage of line length (%) </td> </tr> <tr> <td>Optional Fault Distance display</td> <td>Impedance line length (ohm primary or secondary)</td> </tr> <tr> <td>Other options</td> <td>Zero sequence mutual coupling compensation activation for parallel double circuit lines</td> </tr> </tbody> </table>	Basic Requirements	Details	Distance to Fault Measurement	Impedance loop	Fault Distance display	<ol style="list-style-type: none"> 1) kilometre line length (km), or 2) Percentage of line length (%) 	Optional Fault Distance display	Impedance line length (ohm primary or secondary)	Other options	Zero sequence mutual coupling compensation activation for parallel double circuit lines																
Basic Requirements	Details																										
Distance to Fault Measurement	Impedance loop																										
Fault Distance display	<ol style="list-style-type: none"> 1) kilometre line length (km), or 2) Percentage of line length (%) 																										
Optional Fault Distance display	Impedance line length (ohm primary or secondary)																										
Other options	Zero sequence mutual coupling compensation activation for parallel double circuit lines																										

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed of Data	Referred to Page								
8.2.13	Measurement/ Metering Function The basic requirements of the relay measurement/metering function are: <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: center;">Basic Requirements</th> <th style="text-align: center;">Details</th> </tr> </thead> <tbody> <tr> <td>Measurements under normal load conditions</td> <td> 1) Load current 2) Operating voltage 3) Power </td> </tr> <tr> <td>Display View</td> <td> 1) LCD alpha-numeric display 2) Remote PC access via serial communication facility </td> </tr> <tr> <td>Other Optional Features</td> <td>Able to display in primary or secondary value on system voltage and current</td> </tr> </tbody> </table>	Basic Requirements	Details	Measurements under normal load conditions	1) Load current 2) Operating voltage 3) Power	Display View	1) LCD alpha-numeric display 2) Remote PC access via serial communication facility	Other Optional Features	Able to display in primary or secondary value on system voltage and current				
Basic Requirements	Details												
Measurements under normal load conditions	1) Load current 2) Operating voltage 3) Power												
Display View	1) LCD alpha-numeric display 2) Remote PC access via serial communication facility												
Other Optional Features	Able to display in primary or secondary value on system voltage and current												
8.2.15	IED Clock Circuit and Time-Stamping Capability IEDs shall be equipped with a real-time clock, with full calendar support (including leap year). Clock resolution shall be governed by IEC 60870-4, Table 7 Class TR4. Clocks shall have an accuracy of ± 2 ppm and shall not drift more than twenty (20) ms per hour. All IEDs that need to maintain precise time for time-stamping shall be capable of supporting IEEE 1588 time-synchronization by the Time Data Server, maintaining acceptably low drift in time between synchronizations, and time-stamping events with a precision of ± 0.5 ms relative to the GPS source.												
8.2.16	Performance The IEC 61850 Conformance Test Certificate from an independent laboratory shall be provided as evidence and part of the tender submission. The laboratory shall be accredited by UCA International Users Group with ISO/IEC17025 certification with certification. The IEDs shall not show any non-conformance to IEC 61850 Parts 3, 6, 7-1, 7-2, 7-3, 7-4 & 8-1, and 9-2 (2011).												
8.3.1	Substation LAN Operation of the Substation LAN shall comply with the IEC 61850 Ethernet profile using TCP/IP. Substation LAN shall support 10/100 Mbps for bay level and 1/10/100 Mbps for process level, with consideration of whether 1Gbps is technically and economically appropriate.												
8.3.2	Communication network Cable Construction of Optical Fibre cable (OFC) Characteristics of the OFC shall be the graded index multimode optical fibre conforming to the requirement of IEC Publication No.60793-2-10, 60794-1 and DIN VDE 0888-3. The fibres shall be high grade pure or doped silica. The OFC shall withstand at least 150 kg force without breaking or damaging the fibres in the cable. The permissible bending radius shall be no greater than 20 times the outside diameter of the cable.												

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed of Data	Referred to Page
8.3.4	Ethernet Switch Please refer to Clause 7.3.1 Communication Network Devices- Ethernet Switch.				
8.3.5	HMI Units based on Industrial Computer The HMI unit shall conform to UL approved safety standards and be certified to FCC Class B. The statistical MTBF for the HMI unit shall be not less than 50,000 hours, when analyzed at 75% loading and 25°C. The equipment shall be capable of operating under the specified ambient conditions for indoor equipment.				
	The equipment shall be warranted to work in PEA electrical substation environments. Full repair services shall be available in THAILAND for the selected equipment.				
	All HMI hardware shall be latest available technology and shall have prior approval from the PEA before making orders by the Contractor.				
	One Personal Computer (PC), which is a 19-inch rack mounted industrial type, shall comply with the minimum requirements stated in Annex 3.				
8.3.6	Communications Gateway (CGW) The CGW shall support a data rate of 10/100/1000 Mbps Ethernet port. The CGW interfaces with the SDH WAN through a fibre optic Ethernet port, or can interface with PEA backbone network.				
	The CGW hardware shall be latest available technology and shall have prior approval from PEA before making orders by the Contractor. The CGW shall either be a PC or a Microprocessor Controller. The CGW shall be delivered at least as follows, 1) 1 GHz Intel Processor (or equivalent) 2) 1 GB SDRAM of main memory (or better) 3) 250 GB 24/7 server-type hard disk 4) Real-time clock, calendar with battery backup, and support for time-synchronization. 5) Auto-restart capability. 6) Diagnostics, on-site installation, and validation. 7) Protocol configuration 8) Security Service				
	In case that the Contractor proposes a microprocessor-based IED to work as the CGW, the proposed IED shall at least have performance equivalent to the CGW function specified above.				
8.3.7	Communication Interface Where data communication interfaces using DNP 3.0 protocol are necessary, DNP3.0 over IP shall be used over the Substation LAN.				
	A communication port between PEA SCADA control centre and fibre optic cable at the SCPS or multiplexer is RS-232, as specified in 7.2.				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed of Data	Referred to Page
8.3.8	<p>IED Bay Control Unit (BCU)</p> <p>BCU servers have data acquisition and control responsibilities within the SCPS system. In the systems to be delivered under this technical specification, they connect to traditional I/O points on the back end (e.g. status contacts, counter contacts, analog inputs, and control outputs). On the front end they are presented as IEC 61850 data models, just as though they originated from true IEC 61850-compatible sources. The data from these models shall be selectively delivered to the HMI's Local Repository according to station needs.</p>				
	<p>The BCU servers shall be capable of storing and executing programmable logic applications. In support of a distributed processing environment, they shall be capable of interconnecting with other BCU servers via IEC 61850 GOOSE messaging to acquire status and commands and to provide the same in return. In this way, multiple units can cooperate perform bay interlocking and automation applications. All parameters, configurations, programs, software, and process data shall be stored in non-volatile memory, along with revision control information.</p>				
8.3.12	<p>Printing Facility</p> <p>The printers shall be an A4 color laser printer.</p>				
8.3.13	<p>Control Circuit Requirements and Internal Wiring Conductor</p> <p>All BCUs and Protective relays shall be house in a dust proof cover, class IP51.</p>				
8.3.14	<p>Communication Port</p> <p>Ethernet:</p> <p>- For optic for 10/100 Mbps shall be provided at station level devices and bay level devices.</p>				
8.3.16	<p>KVM Switch</p> <p>The Contractor shall provide communication between a monitor, keyboard, mouse connecting to The HMI-server cabinets in a communication room, by using a KVM Switch.</p>				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed of Data	Referred to Page
8.4	ENGINEERING WORKSTATION AND HMI/SCPS-Server				
8.4.1	<p>Engineering Workstation Functions</p> <p>The main features of the Engineering Workstation shall be:</p> <ol style="list-style-type: none"> 1) Analysis of alarm, events and historical trending 2) Data Historian (Real Time Database) to gather, validate, organize & archive substation data and information from multiple distributed IEDs 3) Dedicated Engineering Interface separate from Station-operator HMI/SCPS-Server / Station Level Operator Interface (SLOI) 4) Local single central point of access of the SCPS and all IEDs within the substation 5) Management of substation configurations, settings and IEC 61850 communication services 6) Monitoring and management of communication network, primary and secondary equipment 7) Panel mounted with all components powered from substation auxiliary DC system without a DC/AC inverter 8) Power system fault information handling, analysis, evaluation & diagnostics 9) Provision of accurate, timely and trusted substation information for supporting effective decision making, engineering, operation & maintenance, fault investigation & diagnostics, and asset management, and planning processes 10) Seamless communication and interrogation with substation IEDs 11) Substation documentation management 12) Value added user specific applications developed utilising the substation information 13) Web-based remote access and applications with system access control and cyber security measures 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed of Data	Referred to Page																
8.4.2	<p>Communication Network Management</p> <p>The Communication Network Management application shall be provided as a management tool to commission, monitor, maintain, troubleshoot, and reconfigure the communication channels and end devices.</p>																				
	<p>The Communication Network Management function shall manage and monitor the status information of the substation communication network, SCPS components together with IED communication interface and communication network devices. The operation and failure of the function shall not affect the substation communication network.</p>																				
8.4.3	<p>System Access Control and Cyber Security Management</p> <p>The major features of the System Access Control and Cyber Security Management function are as follows:</p> <p>Table 8.1 – Security Management</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr style="background-color: #d9ead3;"> <th style="text-align: center;">Level</th> <th style="text-align: center;">Access</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;">Guest</td> <td> <ul style="list-style-type: none"> View or browse the Engineering Workstation display, but no direct access to IEDs or network devices is permitted View the Engineering Workstation data, but not permitted to change or delete data </td> </tr> <tr> <td style="text-align: center;">Operator</td> <td> <ul style="list-style-type: none"> View or browse the Engineering Workstation display Able to connect, access and perform engineering tasks with IEDs or network devices Able to view activity log </td> </tr> <tr> <td style="text-align: center;">System Administrator</td> <td> <ul style="list-style-type: none"> Able to perform as Operator level Able to perform additional administrative features such as resetting the activity log, and configure Engineering Workstation, IEDs and network devices </td> </tr> </tbody> </table>	Level	Access	Guest	<ul style="list-style-type: none"> View or browse the Engineering Workstation display, but no direct access to IEDs or network devices is permitted View the Engineering Workstation data, but not permitted to change or delete data 	Operator	<ul style="list-style-type: none"> View or browse the Engineering Workstation display Able to connect, access and perform engineering tasks with IEDs or network devices Able to view activity log 	System Administrator	<ul style="list-style-type: none"> Able to perform as Operator level Able to perform additional administrative features such as resetting the activity log, and configure Engineering Workstation, IEDs and network devices 												
Level	Access																				
Guest	<ul style="list-style-type: none"> View or browse the Engineering Workstation display, but no direct access to IEDs or network devices is permitted View the Engineering Workstation data, but not permitted to change or delete data 																				
Operator	<ul style="list-style-type: none"> View or browse the Engineering Workstation display Able to connect, access and perform engineering tasks with IEDs or network devices Able to view activity log 																				
System Administrator	<ul style="list-style-type: none"> Able to perform as Operator level Able to perform additional administrative features such as resetting the activity log, and configure Engineering Workstation, IEDs and network devices 																				
	<p>The system will allow access to, and/or manipulation of the following:</p> <p>Table 8.2 – User Access Functions</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr style="background-color: #d9ead3;"> <th style="text-align: center;">Feature</th> <th style="text-align: center;">Description</th> </tr> </thead> <tbody> <tr> <td>Password Management</td> <td> <ul style="list-style-type: none"> User access password identification and verification Password ID management by System Administrator </td> </tr> <tr> <td>Access Management</td> <td> <ul style="list-style-type: none"> User ID authentication User authorisation level management by System Administrator Minimum of three user authorisation permission levels to be provided: </td> </tr> <tr> <td>Information and User Log and Audit Trail</td> <td> <ul style="list-style-type: none"> Automated user log and audit trail in terms of who & when has accessed the system, which user authorization level accessed the system, what activity was performed (e.g. create, edit, delete, etc.) Automated information log and audit trail in terms of how it is handled or changed, who has access to the information, and the protection level Data Historian record and configuration changes </td> </tr> <tr> <td>Network Intrusion Detection System (IDS)</td> <td>Monitor, detect, and respond to unauthorised activity by internal and external intrusion</td> </tr> <tr> <td>Virus Protection</td> <td>Anti-virus solution to prevent the introduction of malicious virus, codes, worm, spy ware and Trojan horse etc. on the Engineering Workstation</td> </tr> <tr> <td>Backup and Recovery</td> <td> <ul style="list-style-type: none"> Create backups System recovering from backup Methodology and procedures to be addressed by Engineering Workstation developer </td> </tr> <tr> <td>Firewalls</td> <td> <ul style="list-style-type: none"> Guard against external threats Placed at router or security perimeter of the SCPS Router and security firewall are supplied as part of ICT scope </td> </tr> </tbody> </table> <p>Please refer to Annex 7 for details of cyber security requirements.</p>	Feature	Description	Password Management	<ul style="list-style-type: none"> User access password identification and verification Password ID management by System Administrator 	Access Management	<ul style="list-style-type: none"> User ID authentication User authorisation level management by System Administrator Minimum of three user authorisation permission levels to be provided: 	Information and User Log and Audit Trail	<ul style="list-style-type: none"> Automated user log and audit trail in terms of who & when has accessed the system, which user authorization level accessed the system, what activity was performed (e.g. create, edit, delete, etc.) Automated information log and audit trail in terms of how it is handled or changed, who has access to the information, and the protection level Data Historian record and configuration changes 	Network Intrusion Detection System (IDS)	Monitor, detect, and respond to unauthorised activity by internal and external intrusion	Virus Protection	Anti-virus solution to prevent the introduction of malicious virus, codes, worm, spy ware and Trojan horse etc. on the Engineering Workstation	Backup and Recovery	<ul style="list-style-type: none"> Create backups System recovering from backup Methodology and procedures to be addressed by Engineering Workstation developer 	Firewalls	<ul style="list-style-type: none"> Guard against external threats Placed at router or security perimeter of the SCPS Router and security firewall are supplied as part of ICT scope 				
Feature	Description																				
Password Management	<ul style="list-style-type: none"> User access password identification and verification Password ID management by System Administrator 																				
Access Management	<ul style="list-style-type: none"> User ID authentication User authorisation level management by System Administrator Minimum of three user authorisation permission levels to be provided: 																				
Information and User Log and Audit Trail	<ul style="list-style-type: none"> Automated user log and audit trail in terms of who & when has accessed the system, which user authorization level accessed the system, what activity was performed (e.g. create, edit, delete, etc.) Automated information log and audit trail in terms of how it is handled or changed, who has access to the information, and the protection level Data Historian record and configuration changes 																				
Network Intrusion Detection System (IDS)	Monitor, detect, and respond to unauthorised activity by internal and external intrusion																				
Virus Protection	Anti-virus solution to prevent the introduction of malicious virus, codes, worm, spy ware and Trojan horse etc. on the Engineering Workstation																				
Backup and Recovery	<ul style="list-style-type: none"> Create backups System recovering from backup Methodology and procedures to be addressed by Engineering Workstation developer 																				
Firewalls	<ul style="list-style-type: none"> Guard against external threats Placed at router or security perimeter of the SCPS Router and security firewall are supplied as part of ICT scope 																				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed of Data	Referred to Page
8.4.6	<p>SCPS System and IED Configuration Management</p> <p>The SCPS Systems and IED Configuration Management application shall be provided;</p> <p>1) to manage, maintain and archive all the Substation Configuration Language (SCL) files using System and IED Configuration engineering tools as follows: a. Library of approved IED Capability Description (ICD) files b. System Specification Description (SSD) files (if available) c. Substation Configuration Description (SCD) file d. Configured IED Description (CID) files (if available)</p> <p>2) to provide capability to automatically update the SCL files during installation and commissioning</p> <p>3) to manage and control the revision or version of the SCL files including and comparing different versions of the configuration file databases</p> <p>4) to configure the substation IEDs based on generated System Configuration Description (.SCD) file specific for the substation</p> <p>5) to provide capability of distributing configuration files from single point of access to various substation IEDs and ensuring version consistency among them</p> <p>6) to provide automated information log and audit trail of the configuration change or revision</p>				
8.4.7	<p>GOOSE Messaging Management</p> <p>Generic Object Oriented Substation Event (GOOSE), supports the exchange of a wide range of possible common data organized by a DATA-SET and is used to very rapidly exchange input and output data mainly of relays of trip, CB position and block, etc. The data exchange is based on publish/subscription. The IED in the same GOOSE can receive data from subscription, and also send data from publish</p>				
8.4.8	<p>Disturbance and Fault Information Handling</p> <p>The Disturbance and Fault Information Handling, application shall be provided;</p> <p>1) to provide IEC 61850 disturbance recorder handling function Logical Node RDRE</p> <p>2) to automatically retrieve, transfer (through IEC61850 file transfer services) or upload fault or disturbance oscillography waveform in COMTRADE file format (IEC 60255-24) from all substation IEDs. The followings are the information to be handled from the files; a. Voltage waveform b. Current waveform c. Zero sequence voltage & current d. Activated element e. Binary Input and Output Status f. CB status</p> <p>3) to collect and archive the fault or disturbance COMTRADE files in Data Historian for further analysis and evaluation</p> <p>4) to provide application software to perform fault or disturbance analysis and evaluation using the retrieved COMTRADE files</p>				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed of Data	Referred to Page
8.4.9	Engineering HMI/SCPS-Server The Engineering HMI/SCPS-Server shall be provided as a graphical user interface for engineers; 1) to access the Engineering Workstation 2) to utilise all the Engineering Workstation functions and applications, and 3) to perform the engineering-related works				
8.4.10	Web Server and Interface The Web Server shall provide user-friendly web-based graphical user interface, accessed via Internet browser; 1) to deliver secure, accurate & timely SCPS information to multiple users 2) to incorporate interactive web-based applications to the user interface 3) to allow remote access from multiple users with different authorization level				
8.4.13	Trending and Historical Analysis The Trending and Historical Analysis application shall be provided to view, trend & analyze accurate operational (real time or historical) process data with high accuracy (actual time stamp) & dependability.				
8.4.14	Automatic Fault Report Generation and Notification The Automatic Fault Report Generation and Notification application shall be provided to automatically deliver accurate, timely and trusted fault & disturbance information to the appropriate personnel.				
8.5	Power Supply power supply voltage variations within the following ranges in accordance with IEC 60870-2-1 Ed. 2. DC-Power supply: 125 V + 20% together with a transformer that will reduce the voltage to 48 V + 20% for communications equipment and PCs. HMI/SCPS-Server will be powered by an AC power supply.				
8.6	POWER DISTRIBUTION SYSTEM The Contractor shall supply power distribution cabinets, power cables, circuit protection, and other accessories needed to supply DC power to the SCPS components.				
8.8	INTEROPERABILITY AMONG DEVICES FROM DIFFERENT MANUFACTURERS, AND WITH LEGACY DEVICES/SYSTEMS Using this specification, in combination with IEC 61850-7 and IEC 61850-6, the Contractor shall make sure that interoperability between devices from different manufacturers is achievable.				
8.8.1	Interoperability among Clients and Servers The Contractor shall develop the necessary IEC 61850-IED interface from detailed IEC 61850 communications requirements provided by PEA so that interoperability at a Bay level is achievable.				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RSUB-010/2560 (Rev.1.0) Substation control and protection system (SCPS)

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed of Data	Referred to Page
8.8.2	Interoperability between Control Systems and Bay LAN Each BCU shall communicate with the BCUs of different manufacturers, protective relays, and other IEDs instead of, or in addition to, the IEDs communicating directly through the bay and station Ethernet Switch, to the SCPS Systems.				
10	ENGINEERING AND CONFIGURATION TOOLS				
10.1	PROTOCOL ANALYSER SOFTWARE The Contractor shall provide test set software for DNP 3.0 protocol and the IEC 61850 communications architecture.				
10.6	ENGINEERING TOOLS The Contractor shall be provided the engineering tools for In IEC 61850-6 part of the standard two different tools are identified in the IEC 61850 engineering process.				
	The following Engineering Tools shall be supplied for substation: 1) IED configuration tools 2) System (Substation) configuration tools 3) IED interrogation, monitoring and analysis software tools 4) Diagnostics and maintenance tools				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RPRO-011/2556 (Rev. 2.0) ARC DETECTION SYSTEM

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page or Clarification Letters
1b	<p>Arc Detection System</p> <p>All design, equipment required within the scope of works, manufacturing and testing shall be in accordance with the IEC, DIN, VDE, ANSI, or equivalent; unless otherwise specified in these specifications.</p>				
1c.1	The arc detection system shall be suitable for installation in the existing high-voltage metal-enclosed indoor switchgears				
1c.2	<p>The arc detection system shall be designed and constructed for indoor installation in PEA's Substation sites and operated under the following conditions:</p> <p>Altitude : up to 1,000 m above sea level Ambient air temperature : up to 40°C Relative humidity : up to 94% Climatic condition : tropical climate</p>				
1c.3	<p>Each arc detection system shall be consisted of the following main equipment:</p> <p>(1) Arc monitoring units (2) Arc detectors/sensors and cables (3) Current sensing units</p> <p>The current sensing unit which included with arc monitoring unit shall be accepted.</p>				
	The arc detection system shall not be activated by interfering light sources, electro-magnetic influences, vibration and torching.				
	<p>The protection principle of the arc detection system consists of two (2) modes:</p> <ul style="list-style-type: none"> - Light intensity and over current - Light intensity only 				
1c.4	<p>Arc monitoring Unit</p> <p>The arc monitoring unit shall detect the occurrence of short-circuit arcing by means of arc detectors/sensors and current sensing units and immediately transmits a tripping signal to trip and lock out all relevant circuit-breakers</p>				
	The system shall be performed the proper protection even all outgoing feeders supplied by one (1) incoming feeder by closing bus coupler circuit-breaker.				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RPRO-011/2556 (Rev. 2.0) ARC DETECTION SYSTEM

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page or Clarification Letters
	When the short-circuit arcing occurs at any points in the incoming cable compartments or incoming switching device compartments, the arc monitoring unit shall send the signal for tripping all circuitbreakers connected to the disturbed busbar including the 115 kV upstream circuit-breaker. Unaffected busbar shall remain in service.				
	When the short-circuit arcing occurs at any point in busbar compartments or switching device compartments except incoming switching device compartments, the arc monitoring unit shall send the signal for tripping all circuit-breakers connected to the disturbed busbars. Unaffected busbar shall remain in service.				
	When the short-circuit arcing occurs at any point in outgoing cable including cable to capacitor bank compartments, the arc monitoring unit shall send the signal for tripping the corresponding circuit-breaker of the feeders only.				
	The corresponding tripped circuit-breakers shall be locked against further closing operation and it shall be possible to override this interlocking through and acknowledge switch.				
	In case of the current sensing unit is out of service, the arc detection system shall be able to perform with complete protection according to able scheme with the event of light only.				
	The bypass switch for rejection the current sensing unit shall be provided.				
	For convenience of access to faulty cubicle, the arc detection system shall be installed properly to indicate the location of internal arc by cubicle basis.				
	The unit shall meet the following requirements: Power supply : 48 V DC or 125 V DC Detectors/sensors : fiber optic wire/bare fiber optic detector Current sensing unit (2-phase+1 ground or 3-phase+1 ground) - Current setting, for phase : 0.5...5.0xIn - Current setting, for ground : 0.1...0.5xIn				
	Indicators - Fault indication and location - Relay self supervision - Fiber optic loop check supervision				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RPRO-011/2556 (Rev. 2.0) ARC DETECTION SYSTEM

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page or Clarification Letters
	<p>Operating time, from detection to : not more than 20 ms. Initiate circuit-breaker tripping</p> <p>Degree of protection of enclosure : IP20 or better</p> <p>Position of installation : anywhere in or near the switchgear</p> <p>Complete with controlling and indication devices, and testing facilities for routine checking the function of the unit while the switchgears in operation.</p>				
1c.5	Arc detectors/sensors and cables				
	The arc detectors/sensors shall be light detectors sensors and shall be installed in each high-voltage compartment of the switchgear panels as follows:				
	<ul style="list-style-type: none"> - Busbar compartment - Switching device compartment - Cable connection compartment - Voltage transformer compartment <p>The detectors/sensors shall be arranged in the manner that every internal arc is detected. The signal from the detectors/sensors shall be transmitted to the arc monitor unit(s) by suitable communication cables.</p>				
1c.6	Current sensing unit				
	The current sensing unit shall be overcurrent two-phase and ground or three-phase and ground relay.				
	The current input for the current sensing unit shall be provided by PEA's existing current transformers at the incoming switchgear.				
	The current sensing unit shall block the tripping of the arc monitoring unit at a load current below a preset value.				
	<p>The unit shall meet the following requirements:</p> <ul style="list-style-type: none"> - Power supply : 48 V DC or 125 V DC - Rated current : 1 A or 5 A - Degree of protection of enclosure : IP 20, or better <p>Complete with control and indicating devices, and testing facilities for routine checking the function of the unit.</p>				
1c.7	Loss-of-DC alarm relay (27X), with special provision for slow dropout				
	The DC under voltage relay (27X) for each DC control and protection circuit shall be provided to alarm for loss of DC potential to the alarm annunciator system.				

Table of Compliance



Bid No. : PAT-SCPS01/2021

Specification No : RPRO-011/2556 (Rev. 2.0) ARC DETECTION SYSTEM

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page or Clarification Letters
	The contact of DC under voltage relay shall be of standard speed, slow dropout characteristic.				
1c.8	Auxiliary tripping and control relays				
	Auxiliary tripping and control relays shall be used to complete the functions of circuit-breaker tripping and closing, trouble alarms, or any indication, etc., as required in these specifications. The relays shall be vibration-proof and shock-proof.				
	All auxiliary tripping and control relays shall be flush mounted where applicable or surface mounted, switchboard type with removable cover and transparent window where applicable.				
	The auxiliary tripping relay shall be of mechanically latched-in type with manual reset device operated from the front of the panel have the operating time and for making not more than 15 ms and for breaking not more than 25 ms .				
	The external auxiliary lock-out relay with manual reset device operated from the front of the panel shall be also accepted				
	Contacts of the tripping relays shall be designed for continuous current carrying capacity of 4 A and 30 A making capacities suitable for their application.				
1c.9	Accessories				
	The arc detection system shall be provided with the following accessories: (1) Terminal blocks with terminals (2) Wiring system (3) Grounding provisions (4) Other according to manufacturer's design				

Table of Compliance



Bid No. : PAT-SCPS01/2021

เงื่อนไขเฉพาะงาน : งานจ้างเหมาปรับปรุงประสิทธิภาพระบบควบคุมสถานีไฟฟ้าด้วยคอมพิวเตอร์ (CSCS) ระยะที่ 4 ตามงบประมาณลงทุนประจำปี 2563 ด้วยวิธีการทางอิเล็กทรอนิกส์

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page										
1	<p>(5)ผู้รับจ้างต้องออกแบบและติดตั้งระบบ SCPS ซึ่งมีคุณสมบัติเป็นไปตามข้อกำหนดดังนี้ (ตาม ADDENDUM ของ Specification No. RSUB-010/2560 (Rev.1.0))</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="width: 50%;">คุณสมบัติ</th> <th style="width: 50%;">ข้อกำหนด</th> </tr> </thead> <tbody> <tr> <td>Network redundancy protocol</td> <td>Parallel Redundancy Protocol (PRP) and/or High Availability Seamless Redundancy (HSR)</td> </tr> <tr> <td>Time synchronization</td> <td>IEEE 1588 or IRIG-B</td> </tr> </tbody> </table>	คุณสมบัติ	ข้อกำหนด	Network redundancy protocol	Parallel Redundancy Protocol (PRP) and/or High Availability Seamless Redundancy (HSR)	Time synchronization	IEEE 1588 or IRIG-B								
คุณสมบัติ	ข้อกำหนด														
Network redundancy protocol	Parallel Redundancy Protocol (PRP) and/or High Availability Seamless Redundancy (HSR)														
Time synchronization	IEEE 1588 or IRIG-B														
2	<p>(6)สำหรับ Ethernet Switch ที่จะนำมาใช้ในระบบ SCPS จะต้องมีคุณสมบัติเป็นไปตามข้อกำหนดดังนี้ (ตาม ADDENDUM ของ Specification No. RSUB-010/2560 (Rev.1.0))</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="width: 50%;">คุณสมบัติ</th> <th style="width: 50%;">ข้อกำหนด</th> </tr> </thead> <tbody> <tr> <td>Conform to the industrial environment performance</td> <td>According to IEEE 1613- class 1 for the Ethernet Switch used in station bus level</td> </tr> <tr> <td>OSI Model Support</td> <td>Ethernet Switch at a station bus level shall be L3 type</td> </tr> <tr> <td>Auxiliary Supply</td> <td>1) 125 VDC nominal voltage (substation DC system) with minimum range 80-120% of nominal voltage, or 2) 230 VAC nominal voltage with $\pm 10\%$ of nominal voltage</td> </tr> <tr> <td>Network Switch and Time Synchronization</td> <td>Transparent Clock</td> </tr> </tbody> </table>	คุณสมบัติ	ข้อกำหนด	Conform to the industrial environment performance	According to IEEE 1613- class 1 for the Ethernet Switch used in station bus level	OSI Model Support	Ethernet Switch at a station bus level shall be L3 type	Auxiliary Supply	1) 125 VDC nominal voltage (substation DC system) with minimum range 80-120% of nominal voltage, or 2) 230 VAC nominal voltage with $\pm 10\%$ of nominal voltage	Network Switch and Time Synchronization	Transparent Clock				
คุณสมบัติ	ข้อกำหนด														
Conform to the industrial environment performance	According to IEEE 1613- class 1 for the Ethernet Switch used in station bus level														
OSI Model Support	Ethernet Switch at a station bus level shall be L3 type														
Auxiliary Supply	1) 125 VDC nominal voltage (substation DC system) with minimum range 80-120% of nominal voltage, or 2) 230 VAC nominal voltage with $\pm 10\%$ of nominal voltage														
Network Switch and Time Synchronization	Transparent Clock														
3	<p>(7)รายละเอียดอุปกรณ์ในระดับ Station Level สำหรับ Network Topology 1 ให้ออกแบบ จัดหาและติดตั้งอุปกรณ์ ดังนี้</p> <p>1)อุปกรณ์ Time Data Server (TDS) ของระบบ SCPS จะต้องมียุกรณ์ GPS Receivers และ GPS Antenna จำนวนอย่างละ 2 ชุด โดยทั้ง 2 ชุด จะต้องทำงานพร้อมกันตลอดเวลาและสามารถทำงานได้ครบถ้วนตาม Spec No. RSUB-010/2560 (Rev. 1.0) ข้อ 7.7 Station Time Synchronization โดยจะต้องมี TDS ทั้ง 2 ชุด ที่สามารถพร้อมทดแทนกันได้ทันทีในกรณีที่อุปกรณ์ TDS ตัวใดตัวหนึ่งมีเหตุให้ไม่สามารถใช้งานได้</p>														
4	<p>(8)ผู้รับจ้างต้องออกแบบและติดตั้งอุปกรณ์ Engineering Workstation (EWS) และ Network Management System (NMS) ทั้ง Hardware และ Software สำหรับทุกสถานีไฟฟ้า โดย Hardware (จะต้องมีพอร์ต) และ Software จะต้องมีความสามารถรองรับการเชื่อมต่อในรูปแบบ Remote access configuration ผ่านระบบ Network ด้วยอุปกรณ์ที่ติดตั้งใช้งานเฉพาะที่สำนักงานใหญ่ ของ กฟภ.</p>														
5 (Protection Management System)	<p>(9)ผู้รับจ้างต้องออกแบบและติดตั้งระบบ Protection Management System (PMS) ทั้ง Hardware และ Software สำหรับทุกสถานีไฟฟ้า โดยอุปกรณ์ Hardware (จะต้องมีพอร์ต) และ Software จะต้องมีความสามารถรองรับการเชื่อมต่อกับอุปกรณ์ Protection Management System (PMS) Server ที่จะติดตั้งใช้งานที่สำนักงานใหญ่ ของ กฟภ. (ซึ่ง กฟภ. มีแผนที่จะติดตั้งใช้งานที่สำนักงานใหญ่ ในอนาคต) ซึ่งระบบจะต้องความสามารถพื้นฐานอย่างน้อยดังต่อไปนี้</p> <ol style="list-style-type: none"> 1)Remote configuration All Relay directly in PEA Substation 2)View device settings and manage change history 3)View and automatic download retrieved fault records, events, and Oscillography All Relay in PEA Substation 4)Store all data in the database 5)Provide web interface to view and download events 6)View reports on screen 7)Print and export reports 8)Securing remote access 9)One user account to access all applications and devices 10)Define access permissions per user, per group, per device 														

Table of Compliance



Bid No. : PAT-SCPS01/2021

เงื่อนไขเฉพาะงาน : งานจ้างเหมาปรับปรุงประสิทธิภาพระบบควบคุมสถานีไฟฟ้าด้วยคอมพิวเตอร์ (CSCS) ระยะที่ 4 ตามงบประมาณลงทุนประจำปี 2563 ด้วยวิธีการทางอิเล็กทรอนิกส์

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
6 (Digital Fault Recorder)	<p>(10)ผู้รับจ้างจะต้องจัดหาพร้อมติดตั้งอุปกรณ์ Digital Fault Recorder (DFR) สำหรับสถานีไฟฟ้าจำนวน 3 สถานี ไฟฟ้าอ่างทอง 1 สถานีไฟฟ้าลาดบัวหลวง สถานีไฟฟ้าบางปะอิน 3 สถานีไฟฟ้าวังน้ำเย็น สถานีไฟฟ้าบางปลา สถานีไฟฟ้าด่านช้าง สถานีไฟฟ้าเขาย้อย 1 และสถานีไฟฟ้าปัตตานี 2 โดยมีรายละเอียดคุณสมบัติ ดังนี้</p> <p>1)อุปกรณ์ Digital Fault Recorder ต้องมีคุณสมบัติทางเทคนิคและฟังก์ชันการทำงานตามที่ระบุไว้ใน Annex 10 – Digital Fault Recorder (DFR) Specification ของสเปคเลขที่ RSUB-010/2560 (Rev. 1.0)</p> <p>2)อุปกรณ์ Digital Fault Recorder จะต้องประกอบด้วย Hardware (จะต้องมีพอร์ต) และ Software ที่มีความสามารถรองรับการเชื่อมต่อและใช้งานร่วมกับ Data Server for Digital Fault Recorder (DFR) (ซึ่ง กฟภ. มีแผนที่จะติดตั้งใช้งานที่สำนักงานใหญ่ ในอนาคต) ได้ โดยระบบจะต้องความสามารถพื้นฐานดังต่อไปนี้</p> <ul style="list-style-type: none"> - Remote configuration - View device settings and manage change history - View and download retrieved fault records <p>3)อุปกรณ์ Digital Fault Recorder ต้องมีรูปแบบการนำสัญญาณเข้า ตามที่ระบุไว้ในเงื่อนไขเฉพาะงาน</p>				
7 (Cyber Security Management System)	<p>(11)ผู้รับจ้างจะต้องออกแบบ จัดหาและติดตั้ง ระบบการรักษาความมั่นคงปลอดภัยไซเบอร์ (Cyber Security) โดยมีรายละเอียด ดังนี้</p> <p>(11.1)ระบบการรักษาความมั่นคงปลอดภัยไซเบอร์ (Cyber Security)จะต้องสามารถดำเนินการร่วมกับระบบเทคโนโลยีสารสนเทศ รวมทั้งสอดคล้องกับนโยบายและแนวปฏิบัติความมั่นคงปลอดภัยสำหรับสารสนเทศของ กฟภ. (PEA Cyber Security) โดยการดำเนินการให้เป็นไปตาม ANNEX 7 – Cyber Securities Requirements ของสเปคเลขที่ RSUB-010/2560 (Rev. 1.0) ทั้งนี้ กฟภ. ขอสงวนสิทธิ์ในการตรวจสอบและปรับปรุงระบบ Cyber Security ดังกล่าว ที่ผู้รับจ้างออกแบบมา โดยผู้รับจ้างต้องรับผิดชอบค่าใช้จ่ายในการปรับปรุงระบบ (ถ้ามี)</p> <p>(11.2)ผู้รับจ้างจะต้องออกแบบ จัดหาและติดตั้งระบบการรักษาความมั่นคงปลอดภัยไซเบอร์ (Cyber Security) จะต้องประกอบด้วย Hardware และ Software โดยจะต้องออกแบบการป้องกัน (Security perimeters) ให้แบ่งเครือข่ายออกเป็น 3 ส่วน เป็นอย่างน้อย ดังนี้ (ตามรูปที่ 2)</p> <ol style="list-style-type: none"> 1)SCPS Engineering Network 2)SCADA Gateway Network (สำหรับส่งข้อมูลขึ้นศูนย์ฯ) 3)Remote Access Server (DMZ) (สำหรับการทำ Remote Access และ File Transfer) 				
	<p>(11.3)ระบบการรักษาความมั่นคงปลอดภัยไซเบอร์ (Cyber Security) จะต้องความสามารถพื้นฐานอย่างน้อย ดังต่อไปนี้</p> <ol style="list-style-type: none"> 1)NG Firewall that detects ICS protocols 2)IDS/IPS 3)Strong remote access authentication (ทำผ่านเครื่อง Remote Access Server ในวง DMZ เท่านั้น และรองรับ Multi-Factor Authentication) 4)Security perimeters (สามารถแบ่งเครือข่ายออกเป็นอย่างน้อย 3 ส่วน ได้แก่ 1. SCPS Network, 2. SCADA Network (สำหรับส่งข้อมูลขึ้นศูนย์ฯ) และ 3. DMZ (สำหรับการทำ Remote Access และ File Transfer)) 5)Role-based access control 6>User authentication 7>Password management 8)Security event monitoring 9)System performance monitoring 10)Patch management 11)Configuration management 12)System hardening 13)Unused ports/drives disabled 14)Backup and recovery 15)Anti-virus 				

Table of Compliance



Bid No. : PAT-SCPS01/2021

เงื่อนไขเฉพาะงาน : งานจ้างเหมาปรับปรุงประสิทธิภาพระบบควบคุมสถานีไฟฟ้าด้วยคอมพิวเตอร์ (CSCS) ระยะที่ 4 ตามงบประมาณลงทุนประจำปี 2563 ด้วยวิธีการทางอิเล็กทรอนิกส์

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page																				
8	(16)สำหรับ 115 kV Line Protection, 115 kV Transformer Protection และ 115 kV Bus Protection จะต้องเป็นแบบ Double Main Protection ทั้งนี้อุปกรณ์ทั้ง Main 1 และ Main 2 จะต้องต่างผลิตภัณฑ์กัน																								
9	(17)อุปกรณ์ 22 kV หรือ 33 kV Protection Relay and Bay Control Unit ต้องเป็นอุปกรณ์ตัวเดียวกันในทุกเบย์																								
10	(18)ผู้รับจ้างต้องจัดหาอุปกรณ์และออกแบบฟังก์ชัน Simultaneous Fault สำหรับระบบ 22 kV และ 33 kV ให้ครบถ้วนตามที่ กฟภ. กำหนดโดยให้ใช้สัญญาณ GOOSE ตามมาตรฐาน IEC 61850 ในการแลกเปลี่ยนข้อมูลระหว่างอุปกรณ์ เพื่อใช้ในการสร้างลจิกของฟังก์ชันดังกล่าว พร้อมทั้งติดตั้ง Cut-Off Switch (Enable/Disable) ที่ตู้ Incoming บัสละ 1 ตัว																								
11	(19)ในส่วนของ 22 kV Capacitor ต้องดำเนินการติดตั้งอุปกรณ์จำนวน 2 ชุด (ตามที่ระบุในตารางรายการแจ้งปริมาณงาน (Bill of Materials) ของแต่ละสถานีไฟฟ้า) ดังนี้ 1)ออกแบบและติดตั้งอุปกรณ์ Protection Relay and Bay Control Unit จำนวน 1 Set ที่ผ้าตู้ CVB-01 และ 2)ออกแบบและติดตั้งอุปกรณ์ Bay Control Unit (BCU) จำนวน 1 Set ต่อ Capacitor Bank 1 ชุดภายในห้อง Capacitor Bank																								
12	(20)ผู้รับจ้างต้องออกแบบให้มีการติดตั้งอุปกรณ์ Lockout Relay สำหรับ 115 kV Bus Protection, 115 kV Transformer Protection Main 1 และ 115 kV Transformer Protection Main 2 โดยให้ผู้รับจ้างเลือกใช้เป็นผลิตภัณฑ์ที่ กฟภ. เคยใช้งานและได้รับความเห็นชอบจาก กฟภ. โดยมีรายละเอียดดังนี้ (20.1) Lockout Relay (อย่างน้อย 20 Contact และเพียงพอต่อติดตั้งใช้งานตามจำนวนวงจรจริงของสถานีไฟฟ้า) ต่อ 1 บัส เพื่อทำหน้าที่ Trip และ Block Close สำหรับ 115 kV Busbar Protection (20.2) Lockout Relay (อย่างน้อย 20 Contact และเพียงพอต่อติดตั้งใช้งานตามจำนวนวงจรจริงของสถานีไฟฟ้า) ต่อ 1 วงจร (Main 1 และ Main 2) เพื่อทำหน้าที่ Trip และ Block Close สำหรับ 115 kV Transformer Protection																								
13	(21)ฟังก์ชัน 50BF สำหรับระบบ 22 kV หรือ 33 kV จะต้องออกแบบให้ใช้อุปกรณ์ Lockout Relay (อย่างน้อย 20Contact และเพียงพอต่อติดตั้งใช้งานตามจำนวนวงจรจริงของสถานีไฟฟ้า) ต่อ 1 บัส เพื่อทำหน้าที่ Trip ผ่านทาง Hardwire ไปยัง Feeder อื่นๆ โดยให้ผู้รับจ้างเลือกใช้เป็นผลิตภัณฑ์ที่ กฟภ. เคยใช้งานและได้รับความเห็นชอบจาก กฟภ. ทั้งนี้สำหรับสถานีไฟฟ้าที่มีระบบ 22 kV หรือ 33 kV จำนวน 3 บัส นั้น อุปกรณ์ Lockout Relay ของบัสที่ 2 จะต้องมีอย่างน้อย 30 Contact																								
14	(22)ผู้รับจ้างต้องออกแบบให้มีการติดตั้งอุปกรณ์ Trip Circuit Supervision Relay แยกสำหรับระบบ 115 kV ซึ่งจะต้องครอบคลุมจำนวนวงจรทริปของทุกเบย์ โดยให้ผู้รับจ้างเลือกใช้เป็นผลิตภัณฑ์ที่ กฟภ. เคยใช้งาน และได้รับความเห็นชอบจาก กฟภ.																								
15	(23)ผู้รับจ้างต้องออกแบบให้มีการติดตั้งอุปกรณ์ 27X (Under Voltage Relay) สำหรับ DC Circuits ของทุกเบย์ และทุกฟีดเดอร์ในแต่ละวงจรให้ครบถ้วนของทุกวงจรโดยให้เลือกใช้เป็นผลิตภัณฑ์ที่ กฟภ. เคยใช้งาน และได้รับความเห็นชอบจาก กฟภ.																								
16	(24)ผู้รับจ้างต้องออกแบบให้มีการติดตั้งอุปกรณ์ Relay Test Block สำหรับ Protection Circuit โดยมีรายละเอียดดังนี้																								
	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>รูปแบบ</th> <th>ตำแหน่งที่ติดตั้ง</th> <th>Test Block</th> <th>สำหรับวงจร</th> <th>ชนิด</th> </tr> </thead> <tbody> <tr> <td rowspan="4">Topology 1</td> <td rowspan="2">115 kV Protection and Control Panel</td> <td>No. 1</td> <td>AC Circuit, VT และ CT</td> <td>Type02</td> </tr> <tr> <td>No. 2</td> <td>DC Circuit, Trip coil 1&2</td> <td>Type01</td> </tr> <tr> <td rowspan="2">22 kV Switchgear</td> <td>No. 1</td> <td>VT และ CT</td> <td>Type 02</td> </tr> <tr> <td>No. 2</td> <td>DC Circuit</td> <td>Type01</td> </tr> </tbody> </table>	รูปแบบ	ตำแหน่งที่ติดตั้ง	Test Block	สำหรับวงจร	ชนิด	Topology 1	115 kV Protection and Control Panel	No. 1	AC Circuit, VT และ CT	Type02	No. 2	DC Circuit, Trip coil 1&2	Type01	22 kV Switchgear	No. 1	VT และ CT	Type 02	No. 2	DC Circuit	Type01				
รูปแบบ	ตำแหน่งที่ติดตั้ง	Test Block	สำหรับวงจร	ชนิด																					
Topology 1	115 kV Protection and Control Panel	No. 1	AC Circuit, VT และ CT	Type02																					
		No. 2	DC Circuit, Trip coil 1&2	Type01																					
	22 kV Switchgear	No. 1	VT และ CT	Type 02																					
		No. 2	DC Circuit	Type01																					

Table of Compliance



Bid No. : PAT-SCPS01/2021

เงื่อนไขเฉพาะงาน : งานจ้างเหมาปรับปรุงประสิทธิภาพระบบควบคุมสถานีไฟฟ้าด้วยคอมพิวเตอร์ (SCSCS) ระยะที่ 4 ตามงบประมาณลงทุนประจำปี 2563 ด้วยวิธีการทางอิเล็กทรอนิกส์

Clause No.	Clause Name	Conformance Status (C,A or N)	Standard Equipment Status (S or M)	Proposed Data	Referred to Page
17	(25)สำหรับระบบ 115 kV ผู้รับจ้างจะต้องดำเนินการจัดหาติดตั้ง Control Cable และ External Cable สำหรับวงจรต่างๆ ต่อไปนี้ ให้ครบถ้วนตามความต้องการของระบบ SCPS ที่ติดตั้งใหม่ 1)Secondary current transformer circuits 2)Secondary voltage transformer circuit 3)Substation equipment DC or AC Control circuits 4)Status and alarm circuit 5)Power supply circuit				
18	(26)สำหรับสถานีไฟฟ้าขนาด 3 และสถานีไฟฟ้าบางปลา ให้ดำเนินการรื้อถอนอุปกรณ์ระบบ Arc Protection ของเดิมออก พร้อมทั้งจัดหาอุปกรณ์, ออกแบบและติดตั้งระบบ Arc Protection ใหม่ที่เป็นแบบตรวจจับด้วยแสงและกระแสฟอลต์ โดยมีรายละเอียด ดังนี้ 1)งานออกแบบดังกล่าวต้องจัดทำเป็นแบบ Wiring Diagram เพื่อแสดงการ Wiring สายต่างๆ รวมทั้งคำนวณค่าการทำงานของรีเลย์ (Relay Setting) ออกแบบ Logic และกำหนดฟังก์ชันการทำงาน โดยทั้งหมดต้องได้รับความเห็นชอบจาก กฟผ. ว่าสามารถใช้งานได้แล้วเท่านั้น 2)อุปกรณ์ระบบป้องกัน Arc Protection จะต้องรองรับการใช้งานกับสถานีไฟฟ้าที่มีพิกัดกระแสของหม้อแปลงกระแสไฟฟ้า (Rated Current) ที่ 1 (หนึ่ง) Amp หรือ 5 (ห้า) Amp 3)อุปกรณ์ระบบป้องกัน Arc Protection System จะต้องสามารถเชื่อมต่อกับระบบ SCPS ได้ด้วย 4)อุปกรณ์ระบบป้องกัน Arc Protection System ต้องเป็นอุปกรณ์ที่แยกจาก Protection Relay and Bay Control Unit				
19 (Inverter)	(29)Inverter ที่จะนำมาติดตั้งใช้งาน จะต้องเป็นไปตามข้อกำหนดดังนี้ (29.1) ขนาดพิกัดInverter ไม่น้อยกว่า 4,000 VA, Output Power ไม่น้อยกว่า 3,200 W สามารถรองรับโหลดของอุปกรณ์ที่ Station Level ได้แก่ อุปกรณ์ Industrial Computer, Monitor, Printer และ Ethernet Switch (กรณีที่ได้รับไฟ AC) เป็นต้น				
20	(31)ผู้รับจ้างต้องรับผิดชอบการปรับปรุงวงจรตู้ DC Board และ AC Board ให้สามารถใช้งานได้ครบถ้วนและเพียงพอกับการใช้งานสำหรับอุปกรณ์ SCPS ที่ติดตั้งใหม่ทั้งหมดทุกวงจร รวมถึงกรณีที่จะต้องจัดหาอุปกรณ์เพิ่มเติมด้วย ยกตัวอย่างเช่น MCB, External Cable และ Name Plate เป็นต้น				
21	(32)การตั้งค่าและรูปแบบการทำงานของ GoCB (GOOSE Control Block) ต้องเป็นไปตามที่มาตรฐาน IEC 61850 กำหนด โดยต้องมี MAC Address ของ GoCB อยู่ในช่วงดังต่อไปนี้ และต้องไม่ใช่ Address ซ้ำกัน				